



🕳 Sample &

🖥 Buy







RF430CL331H

ZHCSE57A-SEPTEMBER 2015-REVISED NOVEMBER 2015

RF430CL331H NFC 类型 4B 动态双接口应答器

1 器件概述

Texas

INSTRUMENTS

1.1 特性

- 通过直通操作向主机控制器发送数据更新和请求
- I²C 接口允许对内部静态随机存取存储器 (SRAM) 进行读写操作
- 预取、缓存和自动应答 特性 提高数据吞吐量
- 支持数据流

1.2 应用

- 无线固件更新
- Wi-Fi[®]和 *Bluetooth*[®]配对

- 最高可自动处理层 4 上的所有射频 (RF) 通信
- 支持最大的 NFC 数据交换格式 (NDEF) 消息
- 符合 ISO/IEC 14443B 标准
- 支持高达 848kbps 的传输速率
- 服务接口
- 无线传感器接口

1.3 说明

德州仪器 (TI) 动态近场通信 (NFC)/射频识别 (RFID) 接口应答器 RF430CL331H 是一款 NFC 标签类型 4 器件,可结合一个非接触式 NFC/RFID 接口和一个有线 I²C 接口将器件连接到主机。NDEF 消息可通过集成的 I²C 串行通信接口读写,也可通过支持高达 848kbps 速率的集成 ISO/IEC 14443 标准类型 B RF 接口进行非接触式访问或更新。

该器件按主机控制器的需求请求响应 NFC 类型 4 命令,每次仅在其缓存中存储部分 NDEF 消息。这使得 NDEF 消息的大小仅受主机控制器的存储器容量以及规范的限制。

该器件支持读缓存、预取和写自动确认 功能, 可提高数据吞吐量。

该器件可利用简单而直观的 NFC 连接切换来替代载波方式,只需一次点击操作即可完成诸如 Bluetooth[®], Bluetooth[®]低功耗 (BLE) 或 Wi-Fi 的配对过程或认证过程。

作为一个常见 NFC 接口, RF430CL331H 使得终端设备能够与启用 NFC 的智能手机、平板电脑和笔记本电脑这类快速发展的基础设施进行通信。

	奋忤乍息、 ¹⁷	
部件号	封装	封装尺寸 (2)
RF430CL331HIPW	TSSOP (14)	5mm x 4.4mm
RF430CL331HRGT	VQFN (16)	3mm x 3mm

四件合百 (1)

(1) 要获得所有可用器件的最新部件、封装和订购信息,请参见封装选项附录(节8)或浏览 TI 网站 www.ti.com。

(2) 这里显示的尺寸为近似值。要获得包含误差值的封装尺寸,请参见机械数据(节8中)。

1.4 典型应用

图 1-1 给出了典型应用。



图 1-1. 典型应用

内容

1	器件	概述1	
	1.1	 特性1	
	1.2	 应用 1	
	1.3	 说明1	
	1.4	 典型应用 2	
2	修订		
3	Term	ninal Configuration and Functions $\frac{1}{4}$	
	3.1	Pin Diagrams 4	
	3.2	Pin Attributes	
	3.3	Signal Descriptions6	
	3.4	Pin Multiplexing6	
	3.5	Connections for Unused Pins	
4	Spec	cifications	6
	4.1	Absolute Maximum Ratings 7	
	4.2	ESD Ratings	
	4.3	Recommended Operating Conditions	7
	4.4	Recommended Operating Conditions, Resonant Circuit	
	4.5	Supply Currents	
	4.6	Electrical Characteristics, Digital Inputs	
	4.7	Electrical Characteristics, Digital Outputs	
	4.8	Thermal Characteristics	
	4.9	Timing and Switching Characteristics 10	
5	Deta	iled Description	
		• –	C

5.1 Overview 12 5.2 Functional Block Diagram 12 Terms and Acronyms 12 5.3 Serial Communication Interface...... 12 5.4 5.5 5.6 5.7 NFC Type 4B Tag Platform 16 5.8 NDEF Structure 19 5.9 5.10 RF Command Response Timing Limits 33 5.11 5.12 Applications, Implementation, and Layout...... 49 6.1 Application Diagram 49 6.2 References 49 器件和文档支持 50 7.1 器件支持...... 50 7.2 文档支持...... 51 7.3 社区资源..... 51 7.4 商标......51 7.5 静电放电警告 52 7.6 出口管制提示 52 7.7 机械、封装和可订购信息...... 52

2 修订历史记录

Chan	ges from September 29, 2015 to November 30, 2015 P	age
•	Deleted "Suggested to be set to 0x3B" from Step 7(a)	<u>34</u>
•	"When the internal state machine determines"	46

3 Terminal Configuration and Functions

3.1 Pin Diagrams

Figure 3-1 shows the pinout for the 14-pin PW package.





Figure 3-2 shows the pinout for the 16-pin RGT package.







3.2 **Pin Attributes**

PIN NUMBER							
PW	RGT	SIGNAL NAME	SIGNAL I TPE	BUFFER ITPE '		RESETSTATE	
1	15	VCC	PWR	Power	VCC	N/A	
2	1	ANT1	RF	Analog	-	N/A	
3	2	ANT2	RF	Analog	-	N/A	
4	3	RST	I	LVCMOS	VCC	PU	
5	4	E0	I	LVCMOS	VCC	OFF	
6	5	E1	I	LVCMOS	VCC	OFF	
7	6	E2	I	LVCMOS	VCC	OFF	
8	7	INTO	0	LVCMOS	VCC	OFF	
9	8	I2C_READY	0	LVCMOS	VCC	DRIVE1	
10	9	I2C_SIGNAL	0	LVCMOS	VCC	DRIVE1	
11	10	SCL	I/O	LVCMOS	VCC	OFF	
12	11	SDA	I/O	LVCMOS	VCC	OFF	
13	12	VCORE	PWR	Power	VCC	N/A	
14	13	VSS	PWR	Power	VCC	N/A	
-	14	NC	-	-	-	-	
-	16	NC	-	_	_	-	

Table 3-1. Pin Attributes

Signal Types: I = Input, O = Output, I/O = Input or Output, PWR = Power, RF = Radio frequency Buffer Types: See Table 3-3 for details. (1)

(2) (3) Reset States:

OFF = High-impedance input with pullup or pulldown disabled (if available) PD = High-impedance input with pulldown enabled

PU = High-impedance input with pullup enabledDRIVE0 = Drive output lowDRIVE1 = Drive output high

N/A = Not applicable

3.3 Signal Descriptions

Table 3-2 describes the signals.

FUNCTION	FUNCTION SIGNAL NAME		PIN NUMBER		DESCRIPTION
		PW	RGT		
	VCC	1	15	PWR	3.3-V power supply
Power	VCORE	13	12	PWR	Regulated core supply voltage
	VSS	14	13	PWR	Ground supply
DE	ANT1	2	1	RF	Antenna input 1
ĸŗ	ANT2	3	2	RF	Antenna input 2
	E0	5	4	I	I ² C address select 0
	E1	6	5	I	I ² C address select 1
	E2	7	6	I	I ² C address select 2
Serial	I2C_READY	9	8	0	High indicates that I^2C communication can be started. Low indicates that I^2C communication must not be started.
Communication	I2C_SIGNAL	10	9	0	Low indicates that a wait time extension command is automatically being sent. I ² C communication does not have to be stopped.
	SCL	11	10	I/O	I ² C clock
	SDA	12	11	I/O	I ² C data
Quatan	INTO	8	7	0	Interrupt output
System	RST	4	3	I	Reset input (active low) (2)
No connect	NC	-	14 16	_	Leave open, no connection

Table 3-2. Signal Descriptions

(1) I = Input, O = Output, PWR = Power, RF = RF antenna

(2) With integrated pullup

3.4 Pin Multiplexing

None of the pins on this device are multiplexed.

Table 3-3. Buffer Type

BUFFER TYPE (STANDARD)	NOMINAL VOLTAGE	HYSTERESIS	PU OR PD	NOMINAL PU OR PD STRENGTH (μΑ)	OUTPUT DRIVE STRENGTH (mA)	OTHER CHARACTERISTICS
LVCMOS	3.3 V	Y	N/A	See Section 4.6, Electrical Characteristics, Digital Inputs	See Section 4.7, Electrical Characteristics, Digital Outputs	
Analog, RF	3.3 V	Ν	N/A	N/A	N/A	See analog modules in Section 4, Specifications, for details
Power	3.3 V	Y with SVS on	N/A	N/A	N/A	

3.5 Connections for Unused Pins

Leave no connect (NC) pins unconnected.

Leave unused outputs unconnected.

Drive or pull unused inputs high or low.



Specifications 4

Absolute Maximum Ratings (1) (2) 4.1

	MIN	MAX	UNIT
Voltage applied at V_{CC} referenced to V_{SS} (V_{AMR})	-0.3	4.1	V
Voltage applied at V_{ANT} referenced to V_{SS} (V_{AMR})	-0.3	4.1	V
Voltage applied to any pin (references to V _{SS})	-0.3	V _{CC} + 0.3	V
Diode current at any device pin		±2	mA
Storage temperature, T _{stg} ⁽³⁾	-40	125	°C

(1) Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

All voltages are referenced to VSS.

For soldering during board manufacturing, it is required to follow the current JEDEC J-STD-020 specification with peak reflow (3) temperatures not higher than classified on the device label on the shipping boxes or reels.

4.2 ESD Ratings

			VALUE	UNIT
V _(ESD) Electrostatic discharge	Electrostatia discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001 (1)		V
	Electrostatic discharge	Charged-device model (CDM), per JEDEC specification JESD22-C101 (2)	±500	V

JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process. (1)

JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process. (2)

4.3 **Recommended Operating Conditions**

Typical values are specified at V_{CC} = 3.3 V and T_A = 25°C (unless otherwise noted)

			MIN	NOM	MAX	UNIT
V _{CC} Su	Supply voltage	During program execution no RF field present	3.0	3.3	3.6	V
	Supply voltage	During program execution with RF field present	2.0	3.3	3.6	
V _{SS}	Supply voltage (GND reference)			0		V
T _A	Operating free-air temperature		-40		85	°C
C ₁	Decoupling capacitor on V _{CC} ⁽¹⁾			0.1		μF
C ₂	Decoupling capacitor on V _{CC} ⁽¹⁾			1		μF
C _{VCORE}	Capacitor on V _{CORE} (1		0.1	0.47	1	μF

(1) Low ESR (equivalent series resistance) capacitor

4.4 **Recommended Operating Conditions, Resonant Circuit**

		MIN	NOM	MAX	UNIT
f _c	Carrier frequency		13.56		MHz
V _{ANT_peak}	Antenna input voltage			3.6	V
Z	Impedance of LC circuit	6.5		15.5	kΩ
L _{RES}	Coil inductance ⁽¹⁾		2.66		μH
C _{RES}	Total resonance capacitance ⁽¹⁾ , $C_{RES} = C_{IN} + C_{Tune}$		51.8		pF
C _{Tune}	External resonance capacitance	C _{RE}	_S – C _{IN} ⁽²⁾		pF
QT	Tank quality factor		30		

The coil inductance of the antenna L_{RES} with the external capacitance C_{Tune} plus the device internal capacitance C_{IN} is a resonant circuit. The resonant frequency of this LC circuit must be close to the carrier frequency f_c: f_{RES} = 1 / [2π(L_{RES}C_{RES})^{1/2}] = 1 / [2π(L_{RES}(C_{IN}+C_{Tune}))^{1/2}] ≈ f_c
 (2) For C_{IN} refer to Section 4.9.3.

4.5 Supply Currents

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

	PARAMETER	TEST CONDITIONS	v _{cc}	MIN	ΓYΡ	MAX	UNIT
I _{CC(I2C)}	I ² C, 400 kHz, Writing into NDEF memory		3.3 V		250		μA
I _{CC(RF enabled)}	RF enabled, no RF field present		3.3 V		40		μA
I _{CC(Inactive)}	Standby enable = 0, RF disabled, no serial communication		3.3 V		15		μA
I _{CC(Standby)}	Standby enable = 1, RF disabled, no serial communication		3.3 V		10	45	μA
$\Delta I_{CC(StrongRF)}$	Additional current consumption with strong RF field present		3.0 V to 3.6 V			160	μA
I _{CC(RF,lowVCC)}	Current drawn from VCC < 3.0 V with RF field present (passive operation)		2.0 V to 3.0 V			0	μA

4.6 Electrical Characteristics, Digital Inputs

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

	PARAMETER	TEST CONDITIONS	V _{cc}	MIN	TYP	MAX	UNIT
V _{IL}	Low-level input voltage					0.3 × V _{CC}	V
V _{IH}	High-level input voltage			0.7 × V _{CC}			V
V _{HYS}	Input hysteresis			0.1 × V _{CC}			V
IL	High-impedance leakage current		3.3 V	-50		50	nA
R _{PU(RST)}	Integrated RST pullup resistor			20	35	50	kΩ

4.7 Electrical Characteristics, Digital Outputs

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

	PARAMETER	TEST CONDITIONS	V _{cc}	MIN	AX	UNIT
			3 V		0.4	
V _{OL}	Output low voltage	I _{OL} = 3 mA	3.3 V		0.4	V
			3.6 V		0.4	
V _{OH}	Output high voltage	I _{OH} = -3 mA	3 V	2.6		
			3.3 V	2.9		V
			3.6 V	3.2		



www.ti.com.cn

4.8 Thermal Characteristics

over operating free-air temperature range (unless otherwise noted)

PARAMETER					
$R\theta_{JA}$	Junction-to-ambient thermal resistance, still air ⁽¹⁾		116.0	°C/W	
$R\theta_{JC(TOP)}$	Junction-to-case (top) thermal resistance ⁽²⁾		45.1	°C/W	
$R\theta_{JB}$	Junction-to-board thermal resistance ⁽³⁾	TSSOP-14 (PW)	57.6	°C/W	
Ψ_{JB}	Junction-to-board thermal characterization parameter		57.0	°C/W	
Ψ_{JT}	Junction-to-top thermal characterization parameter		4.6	°C/W	
$R\theta_{JA}$	Junction-to-ambient thermal resistance, still air ⁽¹⁾		48.8	°C/W	
$R\theta_{JC(TOP)}$	Junction-to-case (top) thermal resistance ⁽²⁾		60.8	°C/W	
Rθ _{JC(BOT)}	Junction-to-case (bottom) thermal resistance ⁽⁴⁾		7.1	°C/W	
$R\theta_{JB}$	Junction-to-board thermal resistance ⁽³⁾	VQFN-16 (RGT)	21.9	°C/W	
Ψ_{JB}	Junction-to-board thermal characterization parameter		21.9	°C/W	
Ψ_{JT}	Junction-to-top thermal characterization parameter		1.5	°C/W	

(1) The junction-to-ambient thermal resistance under natural convection is obtained in a simulation on a JEDEC-standard, High-K board, as specified in JESD51-7, in an environment described in JESD51-2a.

(2) The junction-to-case (top) thermal resistance is obtained by simulating a cold plate test on the package top. No specific JEDEC standard test exists, but a close description can be found in the ANSI SEMI standard G30-88.

(3) The junction-to-board thermal resistance is obtained by simulating in an environment with a ring cold plate fixture to control the PCB temperature, as described in JESD51-8.

(4) The junction-to-case (bottom) thermal resistance is obtained by simulating a cold plate test on the exposed (power) pad. No specific JEDEC standard test exists, but a close description can be found in the ANSI SEMI standard G30-88.

4.9 Timing and Switching Characteristics

4.9.1 Reset Timing

Table 4-1. I²C Power-up Timing

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

PARAM	TER MIN MA		т
t _{Ready} Time after power up or reset until device	is ready to communicate using I ² C ⁽¹⁾ 2	ms	;

(1) The device is ready to communicate after $t_{Ready}(MAX)$ at the latest.

4.9.2 Serial Communication Protocol Timing

Table 4-2. I²C Interface

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted) (see Figure 4-1)

	PARAMETER	TEST CONDITIONS	V _{cc}	MIN	MAX	UNIT
feet	SCL clock frequency (with Master supporting clock stretching according to I^2 C standard, or when the device is not being addressed)		3.3 V	0	400	kHz
SUL	SCL clock frequency (device being addressed by Master not	Write	3.3 V	0	120	
	supporting clock stretching)	Read	3.3 V	0	100	
t _{HD,STA}	Hold time (repeated) START	f _{SCL} ≤ 100 kHz	221/	4		μs
	Hold liftle (repeated) START	f _{SCL} > 100 kHz	3.3 V	0.6		
	Satur time for a repeated START	f _{SCL} ≤ 100 kHz	2.2.1/	4.7		μs
^I SU,STA	Setup time for a repeated START	f _{SCL} > 100 kHz	3.3 V	0.6		
t _{HD,DAT}	Data hold time		3.3 V	0		ns
t _{SU,DAT}	Data setup time		3.3 V	250		ns
t _{SU,STO}	Setup time for STOP		3.3 V	4		μs
t _{SP}	Pulse duration of spikes suppressed by input filter		3.3 V	6.25	75	ns



Figure 4-1. I²C Mode Timing



4.9.3 RF143B NFC/RFID Analog Front End

Table 4-3. Recommended Operating Conditions

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
V _{DDH}	Antenna rectified voltage	Peak voltage limited by antenna limiter	3.0	3.3	3.6	V
I _{DDH}	Antenna load current	RMS, without limiter current			100	μA
CIN	Input capacitance	ANT1 to ANT2, 2 V RMS	31.5	35	38.5	pF

Table 4-4. ISO/IEC 14443B ASK Demodulator

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

	PARAMETER	MIN	TYP	MAX	UNIT
DR ₁₀	Input signal data rate 10% downlink modulation, 7% to 30% ASK, ISO1443B		106	848	kbps
m10	Modulation depth 10%, tested as defined in ISO/IEC 10373-6	7%		30%	

Table 4-5. ISO/IEC 14443B-Compliant Load Modulator

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

	PARAMETER	MIN	TYP	MAX	UNIT
f _{PICC}	Uplink subcarrier modulation frequency	0.2		1	MHz
V _{A_MOD}	Modulated antenna voltage, $V_{A_unmod} = 2.3 V$	0.5			V
V _{SUB14}	Uplink modulation subcarrier level, ISO/IEC 14443B: H = 1.5 to 7.5 A/m	22/H ^{0.5}			mV

Table 4-6. Power Supply

over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_{LIM}	Limiter clamping voltage	I _{LIM} ≤ 70 mA RMS, f = 13.56 MHz	3.0		3.6	V _{pk}
I _{LIM,MAX}	Maximum limiter current				70	mA

5 Detailed Description

5.1 Overview

5.2 Functional Block Diagram



5.3 Terms and Acronyms

表 5-1 describes the terms and acronyms used in this document.

表 5-1. Term Definitions

NAME	DESCRIPTION
PCD	Proximity coupling device, such as NFC enabled handset, NFC/RFID reader/writer devices
PICC	Proximity integrated circuit card, dynamic tag, RF430CL331H IC
NFC Type 4 command	See the NFC Forum Type 4 Tag Operation Specification (http://nfc-forum.org/) for details
PICC Buffer	This is a memory range (0 through 2999) that is accessible through the I ² C bus, where buffer data is stored.
Host Controller	This is a MCU or processor connected to the PICC through the I^2C bus. It responds to all the of Type 4 data requests that come from the PICC.
SW	Type 4 command acknowledgments, referred also as SW1 and SW2 (status word). Refer to NFC/RFID and ISO14443-B specifications for details.
SWTX or S(WTX)	Frame wait time extension. When the RF430CL331H cannot respond to a command that PCD sends, it must send a S(WTX) request indicating that it needs more time. The PCD then responds and the RF430CL331H has the negotiated time that it requested.

5.4 Serial Communication Interface

The serial interface of this device is I^2C . The serial interface allows a connected MCU to configure the device and write to and read from the available registers and the RAM buffer on the RF430CL331H.



5.5 Communication Protocol

The tag is programmed and controlled by writing data into and reading data from the address map shown in $\frac{1}{5}$ 5-2 through the I²C serial interface.

RANGE	ADDRESS	SIZE	DESCRIPTION
	0xFFFE	2 B	Control register
	0xFFFC	2 B	Status register
	0xFFFA	2 B	Interrupt Enable
	0xFFF8	2 B	Interrupt Flags
	0xFFF6	2 B	CRC Result (16-bit CCITT)
	0xFFF4	2 B	CRC Length
	0xFFF2	2 B	CRC Start Address
	0xFFF0	2 B	Communication Watchdog Control register
	0xFFEE	2 B	Version
Registers	0xFFEC	2 B	NDEF File ID register
	0xFFEA	2 B	Host Response register
	0xFFE8	2 B	NDEF Block Length register
	0xFFE6	2 B	NDEF File Offset register
	0xFFE4	2 B	Buffer Start register
	0xFFE2	2 B	Reserved
	0xFFE0	2 B	Reserved
	0xFFDE	2 B	SWTX register
	0xFFDC	2 B	Reserved
	0xFFDA	2 B	Custom SW1 and SW2 Response
Deserved	0x4000 to 0xFFDF		Reserved
Reserved	0x0BB8 to 0x3FFF	13KB	Reserved (for example, for future extension of NDEF Memory size)
Buffer	0x0000 to 0x0BB7	3000 B	Buffer Memory

表 5-2. User Address Map

注

Crossing range boundaries causes writes to be ignored and reads to return undefined data.

5.6 I²C Protocol

A command is always initiated by the master by addressing the device using the specified l^2C device address. The device address is a 7-bit l^2C address. The upper 4 bits are hard-coded, and the lower 3 bits are programmable by the input pins E0, E1, and E2 (see $\frac{1}{8}$ 5-3).

表 5-3. I²C Device Address

BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0
0	0	1	1	E2	E1	E0
MSB						LSB

To write data, the device is addressed using the specified I²C device address with R/W = 0, followed by the upper 8 bits of the first address to be written and the lower 8 bits of that address. Next (without a repeated START), the data to be written starting at the specified address is received. With each data byte received, the address is automatically incremented by 1. The write access is terminated by the STOP condition on the I²C bus.



1 byte cause the data to be ignored. Avoid a transaction less than 1 data byte, as it results in an error.

To read data, the device is addressed using the specified I²C device address with R/W = 0, followed by the upper 8 bits of the first address to be read and then the lower 8 bits of that address. Next, a repeated START condition is expected with the I²C device address and R/W = 1. The device then transmit data starting at the specified address until a not acknowledge (NACK) and a STOP condition are received.





5.6.1 PC Examples

8 5-4 and 8 5-5 show examples of l^2C accesses to the Control and Status registers, respectively. Comments are provided on the tags in the figures.

5.6.1.1 I²C Write



图 5-4. I²C Access Example: Write of the Control Register at Address 0xFFFE With 0x00, 0x16 (RF Enable = 1)

- A. I2C_READY signal, by being high indicates that I²C communication can be started.
- **B**. The device address (18h because E0 = E1 = E2 = 0) is being transmitted out.
- C. Register address is 0xFFFEh (which is the Control register).
- **D**. I2C_READY line is now low, new I²C communication should not be started.
- E. The data to write is transmitted (0016h).

5.6.1.2 I²C Read



图 5-5. I²C Access Example: Read of the Status Register at Address 0xFFFC, Responds With 0x00, 0x01 (Device_Ready = 1)

- A. I2C_READY signal, by being high indicates that I²C communication can be started.
- **B**. Packet has started: the device address (18h because E0 = E1 = E2 = 0) is being sent out.
- C. Address FFFCh next is transmitted, which is the address of the status register.



D. An I²C restart was done and device address sent with a read selection.

E. Clock stretching is being used by the RF430CL331H when it needs more time to respond due to unfinished internal processing.

F. I2C_READY line is now low, new I²C communication should not be started.

G. RF430CL331H drives the SDA line and returns the value of the status register, which is 0001h.

H. I2C_READY signal has returned to high, indicating communication can be started. This occurs after a short period of time after a STOP condition (in square red). This brief time is necessary for the RF430CL331H to finish internal processing.

5.6.2 BIP-8 Communication Mode With f^2C

The BIP-8 communication mode is enabled by setting the BIP-8 bit in the General Control register. All communication after setting this bit uses the following conventions with exactly 2 address bytes (16-bit address) and 2 data bytes (16-bit data) (see $\frac{1}{5}$ 5-4 and $\frac{1}{5}$ 5-5).

表 5-4. Write Access

Master	Address Bits 15 to 8	Address Bits 7 to 0	Data at Addr + 0	Data at Addr + 1	BIP-8
Slave	N/A	N/A	N/A	N/A	N/A

The Bit-Interleaved Parity (BIP-8) is calculated using 16-bit address and 16-bit data. If the received BIP-8 does not match with received data, no write is performed. The BIP-8 calculation does not include the I²C device address.

表 5-5. Read Access

Master	Address Bits 15 to 8	Address Bits 7 to 0	N/A	N/A	N/A	
Slave	N/A	N/A	Data at Addr + 0	Data at Addr + 1	BIP-8	

For read access, the Bit-Interleaved Parity (BIP-8) is calculated using the received 16-bit address and the 2 transmitted data bytes, and it is transmitted back to the master. The BIP-8 does not include the device address.

5.7 NFC Type 4B Tag Platform

This device is an NFC Forum Type 4B Tag Platform and ISO/IEC 14443B-compliant transponder that operates according to the NFC Forum Tag Type-4 specification and supports NDEF (NFC Data Exchange Format) data structure. Through the RF interface, the user can read and update the contents in the NDEF memory. The NDEF message in its entirety would only be present on the memory of the host controller. The RF430CL331H only has a portion of the NDEF message at any one time.

注

This device does not have nonvolatile memory; therefore, the information stored in the NDEF memory is lost when power is removed.

This device does not support the peer-to-peer mode or the reader/writer mode. All RF communication between an NFC forum device and this device is in the passive tag mode. The device responds by load modulation and is not considered an intentional radiator.

This device is intended to be used in applications where the primary reader/writer is, for example, an NFCenabled handset. In this case, the host application can be considered the destination device, and the cell phone or other type of mobile device is treated as the end-point device. This device supports ISO/IEC 14443-3, ISO/IEC 14443-4, and NFC Forum commands as described in the following sections.

The device supports data rates of 106, 212, 424, and 848 kbps.

Even though all data rates up to 848 kbps are supported, the device by default reports only the capability to support 106 kbps to the PCD. To change this behavior, use the sequence described in $\ddagger 5.7.3$.

The device always answers ATTRIB commands from the PCD that request higher data rates. The NFC Forum specifies for NFC-B a maximum data rate of 106 kbps. It is assumed that an NFC-compliant PCD would not request higher data rates, thus, no interoperability issues are expected.

The NFC Forum Type 4B Tag Platform and ISO/IEC 14443B command and response structure is detailed in ISO/IEC 14443-3, ISO/IEC 14443-4, and NFC Forum-TS-Digital Protocol. The applicable ISO/IEC 7816-4 commands are detailed in NFC Forum-TS-Type-4-Tag_2.0.

5.7.1 ISO/IEC 14443-3 Commands

These commands use the character, frame format, and timing that are described in ISO/IEC 14443-3, clause 7.1. The following commands are used to manage communication:

REQB and WUPB

The REQB and WUPB commands sent by the PCD are used to probe the field for PICCs of Type B. In addition, WUPB is used to wake up PICCs that are in the HALT state. The number of slots N is included in the command as a parameter to optimize the anticollision algorithm for a given application.

Slot-MARKER

After a REQB or WUPB command, the PCD may send up to (N - 1) Slot-MARKER commands to define the start of each timeslot. Slot-MARKER commands can be sent after the end of an ATQB message received by the PCD to mark the start of the next slot or earlier if no ATQB is received (no need to wait until the end of a slot, if this slot is known to be empty).

ATTRIB

The ATTRIB command sent by the PCD includes information required to select a single PICC. A PICC receiving an ATTRIB command with its identifier becomes selected and assigned to a dedicated channel. After being selected, this PICC only responds to commands defined in ISO/IEC 14443-4 that include its unique CID.

HLTB

The HLTB command is used to set a PICC in HALT state and stop responding to a REQB. After answering to this command, the PICC ignores any commands except the WUPB.

5.7.2 NFC Tag Type 4 Commands

Select

Selection of applications or files

Read Binary

Read data from file

Update Binary

Update (erase and write) data to file

5.7.3 Data Rate Settings

The device supports data rates of 106, 212, 424, and 848 kbps.

The device always answers ATTRIB commands from the PCD that request higher data rates. The NFC Forum specifies for NFC-B a maximum data rate of 106 kbps. It is assumed that an NFC-compliant PCD would not request higher data rates, thus, no interoperability issues are expected.

Even though all data rates up to 848 kbps are supported, the device by default reports only the capability to support 106 kbps to the PCD.

To change this behavior, follow these steps using the I²C serial interface:

- If you do not want to support all data rates up to 848 kbps, change the Data Rate Capability byte according to 表 5-7. 表 5-6 summarizes how to write the data rate, and the Data Rate Capability byte is set by the DATA 0 value in Step 3. Write Access.
- 2. Do the steps of the selected sequence. It is important to execute this sequence (in 表 5-6) before setting the Control register.

注

The General Control register (see \ddagger 5.11.1) is set to 0 after the sequence is completed in $\frac{1}{5}$ 5-6.

表 5-6. Data Rate Setting Sequence

ACCESS TYPE	ADDRESS BITS 15 TO 8	ADDRESS BITS 7 TO 0	DATA 0	DATA 1
1. Write Access	0xFF	0xE0	0x4E	0x00
2. Write Access	0xFF	0xFE	0x80	0x00
3. Write Access	0x2A	0xBA	0xF7 ⁽¹⁾	0x00
4. Write Access	0x27	0xB8	0x00	0x00
5. Write Access	0xFF	0xE0	0x00	0x00

(1) Data Rate Capability according to 表 5-7. 0xF7: all data rates up to 848 kbps are supported.

表 5-7. Data Rate Capability

	I	DATA R	АТА СА	PABILI	ГҮ ВҮТЕ	E		DESCRIPTION		
B7	B6	B5	B4	B3	B2	B1	B0			
0	0	0	0	0	0	0	0	PICC supports only 106 kbps in both directions (default).		
1	x	х	х	0	х	х	х	Same data rate from PCD to PICC and from PICC to PCD compulsory		
х	x	х	1	0	х	х	х	PICC to PCD, data rate supported is 212 kbps		
х	х	1	х	0	х	х	х	PICC to PCD, data rate supported is 424 kbps		
х	1	х	х	0	х	х	х	PICC to PCD, data rate supported is 848 kbps		
х	х	х	х	0	х	х	1	PCD to PICC, data rate supported is 212 kbps		
х	x	х	х	0	х	1	х	PCD to PICC, data rate supported is 424 kbps		
х	х	х	х	0	1	х	х	PCD to PICC, data rate supported is 848 kbps		



5.8 NDEF Structure

The NDEF message in its entirety is not stored at any time on the PICC. The host controller writes to the buffer memory as the NFC Type 4 requests come in.

 $\frac{1}{8}$ 5-8 shows the mandatory structure. This NDEF message would be present on the memory of the host controller. For more information, refer to the NFC Forum Type 4 Tag Operation Specification (see $\frac{1}{6}$ 6.2).

		2B - CCLen				
		1B - Mapping version (
		$2B - MLe = 000F9h^{(2)}$	2B - MLe = 000F9h ⁽²⁾			
		2B - MLc = 000F6h				
NDEF Application Selectable by Name =	Capability Container		1B - Tag = 04h			
	File ID = E103h		1B - Len = 06h			
				2B - File Identifier	The NDEF file	
D2760000850101h		NDEF FILE CUITIEV		2B - Maximum file size	mandatory	
			0D - Vai	1B - Read access		
				1B - Write access		
	NDEF File	2B - Len				
	Selectable by File ID = xxyyh	xB - Binary NDEF file of		Mandatory NDEF		
		yB - Unused if Len < N	in File Ctrl TLV			

表 5-8. NDEF Application Data

(1) RF430CL331H only supports mapping version up to 2.0.

(2) RF430CL331H specific

$\begin{tabular}{ c c c c c c c } \hline 2B - CLen & & & & & & & & & & & & & & & & & & &$							
NDEF Application Selectable by Selectable by File ID = E103h 18 - Mapping version (1) 28 - MLe = 000F6h (2) 28 - MLe = 000F6h (2) 18 - Len = 06h 18 - Len = 06h 18 - Val The NDEF File 28 - Maximum file size 18 - Write access 18 - Write access 19 - Write access 10 - Write access			2B - CCLen				
NDEF Application Selectable by Name = D2_7600_0085_0101h 2B - MLc = 000F6h ⁽²⁾ 1B - Tag = 04h 1B - Len = 06h 1B - Val The NDEF file Ctrl TLV The NDEF file Ctrl TLV is mandatory NDEF File Selectable by File ID = E103h IB - Tag = 05h 1B - Val IB - Tag = 05h 1B - Val The NDEF file Ctrl TLV is mandatory NDEF File Selectable by Selectable by Selectable by Selectable by Selectable by Name = D2_7600_0085_0101h IB - Tag = 05h 1B - Val IB - Tag = 05h 1B - Val IB - File Identifier 2B - Maximum file size 1B - Read access 1B - Val Zero or more proprietary file Ctrl TLV (N) NDEF File Selectable by Name = D2_7600_0085_0101h IB - Tag = 05h 1B - Val Zero or more proprietary file Ctrl TLV (N) Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or more proprietary file Ctrl TLV 1B - Val Zero or			1B - Mapping version	(1)			
NDEF Application Selectable by Name = D2_7600_0085_0101h 2B -MLc = 000F6h ⁽²⁾ 1B - Tag = 04h 1B - Len = 06h 1B - Val The NDEF file 2B - File Identifier 2B - Maximum file size 1B - Write access The NDEF file control TLV is mandatory NDEF Application Selectable by Name = D2_7600_0085_0101h 1B - Tag = 05h 1B - Len = 06h 1B - Len = 06h The NDEF file control TLV is mandatory NDEF File D2_7600_0085_0101h 1B - Tag = 05h 1B - Len = 06h 2B - File Identifier 2B - File Identifier Zer or more proprietary file Ctrl 1B - Len = 06h NDEF File Selectable by Name = D2_7600_0085_0101h 1B - Tag = 05h 1B - Len = 06h Zer or more proprietary file 2B - File Identifier NDEF File Selectable by Name = D2_7600_0085_0101h NDEF File Selectable by File ID = xxyyh Zer Len xB - Binary NDEF file content yB - Unused if Len < Maximum file size in File Ctrl TLV			2B -MLe = 000F9h $^{(2)}$				
NDEF Application Capability Container Selectable by File ID = E103h NDEF File Ctrl TLV IB - Tag = 04h IB - Len = 06h The NDEF file Control TLV is mandatory NDEF Application Selectable by Name = D2_7600_0085_0101h Capability Container Selectable by File ID = E103h IB - Tag = 05h IB - Len = 06h IB - Val ZB - File Identifier ZB - Maximum file size IB - Read access IB - Nrite access IB - Nrite access IB - Val ZB - File Identifier ZB - Maximum file size IB - Nrite access IB - Val ZB - File Identifier ZB - Maximum file size IB - Val ZB - File Identifier ZB - Maximum file size IB - Val ZB - File Identifier ZB - Maximum file size IB - Nrite access IB - Nrite access<			2B -MLc = 000F6h (2)				
$ \begin{tabular}{ c c c c c } \label{eq:relation} \end{tabular} \begin{tabular}{ c c c c c c } \label{eq:relation} \end{tabular} tabula$				1B - Tag = 04h	I	_	
$ \begin{tabular}{ c c c c c c } \label{eq:constraint} NDEF File Ctrl TLV \\ \end{tabular} \begin{tabular}{ c c c c c c c } \label{eq:constraint} \end{tabular} tabul$				1B - Len = 06h			
NDEF Application Capability Container Selectable by File ID = E103h Proprietary File Ctrl ILV (1) 1B - Tag = 05h IB - Len = 06h 1B - Tag = 05h IB - Len = 06h 2B - File Identifier NDEF Application 2B - File Identifier 2B - Maximum file size IB - Read access Zero or more proprietary File Ctrl ILV (1) 2B - File Identifier NDEF File IB - Tag = 05h 1B - Urite access 2B - File Identifier ID - TLV (1) IB - Tag = 05h 1B - Write access Zero or more proprietary file control TLVs NDEF File IB - Tag = 05h 1B - Len = 06h Zero or more proprietary file control TLVs NDEF File 2B - Len 2B - File Identifier Zero or more proprietary file control TLVs NDEF File 2B - Len 2B - Maximum file size Mandatory NDEF file ID = xxyyh Yei - Unused if Len < Maximum file size in File Ctrl TLV					2B - File Identifier	The NDEF file	
NDEF Application Capability Container Selectable by File ID = E103h Proprietary File (L1) Proprietary File Ctrl 1B - Tag = 05h 1B - Len = 06h 1B - Vall 2B - File Identifier 1LV (1) 1B - Tag = 05h 1B - Read access 1B - Maximum file size 1B - Tag = 05h 1B - Write access 1B - Tag = 05h 1B - Write access 1B - Tag = 05h 1B - Write access 1B - Tag = 05h 1B - Len = 06h Proprietary File (Ctrl) 1B - Tag = 05h 1B - Len = 06h 1B - Len = 06h 1B - Len = 06h 1B - Len = 06h 1B - Len = 06h 1B - Len = 06h 1B - Len = 06h 2B - Maximum file size 1B - Vall 1B - Read access 1B - Write access 1B - Write access 1B - Write access			NDEF FILE GUI TEV		2B - Maximum file size	mandatory	
NDEF Application Selectable by File ID = E103h				ов - vai	1B - Read access		
NDEF Application Selectable by Name = D2_7600_0085_0101h Capability Container Selectable by File ID = E103h Proprietary File Ctrl TLV (1) 1B - Len = 06h 2B - File Identifier Zero or more 1B - Read access Zero or more 1B - Write access Zero or more 1B - Val Zero or more 1B - Val Zero or more 1B - Len = 06h Zero or more 1B - Val Zero or more 2B - Val Zero or more 1B - Val Zero or more 1B - Val Zero or more 1B - Val Zero or more 2B - Val Zero or more 1B - Val Zero or more 2B - Val Zer					1B - Write access		
NDEF Application Selectable by Name = D2_7600_0085_0101h Proprietary File Ctrl TLV (1) 1B - Len = 06h 2B - File Identifier Zero or more proprietary file 02_7600_0085_0101h IB - Tag = 05h 1B - Len = 06h Zero or more		Capability Container		1B - Tag = 05h		_	
NDEF Application Selectable by Name = D2_7600_0085_0101h File ID = E103h Proprietary File Ctrl TLV (1) 6B - Val 2B - File Identifier 2B - Maximum file size 1B - Read access 1B - Write access Zero or more proprietary file control TLVs NDEF File D2_7600_0085_0101h 1B - Tag = 05h 1B - Len = 06h 2B - File Identifier Zero or more proprietary file Zero or more Proprietary File Ctrl TLV (N) 1B - Tag = 05h 1B - Val 2B - File Identifier Zero or more Proprietary file Ontrol TLVs IL - Second		Selectable by		1B - Len = 06h			
NDEF Application Selectable by Name = D2_7600_0085_0101h TLV (1) 6B - Val 2B - Maximum file size 1B - Read access 1B - Write access 1B - Write access 1B - Val Zero or more proprietary file control TLVs NDEF File Selectable by File ID = xxyyh 2B - Len XB - Binary NDEF file content YB - Unused if Len < Maximum file size in File Ctrl TLV		File ID = E103h	Proprietary File Ctrl TLV (1)		2B - File Identifier		
NDEF Application Selectable by Name = D2_7600_0085_0101h Image: Imag	NDEE Application				2B - Maximum file size		
NDEF Application Selectable by Name = D2_7600_0085_0101h Image: Constant of the selectable by Name = D2_7600_0085_0101h Image: Constant of the selectable by Name = D2_7600_0085_0101h Image: Constant of the selectable by Name = Image: Constant of the selectable by Name = Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable by File ID = xxyyh Image: Constant of the selectable bit File Ctrl TLV Image: Constant of the selectable bit File Ctrl TLV Image: Constant of the selectable bit File Ctrl TLV Image: Constant of the selectable bit File Ctrl TLV Image: Constant of the selectable bit File Ctrl TLV Image: Constant of the selectable bit File Ctrl TLV Image				ов - vai	1B - Read access		
Selectable by Name = D2_7600_0085_0101h i iiiiiiiiiiiiiiiiiiiiiiiiiiiiiiiiiiii		NDEE Application				1B - Write access	Zero or more
D2_7600_0085_0101h IB - Tag = 05h control TLVs Proprietary File Ctrl IB - Len = 06h IB - Read access IB - Val IB - Read access IB - Write access IB - Val IB - Write access IB - Write access IB - Val IB - Val IB - Write access IB - Val IB - Write access IB - Write access VB - File ID = xxyyh YB - Unused if Len < Maximum file size in File Ctrl TLV	Selectable by Name =		÷			proprietary file control TLVs	
1	D2_7600_0085_0101h			1B - Tag = 05h	l		
Proprietary File Ctrl TLV (N)Proprietary File Ctrl TLV (N)B2B - File Identifier 2B - Maximum file size 1B - Read access 1B - Write accessNDEF File Selectable by File ID = xxyyh2B - Len xB - Binary NDEF file content yB - Unused if Len < Maximum file size in File Ctrl TLV				1B - Len = 06h	1B - Len = 06h		
TLV (N) 6B - Val 2B - Maximum file size 1B - Read access 1B - Write access NDEF File Selectable by File ID = xxyyh 2B - Len xB - Binary NDEF file content yB - Unused if Len < Maximum file size in File Ctrl TLV			Proprietary File Ctrl		2B - File Identifier		
Image: NDEF File Selectable by File ID = xxyyh 2B - Len xB - Binary NDEF file content yB - Unused if Len < Maximum file size in File Ctrl TLV Mandatory NDEF file Proprietary File (1) Selectable by File ID = xxyyh 2B - Len xB - Binary proprietary file content yB - Unused if Len < Maximum file size in File Ctrl TLV			TLV (N)	6R Val	2B - Maximum file size		
NDEF File Selectable by File ID = xxyyh 2B - Len xB - Binary NDEF file content yB - Unused if Len < Maximum file size in File Ctrl TLV				OB - Vai	1B - Read access		
NDEF File Selectable by File ID = xxyyh2B - Len xB - Binary NDEF file content yB - Unused if Len < Maximum file size in File Ctrl TLVMandatory NDEF fileProprietary File (1) Selectable by File ID = xxyyh2B - Len xB - Binary proprietary file content yB - Unused if Len < Maximum file size in File Ctrl TLV					1B - Write access		
Selectable by File ID = xxyyh xB - Binary NDEF file content Mandatory NDEF file Proprietary File (1) Selectable by File ID = xxyyh 2B - Len Optional proprietary file XB - Binary proprietary file content yB - Unused if Len < Maximum file size in File Ctrl TLV		NDEF File	2B - Len				
File ID = xxyyn yB - Unused if Len < Maximum file size in File Ctrl TLV		Selectable by	xB - Binary NDEF file	content		file	
Proprietary File (1) 2B - Len Optional Selectable by xB - Binary proprietary file content proprietary file yB - Unused if Len < Maximum file size in File Ctrl TLV		File ID = xxyyh	yB - Unused if Len < N	Maximum file size	in File Ctrl TLV		
Selectable by File ID = xxyyh xB - Binary proprietary file content yB - Unused if Len < Maximum file size in File Ctrl TLV		Proprietary File (1)	2B - Len				
File ID = xxyyh yB - Unused if Len < Maximum file size in File Ctrl TLV :		Selectable by	xB - Binary proprietary	/ file content		optional	
Image: Selectable by File ID = xxyyh 2B - Len Optional proprietary file content Where With Selectable by File ID = xxyyh 2B - Len Optional proprietary file			File ID = xxyyh	yB - Unused if Len < N			
Proprietary File (N) 2B - Len Optional Selectable by xB - Binary proprietary file content optional yB - Unused if Len < Maximum file size in File Ctrl TLV		:					
Selectable by xB - Binary proprietary file content Optional File ID = xxyyh yB - Unused if Len < Maximum file size in File Ctrl TLV		Proprietary File (N)	2B - Len				
File ID = xxyyh yB - Unused if Len < Maximum file size in File Ctrl TLV		Selectable by	xB - Binary proprietary	xB - Binary proprietary file content			
		File ID = xxyyh	yB - Unused if Len < N	Maximum file size	in File Ctrl TLV		

表 5-9. NDEF Application Data (Includes Proprietary Sections)

(1) RF430CL331H only supports mapping version up to 2.0.
 (2) RF430CL331H specific





5.9 Typical Operation

Image S-6 shows typical operation of this device. Generally, on power up or reset, the host controller initializes this device and then enables the RF. When a PCD approaches the dynamic tag, it starts by performing the ISO14443-B anticollision sequence. This portion is handled automatically by the RF430CL331H.

Eventually the sequence reaches the NFC Type 4 level. When the PCD issues a file select, Read Binary or Update Binary commands, the RF430CL331H interrupts the host controller by asserting the INT0 pin to request the necessary information or act on the information. Each type of interrupt request is detailed in the following sections.



图 5-6. High-Level Flow

5.9.1 NDEF or Capability Container Select Procedure

This select procedure does not change between selection of the capability container or an NDEF file. These two types of selects can be differentiated by the file identifier that the RF430CL331H reports in the NDEF File Identifier register (see $\ddagger 5.11.7$).

For the general flow, see 85-7.



图 5-7. Select System Flow

The procedure:

1. PCD procedure:

(a) Issues a Capability Container or a NDEF File Select command.

- 2. RF430CL331H procedure:
 - (a) Receives the RF packet.
 - (b) Sets the NDEF File Identifier register (see 节 5.11.7) using the file identifier that was included in the packet from the PCD.
 - (c) Sets up the Status register (see 节 5.11.2) and the interrupt registers (see 节 5.11.3) to describe the file select request.
 - (d) Ensure that General Type 4 request interrupt is enabled to generate the required interrupt on the INTO pin.
- 3. Host controller procedure:
 - (a) Interrupt is received.
 - (b) Checks the source of the interrupt by reading the interrupt registers (see \ddagger 5.11.3).
 - (c) The source of the interrupt is the General Type 4 request.
 - (d) When there is a General Type 4 request, the Status register (see 节 5.11.2) must be read and the Type 4 Command field examined to determine what Type 4 command has been received.
 - (e) The result is a File Select command.
 - (f) The NDEF File Identifier register (see $\ddagger 5.11.7$) should be read.
 - (g) The host controller should, search its available files and determine if the file exists.
 - (h) The interrupt must be cleared by writing to the Interrupt Flag register (see [†] 5.11.3). This step must be done before setting the Interrupt Serviced field in the Host Response register (see [†] 5.11.8).
 - (i) If a specific Status Word (SW) response is necessary (generally for communicating specific error conditions) to the Select command:
 - (i) Set the Custom Status Word Response register (see $\frac{1}{5}$ 5.11.13) with the desired status word.
 - (ii) Set the Use Custom SW Response bit in the Host Response register (see \ddagger 5.11.8).
 - (j) To complete servicing the Select command interrupt, set the Interrupt Serviced field in the Host Response register (see 节 5.11.8).

Servicing of the Select command is complete.

- 4. RF430CL331H procedure:
 - (a) If the custom Status Words (SW) feature was not used:
 - (i) If the host controller indicated that the file existed, the response to the PCD is SW1 = 90h and SW2 = 00h.
 - (ii) If the host controller indicated that the file did not exist, the response to the PCD is SW1 = 6Ah and SW2 = 82h.
 - (b) If the custom response feature was used, the response to the PCD is what was set in the Custom Status Word Response register (see 节 5.11.13).

5.9.2 NDEF or Capability Container Read Binary Procedure

This read procedure does not change between when the PCD reads the Capability Container or an NDEF file. These two types of reads can be differentiated by the file identifier that the RF430CL331H reports in the NDEF File Identifier register (see $\ddagger 5.11.7$).

For the general flow, see 5-8.



图 5-8. Read System Flow

The procedure:

- 1. PCD procedure:
 - (a) Issues a Capability Container or a NDEF Read Binary command.
- 2. RF430CL331H procedure:
 - (a) Receives the RF packet.
 - (b) Checks its buffer and determines if all of the requested data in the Read Binary command exists already in the buffer.
 - (c) If all the data is available in the buffer then (in the case that extra data was written in a previous read request):
 - (i) No interrupt is issued to the host controller.
 - (ii) The data is supplied in the response packet to the PCD automatically.
 - (iii) The status word response SW1 = 90h and SW2 = 00h is appended to the packet.
 - (iv) The flow returns to wait for the next Type 4 request.
 - (d) If no data or only partial data is available, then an interrupt is issued to the host controller.
- 3. Host controller procedure:
 - (a) An interrupt is received.
 - (b) Checks the source of the interrupt by reading the interrupt registers (see $\ddagger 5.11.3$).
 - (c) The source of the interrupt is the General Type 4 request.
 - (d) When there is a General Type 4 request, the Status register (see # 5.11.2) must be read and the

Type 4 Command field examined to determine what Type 4 command has been received.

- (e) The result is a Read Binary command.
- (f) The NDEF File Identifier register (see 节 5.11.7) may be read, but it is not necessary as it is always the file that the last Select command selected.
- (g) Read the Buffer Start register (see 节 5.11.11) to determine where in the buffer of the RF430CL331H to begin storing the data.
- (h) Read the NDEF File Offset register (see 节 5.11.10) to determine at which index in the NDEF or CC file to begin supplying the data to the RF430CL331H.
- (i) Read the NDEF Block Length register (see 节 5.11.9) to determine what block length the PCD is requesting.
- (j) Check if the request is valid:
 - (i) If it is valid, write the data into the buffer of the RF430CL331H starting at Buffer Start index for NDEF Block Length bytes.
 - (ii) If it is not valid, assert the Custom Status Word option in the Host Response register (see [†] 5.11.8) and write the custom word in the Custom Status Word Response register (see [†] 5.11.13). Only the status word response supplied will be sent out.
- (k) If caching is desirable, extra sequential data can be written to the RF430CL331H buffer, up to the maximum RF430CL331H buffer length (length is 3000 bytes, highest index is 2999).

注

To improve the Read Binary performance of the RF430CL331H , a caching feature may be used. After writing the requested Read Binary request data into the RF430CL331H buffer, extra sequential data may be written. If on the next Read Binary request, all of the requested data is in the buffer, the RF430CL331H automatically responds and services that request without any intervention of the host controller; that is, no interrupt is issued.

- (I) Update the NDEF Block Length register (see 节 5.11.9) with the number of bytes written into the buffer.
- (m) The interrupt must be cleared by writing to the Interrupt Flag register. This step must be done before setting the Interrupt Serviced field in the Host Response register.
- (n) To complete servicing the Read Binary command interrupt, set the Interrupt Serviced field in the Host Response register.
- 4. RF430CL331H procedure:
 - (a) Only the requested data (even if extra was supplied) is included in the response packet to the PCD. The status words are appended to the response packet per NFC Type 4 specification.
 - (b) If the command was valid, the status words are SW1 = 90h and SW2 = 00h.
 - (c) If the custom response feature *was* used, the response to the PCD is only what was set in the Custom Status Word Response register.

5.9.2.1 NDEF Read Command Internal Buffer Handling



4. Next Request: Cycle repeats

图 5-9. Read Buffer Flow (no extra data)

In normal read mode, when Read Prefetch functionality has not been enabled, each Read Binary request that comes in, is passed to the host controller and the internal state machine is in blocking mode until the data is sent back to the RF430CL331H. The RF430CL331H uses the same memory for each request, it is no more than the size of the read request packet length.

5.9.2.2 NDEF Read Command Internal Buffer Handling (With Caching)



图 5-10. Read Buffer Flow (with caching)

- 1. PCD requests a block of data. PICC received the requests, sets up the internal register and asserts the INTO interrupt.
- 2. Host controller supplies the request but also adds more data on the file that is continuous with this request.
- 3. The next PCD request is fulfilled automatically because the data that is requested is already in the buffer. The host controller is not interrupted.
- 4. The next PCD request has insufficient data, so the data that is available is shifted to the beginning of the buffer and the unavailable data is requested.
- 5. The full request is transmitted out.
- 6. The cycle can repeat.

5.9.3 NDEF or Capability Container Read Procedure (Prefetch Feature)

The read prefetch feature includes the standard read procedure. However, after the requested data is written into the RF430CL331H buffer, when the RF430CL331H starts to transmit the requested data over the air, another interrupt is issued to the host controller indicating that extra data can be appended to the RF430CL331H buffer. The host controller can start adding data to the buffer while the RF430CL331H is transmitting over RF, because two tasks are happening at once, this increases the throughput of the system. For optimum operation, the host controller should cease to write extra data before the next interrupt. If the host controller does not cease to write, latency is introduced into the system, which can accumulate until requests start to time out. To determine how much is available to write the prefetch data, the time to send out the packet (that was requested) over RF can be calculated.

To enable read prefetch feature, the Read Prefetch interrupt must be enabled in the Interrupt Enable register (see $\ddagger 5.11.3$).

For a general flow, see 5-11.



图 5-11. Read System Flow (Prefetch Feature)

www.ti.com.cn

The procedure:

RUMENTS

- 1. PCD procedure:
 - (a) Issues a Capability Container or a NDEF Read Binary command.
- 2. Dynamic Tag/RF430CL331H procedure:
 - (a) Receives the RF packet.
 - (b) Checks its buffer and determines if all of the requested data in the Read Binary command exists already in the buffer.
 - (c) If all the data is available in the buffer then (in the case that extra data was written in a previous read request)
 - (i) No General Type 4 interrupt is issued to the host controller.
 - (ii) The data is supplied in the response packet to the PCD automatically.
 - (iii) The status word response SW1 = 90h and SW2 = 00h is appended to the packet.
 - (iv) The flow now goes to Step 4e.
 - (d) If no data or only partial data is available, then a General Type 4 interrupt is issued to the host controller.
- 3. Host controller procedure:
 - (a) Interrupt is received.
 - (b) Checks the source of the interrupt by reading the interrupt registers (see \ddagger 5.11.3).
 - (c) The source of the interrupt is the General Type 4 request.
 - (d) When there is a General Type 4 request, the Status register (see 节 5.11.2) must be read and the Type 4 Command field examined to determine what Type 4 command has been received.
 - (e) The result is a Read Binary command.
 - (f) The NDEF File Identifier register (see 节 5.11.7) may be read, but it is not necessary as it is always the file that the last Select command selected.
 - (g) Read the Buffer Start register (see 节 5.11.11) to determine where in the buffer of the RF430CL331H to begin storing the data.
 - (h) Read the NDEF File Offset register (see 节 5.11.10) to determine at which index in the NDEF or CC file to begin supplying the data to the RF430CL331H.
 - (i) Read the NDEF Block Length register (see † 5.11.9) to determine what block length the PCD is requesting.
 - (j) Check if the request is valid:
 - (i) If it is valid write the data into the buffer of the RF430CL331H starting at Buffer Start index for NDEF Block Length bytes.
 - (ii) If it is not valid, assert the Custom Status Word option in the Host Response register (see [†] 5.11.8) and write the custom word in the Custom Status Word Response register (see [†] 5.11.13). Only the status word response supplied will be sent out.
 - (k) Write the requested amount of data to the buffer starting at the Buffer Start register index.

注

Read caching (writing data beyond the request in a General Type 4 request interrupt) should be avoided with the prefetch feature, because caching, at least initially, creates latency because the system is waiting (blocking) for the General Type 4 request interrupt to complete. Instead, in prefetch mode, only the requested data should be supplied in the General Type 4 request interrupt. When the Extra Data interrupt occurs afterwards (in tandem with the RF transmission), only then as much as possible extra data should be written to the buffer.

- (I) Update the NDEF Block Length register with how much bytes were written into the buffer.
- (m) The interrupt must be cleared by writing to the Interrupt Flag register. (This step must be done before setting the Interrupt Serviced field in the Host Response register.)
- (n) To complete servicing the Read Binary command interrupt, set the Interrupt Serviced field in the Host Response register.

- 4. Dynamic Tag RF430CL331H procedure:
 - (a) Only the requested data (even if extra was supplied) is included in the response packet to the PCD. The status words are appended to the response packet per NFC Type 4 specification.
 - (b) If the command was valid, the status words are SW1 = 90h and SW2 = 00h.
 - (c) If the custom response feature *was* used, the response to the PCD is what was set in the Custom Status Word Response register.
 - (d) RF transmission starts, the Extra Data interrupt is always asserted.
- 5. The host controller must service the Extra Data interrupt by appending to the buffer extra sequential data up until the buffer size (3000 bytes).
 - (a) Checks the source of the interrupt by reading the interrupt registers.
 - (b) The interrupt is an Extra Data interrupt.
 - (c) Read the Buffer Start register to determine where in the buffer of the RF430CL331H to begin storing the data.

注

When the Extra Data interrupt is enabled, the interrupt always occurs when the RF430CL331H is responding to the Read Binary request. However, this does not mean that every interrupt service can add to the RF430CL331H buffer (3000 bytes). If the Buffer Start register read indicates its index is at the end of the buffer, then no more data can be added. In this case the NDEF Block Length register should be set to 0 indicating that no data was added to the buffer. On the next Read Binary request, the valid data in the RF430CL331H buffer is shifted to the beginning to allow more room for extra data to be appended again.

- (d) NDEF File Offset register can be read.
- (e) Write sequential extra data to the buffer starting at the Buffer Start register index.
- (f) The time limit of writing extra data to the buffer is until the next Read Binary command is completed to be transmitted to the RF430CL331H. After that point, latency starts to be introduced into the system as the processing of the new packet is delayed.
- (g) Update the NDEF Block Length register with how many bytes were written into the buffer. If none, set to 0.
- (h) The prefetch interrupt must be cleared by writing to the Interrupt Flag register.
- (i) Set the Extra Data Send In bit in the Host Response register.
- (j) This completes servicing of the Read Prefetch interrupt.

5.9.3.1 NDEF Read Command With Prefetch Internal Buffer Handling

0	е	Entire Buffer Space (r	not to scale)	
1. PCD – Read Binary Request	N Block Requested	(<255 bytes)		
2. Host – Service Request	Filling Block]		
3. PCD/Host – Data Being Transmitted (prefetch interrupt):	Being Transmitted	Filling Now		
4. PCD/Host – Next Request (only prefetch interrupt):	Sent	Being Transmitted	Filling Now	
5. PCD/Host – Next Request (only prefetch interrupt):	Sent	Sent	Being Transmitted	Filling
6. PCD – Next Request (General Type 4 Request interrupt) Buffer shifted internally:	Have Need	N		(up to limit)
	Request Parameters buffer_start_index = length_requested =	s: L N - L		
7. Host – Service Request:	Sending			

8. Next: Cycle repeats (to Step 3)

图 5-12. Read Buffer Flow (Prefetch Feature)

The key feature with Prefetch is that while the Read Binary is being transmitted, the next packet can be sent out by the host controller and be filling the internal RF430CL331H buffer. Each request is stored in the subsequent buffer memory until the buffer limit is reached. When the buffer limit is reached, the remaining unsent data is shifted to the beginning of the buffer and what data is needed for the next request is requested (see Step 6). This command is requested using the General Type 4 request interrupt (not with a prefetch interrupt) because it does not happen during the time when the RF430CL331H is sending data over RF.

Read buffer flow procedure (see 85-12):

- 1. PCD requests a block of data.
- 2. PICC received the requests, sets up the internal register and asserts the INTO interrupt.
- 3. Host services the interrupt by supplying the data. PICC transmits the data. After starting to transmit the data, PICC issues a Read Prefetch interrupt. The host supplies the extra data while the RF communication is ongoing.
- 4. When the next Read Binary request comes, because the data is already cached, only the Prefetch interrupt is asserted.
- 5. This time a Prefetch interrupt is asserted, but only a portion of the data can be written because the buffer space is running out.
- 6. Because there is not enough data to service the Read Binary requests, a General Type 4 interrupt is asserted. The partial data that has been written previously is shifted to the beginning of the buffer and the only the remaining missing data is requested in the interrupt.
- 7. The complete data is sent out. The cycle repeats (the Prefetch interrupt is issued again).

If a prefetch interrupt is issued for a file, but there is no more data to send, this interrupt can be canceled by servicing it by setting the data length sent to 0. Also if data was sent by a prefetch but it was not needed by the RF430CL331H (due to a different request by the PCD) that data is discarded and the new request handling initiated.

5.9.4 NDEF or Capability Container Write Procedure (Blocking)

This write procedure does not change between when the PCD writes the Capability Container or an NDEF file. These two types of writes can be differentiated by the file identifier that the RF430CL331H reports in the NDEF File Identifier register (see $\ddagger 5.11.7$).

For a general flow, see 85-13.



图 5-13. Write System Flow (Blocking)

The procedure:

- 1. PCD procedure:
 - (a) Issues a Capability Container or a NDEF File Write (or Update Binary) command.
- 2. RF430CL331H procedure:
 - (a) Receives the RF Update Binary packet.
 - (b) Sets up the appropriate registers.
 - (c) Issues the General Type 4 request interrupt.
- 3. Host controller procedure:
 - (a) Checks the source of the interrupt by reading the interrupt registers (see $\ddagger 5.11.3$).
 - (b) The source of the interrupt is the General Type 4 request.
 - (c) When there is a General Type 4 request, the Status register (see 节 5.11.2) must be read and the Type 4 Command field examined to determine what Type 4 command has been received.
 - (d) The result is an Update Binary command.
 - (e) The NDEF File Identifier register (see 节 5.11.7) may be read, but it is not necessary as it is always the file that the last Select command selected.
 - (f) Read the Buffer Start register (see [†] 5.11.11) to determine where in the buffer of the RF430CL331H to begin reading the stored data. Reading this register is unnecessary as it is always 0.
 - (g) Read the NDEF File Offset register (see 节 5.11.10) to determine at which index of the NDEF or CC file the current data is starting.
 - (h) Read the NDEF Block Length register (see † 5.11.9) to determine how much data is being sent by the PCD in this packet.
 - (i) Read the data from the buffer of the RF430CL331H starting at index of 0 until the block length supplied, updating the main file on the host controller.
 - (j) If a specific Status Word (SW) response is necessary to the Update Binary command:
 (i) Set the Custom Status Word Response register (see [†] 5.11.13) with the desired status word.
 - (ii) Set the Use Custom SW Response bit in the Host Response register.
 - (k) The interrupt must be cleared by writing to the Interrupt Flag register. This step must be done before setting the Interrupt Serviced field in the Host Response register.
 - (I) To complete servicing the Update Binary command interrupt, set the Interrupt Serviced field in the

Host Response register.

- 4. RF430CL331H procedure:
 - (a) If the custom SW feature was not used, the response is status words SW1 = 90h and SW2 = 00h.
 - (b) If the custom response feature *was* used, the response to the PCD is what was set in the Custom Status Word Response register.

5.9.4.1 NDEF Write Command (Blocking) Internal Buffer Handling



图 5-14. Write Buffer Flow (Blocking)

The write with blocking stores the send in data packet until it is read out by the host controller. Once it has been read out, the next write data packet is stored in the same section of memory. The cycle repeats with more Update Binary packets.

5.9.5 NDEF or Capability Container Write Procedure (Nonblocking)

This command is different from the blocking operation in that the RF430CL331H automatically responds to an Update Binary command with a success acknowledgment upon receiving the Update Binary packet.

After the acknowledgment, the PCD starts to send the next Update Binary block. The intent is to increase throughput by downloading the previous Update Binary packet while the new one is being transmitted into a separate buffer on the RF430CL331H.

Care must be taken to read out the entire packet before the new one is completely transmitted to the RF430CL331H. Otherwise, this creates latency that, if not corrected, accumulates to the point where one Update Binary packet request eventually times out.

To enable write nonblocking mode, set the Automatic ACK On Write field in the General Control register.

For a general flow, see 8 5-15.

RF430CL331H (PICC) Host Controller Reader (PCD) Stores the packet in the buffer Reads the PICC data buffer while PCD sends the File Write INTO 1.) Acknowledges the request RFthe next RF Interrupt (Second) request over RF transmission is 2.) Issues the interrupt occurring If necessary Decides whether to continue -RF (First) writing more data

图 5-15. Write System Flow (Nonblocking)

- 1. PCD procedure:
 - (a) Issues a Capability Container or a NDEF File Write (or Update Binary) command.
- 2. RF430CL331H procedure:
 - (a) Receives the RF Update Binary packet.
 - (b) Automatically responds with a successful acknowledgment: SW1 = 90h and SW2 = 00h.
 - (c) Sets up the appropriate registers.
 - (d) Issues the General Type 4 request interrupt.
 - (e) Waits for a new Update Binary packet to be transmitted to.
- 3. Host controller procedure:
 - (a) Checks the source of the interrupt by reading the interrupt registers (see $\ddagger 5.11.3$).
 - (b) The source of the interrupt is the General Type 4 request.
 - (c) When there is a General Type 4 request, the Status register (see 节 5.11.2) must be read and the Type 4 Command field examined to determine what Type 4 command has been received.
 - (d) The result is an Update Binary command.
 - (e) The NDEF File Identifier register (see [†] 5.11.7) may be read, but it is not necessary as it is always the file that the last Select command selected.
 - (f) Read the Buffer Start register (see [†] 5.11.11) to determine where in the buffer of the RF430CL331H to begin reading the stored data. Reading this register is unnecessary, as it is always 0.
 - (g) Read the NDEF File Offset register (see 节 5.11.10) to determine at which index of the NDEF or CC file the current data is starting.
 - (h) Read the NDEF Block Length register (see $\ddagger 5.11.9$) to determine how much data is being sent by the PCD in this packet.
 - (i) Read the data from the buffer of the RF430CL331H, starting at the index of 0, until the block length supplied, updating the main file on the host controller.
 - (j) The interrupt must be cleared by writing to the Interrupt Flag register. This step must be done before setting the Interrupt Serviced field in the Host Response register.
 - (k) To complete servicing the Update Binary command interrupt, set the Interrupt Serviced field in the Host Response register.

5.9.5.1 NDEF Write Procedure (Nonblocking) Internal Buffer Handling



图 5-16. Write System Flow (Nonblocking)

The main difference in a nonblocking write operation is that when the data packet has been received from the PCD, the host controller is reading out the packet while the next one is being sent in (see Steps 3 and 4 in \mathbb{E} 5-16). Data is received into a temporary buffer and when the last packet has been read out, the data in the temporary buffer is copied into the standard buffer so the data can be accessed by the host controller.

5.10 RF Command Response Timing Limits

Meeting specification timing is an important part of designing a stable and reliable system. There are various timing parameters that must be considered in this system, and one of the most important is the RF command response time.

The RF430CL331H negotiates the maximum allowable FWI timing (frame waiting time integer). This negotiated setting is the maximum of 8 (NFC Digital Protocol Section A.2, NFC-B Technology, FWI_{MAX}), giving the time of approximately 77 ms. This is the time that the PCD allows to respond to any command.

The RF430CL331H implements an internal timer monitoring this FWI timing specification. The internal timer defaults to approximately 55 ms instead of 77 ms due to variations in the internal oscillator frequency. The 55 ms allows meeting the 77-ms specification across all devices reliably.

12C READY I2C_SIGNAL Asserted INTO I2C (possible case) Activity Activity 55 ms 0 ms - First time-out time Second time-out time 2. PICC 4. PICC formats a 1. Select. Read prepares 5 Host controller has S(WTX) request Write Type 4 registers and 3. Host controller has 55 ms this time to service the (see SWTX register) 6. After this point. command sent issues an to service the interrupt interrupt PCD/Mobile either and sends it over RF to PICC nterrupt to host sends a NACK controller (which will not be handled) or a Deselect command and PICC starts Host controller has not PCD stops listening and internal timer cycles the RF field serviced the interrupt issues a packet. (defaults to (Host response register Bit This time varies from PCD 55 ms) 0 not set) to PCD.





- 1. The PCD issues a Type 4 command (Select, Read Binary, or Update Binary).
- 2. If this command needs host controller response, the RF430CL331H sets up the registers and asserts INTO.
- 3. The RF430CL331H starts the internal initial timer of 55 ms.
- 4. If the host controller does not respond in 55 ms, (that is, the Host Response register Interrupt Serviced Bit 0 is not set) the RF430CL331H sets the I2C_READY and I2C_SIGNAL pins to low, which. I2C_SIGNAL is a signal that is asserted when there is an active S(WTX) request ongoing. During this time the I²C communication does not have to be stopped.
- 5. After the PICC issues the wait time extension there is another period of time in which the host controller has time to respond to the initial interrupt request.
- 6. At this time, the PCD sends out a packet. This point should be avoided, because this will likely mean the PCD will break off communications.
- 7. After several milliseconds, the RF430CL331H issues an S(WTX) request to the PCD.
 - (a) The WTXM field in the Frame Wait Time Extension (see 节 5.11.12) is set with the value in the SWTX register.
- 8. Sends the Wait Time Extension request.
- 9. Sets the I2C_SIGNAL and I2C_READY pins to high indicating that communication can continue.
- 10. If the host controller does not service the interrupt in a certain period of time (the internal timer expires, but this does not produce an effect), the PCD issues a R(NACK) command. This and any other command are not handled by the RF430CL331H; there is no response, because the RF430CL331H command buffer still has the previous command that it has not serviced. Thus, the command must be serviced after the first S(WTX) request.
- 11. If the PCD issues a command after the first S(WTX) command, it is likely to not be serviced, and this typically results in a Deselect command with a field reset. The communication must be restarted.



5.11 Registers

All 16-bit registers are in little-endian format: the least significant byte with bits 7-0 is at the lowest address (this address is always even). The most significant byte with bits 15-8 is at the highest address (this address is always odd).

5.11.1 General Control Register

					-			
ADDRESS	15	14	13	12	11	10	9	8
0xFFFF				Reserved				Automatic ACK On Write
ADDRESS	7	6	5	4	3	2	1	0
0xFFFE	Reserved	Standby Enable	BIP-8	INTO Drive	INTO High	Enable INT	Enable RF	SW-Reset

表 5-10. General Control Register

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-9	Reserved	R	0	Reserved for future use. Write with 0.
8 Automatic ACK On Write		R/W	0	Enabling this bit causes an automatic acknowledgment to be sent when an Update Binary command is received. The buffer must be read out immediately (possibly while a new Update Binary command is being received over RF).
				1b - Automatic acknowledgment of Undate Binary command
7	Reserved	R/W	0	
6	Standby Enable	R/W	0	Enables a low-power standby mode. The standby mode is entered if the RF interface is disabled, the communication watchdog is disabled, and no serial communication is ongoing. 0b = Standby mode disabled
				1b = Standby mode enabled
5	BIP-8	R/W	0	Enables BIP-8 communication mode (bit interleaved parity). If BIP-8 is enabled, a separate running tally is kept of the parity (that is, the number of ones that occur) for every bit position in the bytes included in the BIP-8 calculation. The corresponding bit position of the BIP-8 byte is set to 1 if the parity is currently odd and is set to 0 if the parity is even – resulting in an overall even parity for each bit position including the BIP-8 byte. All communication when this bit is set must follow the conventions defined in the BIP-8 communication mode disabled 1b = BIP-8 communication mode enabled
4	INTO Drive	R/W	0	Configuration of the interrupt output pin INTO Ob = Pin is Hi-Z if there is no pending interrupt. Application provides an external pullup resistor if bit 3 (INTO High) = 0. Application provides an external pull- down resistor if bit 3 (INTO High) = 1. 1b = Pin is actively driven high or low if there is no pending interrupt. It is driven high if bit 3 (INTO High) = 0. It is driven low if bit 3 (INTO High) = 1.
3	INTO High	R/W	0	Configuration of the interrupt output pin INTO 0b = Interrupts are signaled with an active low 1b = Interrupts are signaled with an active high

表 5-11. General Control Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
				Global interrupt output enable
2	Enable INT	R/W	0	0b = Interrupt output disabled. The INTO pin is Hi-Z.
				1b = Interrupt output enabled. The INTO pin signals any enabled interrupt according to the INTO High and INTO Drive bits.
		R/W		Global enable of RF interface. This bit must be set before the PICC can respond to any RF commands.
1	Enable RF		0	0b = RF interface disabled
				1b = RF interface enabled
				Software reset
				0b = Always reads 0.
0	SW-Keset	W	0	1b = Resets the device to default settings and clears memory. The serial communication is restored after t_{Ready} , and the register settings and NDEF memory must be restored afterward.

表 5-11. General Control Register Description (continued)



5.11.2 Status Register

			18	J-12. Status	Register				
ADDRESS	15	14	13	12	11	10	9	8	
0xFFFD		Reserved							
ADDRESS	7	6	5	4	3	2	1	0	
0xFFFC	Rese	erved	Type 4 Command MSb	Type 4 Command LSb	Reserved	RF Busy	CRC Active	Device Ready	

表 5-12. Status Register

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-6	Reserved	R	0	Reserved for future use. Write with 0.
				This is set after a NFC Type 4 command is received and only must be serviced if a General Type 4 request interrupt has been asserted.
5-4				Bit 5 + Bit 4
	Type 4 Command	R	0	00b = No Type 4 command has been received
				01b = File Select Command has been received and must be serviced
				10b = Read Binary command has been received and must be serviced
				11b = Update Binary command has been received and must be serviced
3	Reserved	R	0	Reserved for future use. Write with 0.
2		Р	0	0b = No RF communication ongoing
2	RF Busy	ĸ	0	1b = RF communication ongoing
4	CPC Active	Р	0	0b = No CRC calculation ongoing
1		к	0	1b = CRC calculation ongoing
0	Davias Ready	Р	0	0b = Device not ready
0	Device Ready	R		1b = Device ready for serial communication and control

表 5-13. Status Register Description

5.11.3 Interrupt Registers

The interrupt enable register (see $\frac{1}{8}$ 5-14 and $\frac{1}{8}$ 5-15) determines which interrupt events are signaled on the external output pin INTO. Setting any bit high in this register allows the corresponding event to trigger the interrupt signal. See $\frac{1}{8}$ 5-18 for a description of each interrupt.

All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.

			12 J-14.	interrupt Li	iable Negisi	.01				
ADDRESS	15	14	13	12	11	10	9	8		
0xFFFB		Reserved								
ADDRESS	7	6	5	4	3	2	1	0		
0xFFFA	Generic Error	RF Field Removed	General Type 4 Request	BIP-8 Error Detected	CRC Calculation Completed		Reserved			

表 5-14. Interrupt Enable Register

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-9	Reserved	R	0	Reserved for future use. Write with 0.
				Enable for the Read Prefetch IRQ. All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.
8	Read Prefetch	R/W	0	0b = IRQ disabled
				1b = IRQ enabled
				Enable for the Generic Error IRQ. All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.
7	Generic Error	R/W	0	0b = IRQ disabled
				1b = IRQ enabled
				Enable for the RF Field Removed IRQ. All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.
6	RF Field Removed	R/W	0	0b = IRQ disabled
				1b = IRQ enabled
				Enable for the General Type 4 Request IRQ. All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.
5	General Type 4 Request	R/W	0	0b = IRQ disabled
				1b = IRQ enabled
				Enable for the BIP-8 Error Detected IRQ. All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.
4	BIP-8 Error Detected	R/W	0	0b = IRQ disabled
				1b = IRQ enabled
	3 CRC Calculation Completed	R/W		Enable for the CRC Calculation Completed IRQ. All enabled interrupt signals are ORed together, and the result is signaled on the output pin INTO.
3			0	0b = IRQ disabled
				1b = IRQ enabled
2-0	Reserved	R	0	Reserved for future use. Write with 0.

表 5-15. Interrupt Enable Register Description

The interrupt flag register (see $\frac{1}{8}$ 5-16 and $\frac{1}{8}$ 5-17) is used to report the status of any interrupts that are pending. Setting any bit high in this register acknowledges and clears the interrupt associated with the respective bit. See $\frac{1}{8}$ 5-18 for a description of each interrupt.

	A 5-10. Interrupt hag Register									
ADDRESS	15	14	13	12	11	10	9	8		
0xFFF9	Reserved									
ADDRESS	7	6	5	4	3	2	1	0		
0xFFF8	Generic Error	RF Field Removed	General Type 4 Request	BIP-8 Error Detected	CRC Calculation Completed		Reserved			

表 5-16. Interrupt Flag Register

15-9 Reserved R 0 Reserved for future use. Write with 0. 8 Read Prefetch R Flag pending Read Prefetch IRQ. 8 Read Prefetch R/W 0 1b = Pending IRQ 9 0b = No pending IRQ Write Access: 0b = No pending IRQ 9 No change 1b = Clear pending IRQ flag 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Clear pending IRQ flag 7 Generic Error R/W 0 1b = Clear pending IRQ flag 8 Flag pending Red Field Removed IRQ. Read Access: 0b = No pange 9 No panding IRQ 1b = Pending IRQ 1b = Pending IRQ 9 </th <th>BIT</th> <th>FIELD</th> <th>TYPE</th> <th>RESET</th> <th>DESCRIPTION</th>	BIT	FIELD	TYPE	RESET	DESCRIPTION
8 Read Prefetch R/W Read Access: 0b = No pending IRQ 8 Read Prefetch R/W 0 1b = Pending IRQ 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag 7 Generic Error R/W P Flag pending Generic Error IRQ. 8 Read Access: 0b = No change 1b = Clear pending IRQ flag 7 Generic Error R/W P Flag pending Generic Error IRQ. 8 Read Access: 0b = No change 0b = No change 10 No pending IRQ 1b = Pending IRQ 10 No pending IRQ 1b = Pending IRQ 10 No pending IRQ 1b = Pending IRQ 10 No pending IRQ flag 1b = Clear pending IRQ flag 11 Second IRQ No pending IRQ 12 No pending IRQ 1b = No pending IRQ 13 No pending IRQ 1b = No pending IRQ 14 No pending IRQ 1b = No pending IRQ 15 General Type 4 Request R/W No 14 Flag pending General Type 4 Request IRQ. Read Access: <td< td=""><td>15-9</td><td>Reserved</td><td>R</td><td>0</td><td>Reserved for future use. Write with 0.</td></td<>	15-9	Reserved	R	0	Reserved for future use. Write with 0.
8 Read Prefetch RW 0 Read Access: 0b = No pending IRQ 8 Read Prefetch RW 0 1b = Pending IRQ 9 No thange 1b = Clear pending IRQ flag 7 Generic Error RW 0 1b = Clear pending IRQ flag 7 Generic Error RW 0 1b = Ponding IRQ 10 De Ponding IRQ Read Access: 0b = No pending IRQ 10 No pending IRQ Read Access: 0b = No pending IRQ 10 Pending IRQ 1b = Clear pending IRQ 1b = Clear pending IRQ 10 No change 1b = Clear pending IRQ 1b = Clear pending IRQ 10 No change 1b = Clear pending IRQ 1b = Clear pending IRQ 10 No pending IRQ 1b = No ding IRQ 1b = Ponding IRQ 10 No change 1b = Pending IRQ 1b = Ponding IRQ 10 No change 1b = Clear pending IRQ 1b = No ding IRQ 10 No change 1b = Ponding IRQ 1b = Ponding IRQ 10 No change					Flag pending Read Prefetch IRQ.
8 Read Prefetch R/W 0 b = No pending IRQ 8 Read Prefetch R/W 0 tb = Pending IRQ 9 No change 0b = No change 0b = No change 1b = Clear pending IRQ flag Flag pending Generic Error IRQ. Read Access: 6 Representation of the pending IRQ flag 0b = No pending IRQ 6 RF Field Removed R/W 0 1b = Pending IRQ 6 RF Field Removed R/W 0 Flag pending RF Field Removed IRQ. 6 RF Field Removed R/W 0 Flag pending RF Field Removed IRQ. 7 General Type 4 Request R/W 0 1b = Pending IRQ 7 General Type 4 Request R/W 0 1b = Pending IRQ 7 General Type 4 Request R/W 0 1b = Pending IRQ 7 General Type 4 Request R/W 0 1b = Pending IRQ 7 Flag pending General Type 4 Request IRQ. Read Access: 0b = No pending IRQ 7 Flag pending General Type 4 Request IRQ. Read Acces					Read Access:
8 Read Prefetch R/W 0 1b = Pending IRQ 9 No change 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 8 Read Access: 0b = No pending IRQ 9 No pending IRQ 0b = No pending IRQ 9 No pending IRQ 0b = No pending IRQ 9 No pending IRQ 0b = No pending IRQ 9 No pending IRQ 0b = No pending IRQ 9 No pending IRQ flag 1b = Clear pending IRQ flag 9 RF Field Removed R/W 0 1b = Pending IRQ 9 No pending IRQ 1b = Pending IRQ Write Access: 9 No pending IRQ flag 1b = Clear pending IRQ flag 9 No pending IRQ 1b = Clear pending IRQ flag 9 No pending IRQ No pending IRQ 9 No pending IRQ No pending IRQ					0b = No pending IRQ
5 General Type 4 Request R/W R Write Access: 	8	Read Prefetch	R/W	0	1b = Pending IRQ
6 RF Field Removed RW 0 No change 6 Rerating Removed RW 0 Second Res 6 RF Field Removed RW 0 Flag pending IRQ 7 General Type 4 Request RW 0 Second Res 7 General Type 4 Request RW 0 Second Res 7 General Type 4 Request RW 0 Second Res 7 General Type 4 Request RW 0 Second Res 7 General Type 4 Request RW 0 Second Res					Write Access:
1 1					0b = No change
7 Generic Error R/W 0 Flag pending Generic Error IRQ. 7 Generic Error R/W 0 1b = Pending IRQ 0b = No pending IRQ Write Access: 0b = No change 1b = Clear pending RC flag 1b = Clear pending IRQ 6 RF Field Removed R/W 0 7 No pending IRQ Read Access: 0b = No change 1b = Clear pending RF Field Removed IRQ. 8 RF Field Removed R/W 0 1b = Pending IRQ 0b = No pending IRQ No pending IRQ 0b = No pending IRQ Write Access: 0b = No change 0b = No change 1b = Clear pending IRQ Write Access: 0b = No change 1b = Pending IRQ 1b = Clear pending IRQ flag No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ 5 General Type 4 Request R/W 0 1b = Pending IRQ 1b = No pending IRQ Norte Access: 0b = No pending IRQ Norte Access: 0b = No pending IRQ Norte Access: 0b = No pending IRQ Norte Access: 0b = No pending IRQ					1b = Clear pending IRQ flag
7 Generic Error RW RW 0 1b = Pending IRQ 7 Generic Error RW 0 1b = Pending IRQ 8 RF Generic Error NU 0 6 RF Field Removed RW PI Flag pending RF Field Removed IRQ. 6 RF Field Removed RW PI Flag pending IRQ 6 RF Field Removed RW PI Flag pending IRQ 6 RF Field Removed RW PI Flag pending IRQ 6 RF Field Removed RW PI Flag pending IRQ 7 Db = No change Db = No change Db = No change 10 Db = No change Db = No change Db = No change 10 Db = No change Db = No change Db = No change 10 De Clear pending IRQ flag Read Access: Db = No pending IRQ 7 General Type 4 Request RW PI Flag pending General Type 4 Request IRQ. 8 Read Access: Db = No pending IRQ Db = No pending IRQ 9 No pending IRQ Db = No change Db = No change					Flag pending Generic Error IRQ.
7 Generic Error RW 0 1b = Pending IRQ 7 Generic Error RW 0 1b = Pending IRQ 8 RF Herror Herror Herror 6 RF Field Removed RW 0 Flag pending IRQ flag 6 RF Field Removed RW 0 Herror 7 Herror Herror Herror Herror 7 Field Removed RW 0 Herror Herror 7 Herror Herror Herror Herror Herror 6 RF Field Removed RW 0 Herror Herror Herror 6 Herror Herror Herror Herror Herror Herror 6 Herror Herror Herror Herror Herror Herror 7 Herror Herror Herror					Read Access:
7 Generic Error R/W 0 1b = Pending IRQ 7 Generic Error R/W 0 1b = Pending IRQ 8 Field No b = No No 6 Field Removed R/W 0 1b = Clear pending IRQ flag 6 RF Field Removed R/W 0 1b = Pending IRQ 6 RF Field Removed R/W 0 1b = Pending IRQ 6 RF Field Removed R/W 0 1b = Pending IRQ 6 RF Field Removed R/W 0 1b = Pending IRQ 7 Definition (RC) No change 1b = Clear pending IRQ flag 7 General Type 4 Request R/W P Flag pending General Type 4 Request IRQ. 7 General Type 4 Request R/W 0 1b = Pending IRQ 7 General Type 4 Request R/W 0 1b = Pending IRQ 8 Provide Access: Ob = No change Ob = No change 9 No tenange Ob = No change Ob = No change 9 No tenange Ob = No change Ob = No change 1					0b = No pending IRQ
6 RF Field Removed R/W 0 Flag pending IRQ 6 RF Field Removed R/W 0 Bending IRQ 7 General Type 4 Request R/W 0 Flag pending General Type 4 Request 6 R/W 0 Bending IRQ 7 General Type 4 Request R/W 0 7 General Type 4 Request R/W 0 8 Flag pending IRQ Bending IRQ 9 No change Bending IRQ 10 No change Bending IRQ 10 No change Bending IRQ 10 No change Bending IRQ flag	7	Generic Error	R/W	0	1b = Pending IRQ
6 RF Field Removed R/W 0 Flag pending RF Field Removed IRQ. 6 RF Field Removed R/W 0 Flag pending IRQ 0b = No pending IRQ 0b = No pending IRQ 0b = No pending IRQ 0b = No pending IRQ 0b = No pending IRQ 0b = No pending IRQ 0b = No change 0b = No change 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag 5 General Type 4 Request R/W 0 5 General Type 4 Request R/W 0 1b = Pending IRQ 0b = No pending IRQ 1b = Pending IRQ 0b = No pending IRQ 5 General Type 4 Request R/W 0 1b = Pending IRQ 0b = No pending IRQ 1b = Pending IRQ 0b = No pending IRQ 1b = Dending IRQ 1b = Pending IRQ 0b = No pending IRQ 0b = No change 1b = Olear pending IRQ flag 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag					Write Access:
6 Image: Field Removed Image: Field Removed IRQ. 6 RF Field Removed R/W Pail Pending IRQ 6 RF Field Removed R/W Pail Pending IRQ 7 Description Description Description 5 General Type 4 Request R/W Pail Pending IRQ 5 General Type 4 Request R/W Pail Pending IRQ 6 R/W Description Description 7 General Type 4 Request R/W Pail Pending IRQ 7 General Type 4 Request R/W Pail Pending IRQ 7 General Type 4 Request R/W Pail Pending IRQ 7 General Type 4 Request R/W Pail Pending IRQ 7 Description Description Description 7 Description Description Description <					0b = No change
6 RF Field Removed R/W 0 Read Access: 0b = No pending IRQ 6 RF Field Removed R/W 0 1b = Pending IRQ 7 0b = No pending IRQ 0b = No change 1b = Clear pending IRQ flag 7 General Type 4 Request R/W 0 Flag pending IRQ 6 No pending IRQ 0b = No change 0b = No pending IRQ flag 7 General Type 4 Request R/W 0 Flag pending IRQ 7 Deneral Type 4 Request R/W 0 Ib = Pending IRQ 8 Deneral Type 4 Request R/W 0 Ib = Pending IRQ 9 No pending IRQ 1b = Pending IRQ Write Access: 9 No change 1b = Pending IRQ Write Access: 9 No change 1b = Pending IRQ Write Access: 9 No change 1b = Clear pending IRQ flag Write Access: 9 No change 1b = Clear pending IRQ flag The Clear pending IRQ flag					1b = Clear pending IRQ flag
6 RF Field Removed R/W 0 Read Access: 0b = No pending IRQ 0 1b = Pending IRQ Write Access: 0b = No change 0b = No change 1b = Clear pending IRQ flag 5 General Type 4 Request R/W 0 Flag pending IRQ 5 General Type 4 Request R/W 0 Ib = Pending IRQ 6 No pending IRQ Ib = No pending IRQ No pending IRQ 5 General Type 4 Request R/W 0 Ib = Pending IRQ 10 = No pending IRQ Ib = No pending IRQ Write Access: 0b = No pending IRQ 10 = No change Ib = Pending IRQ Ib = No change Ib = No change 11 = Declar pending IRQ Ib = No change Ib = No change Ib = Clear pending IRQ flag					Flag pending RF Field Removed IRQ.
6 RF Field Removed R/W 0 1b = Pending IRQ 6 RF Field Removed R/W 0 1b = Pending IRQ 6 Write Access: 0b = No change 0b = No change 7 General Type 4 Request R/W 0 Flag pending General Type 4 Request IRQ. 5 General Type 4 Request R/W 0 1b = Pending IRQ 6 No pending IRQ 0b = No pending IRQ 6 No pending IRQ 0b = No pending IRQ 6 No pending IRQ 0b = No pending IRQ 7 General Type 4 Request R/W 0 8 Pending IRQ 0b = No pending IRQ 9 No thange 0b = No change 10 = No change 0b = No change 0b = No change 10 = No change 1b = Clear pending IRQ flag 0b = No change 10 = No change 1b = Clear pending IRQ flag 0b = No change					Read Access:
6 RF Field Removed R/W 0 1b = Pending IRQ 6 Write Access: 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending General Type 4 Request IRQ. 5 General Type 4 Request R/W 0 1b = Pending IRQ 5 General Type 4 Request R/W 0 1b = Pending IRQ 6 No pending IRQ 0b = No pending IRQ 7 Beneral Type 4 Request R/W 0 1b = Pending IRQ Write Access: 0b = No pending IRQ 6 No pending IRQ Write Access: 0b = No change 1b = Clear pending IRQ 1b = Clear pending IRQ Write Access: 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag					0b = No pending IRQ
5 General Type 4 Request R/W 0 Flag pending IRQ 0b = No change 0b = No change 1b = Clear pending IRQ flag 5 General Type 4 Request R/W 0 Flag pending IRQ 0b = No pending IRQ 0b = No pending IRQ Write Access: 0b = No pending IRQ 1b = Pending IRQ Write Access: 0b = No change 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag 0b = No change	6	RF Field Removed	R/W	0	1b = Pending IRQ
5 General Type 4 Request R/W 0 1b = Pending IRQ 5 General Type 4 Request R/W 0 1b = Pending IRQ Write Access: 0b = No pending IRQ Write Access: 0b = No change 1b = Pending IRQ 1b = Pending IRQ 1b = Pending IRQ 1b = Pending IRQ Write Access: 0b = No change 1b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag					Write Access:
10 1b = Clear pending IRQ flag 10 1b = Clear pending IRQ flag 10 Flag pending General Type 4 Request IRQ. 10 Read Access: 10 0b = No pending IRQ 10 1b = Pending IRQ 10 Write Access: 10 0b = No change 10 1b = Clear pending IRQ flag					0b = No change
5 General Type 4 Request R/W 0 Flag pending General Type 4 Request IRQ. 5 General Type 4 Request R/W 0 1b = No pending IRQ Write Access: 0b = No change 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ					1b = Clear pending IRQ flag
5 General Type 4 Request R/W 0 Read Access: 0b = No pending IRQ 5 Write Access: 0b = No change 0b = No change 0b = No change 1b = Clear pending IRQ flag 1b = Clear pending IRQ flag					Flag pending General Type 4 Request IRQ.
5 General Type 4 Request R/W 0 b = No pending IRQ b = Pending IRQ Write Access: 0b = No change 1b = Clear pending IRQ flag					Read Access:
5 General Type 4 Request R/W 0 1b = Pending IRQ Write Access: 0b = No change 1b = Clear pending IRQ flag					0b = No pending IRQ
Write Access: 0b = No change 1b = Clear pending IRQ flag	5	General Type 4 Request	R/W	0	1b = Pending IRQ
0b = No change 1b = Clear pending IRQ flag					Write Access:
1b = Clear pending IRQ flag					0b = No change
					1b = Clear pending IRQ flag

表 5-17. Interrupt Flag Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
				Flag pending BIP-8 Error Detected IRQ.
				Read Access:
				0b = No pending IRQ
4	BIP-8 Error Detected	R/W	0	1b = Pending IRQ
				Write Access:
				0b = No change
				1b = Clear pending IRQ flag
				Flag pending CRC Calculation Completed IRQ.
				Read Access:
				0b = No pending IRQ
3	CRC Calculation Completed	R/W	0	1b = Pending IRQ
				Write Access:
				0b = No change
				1b = Clear pending IRQ flag
2-0	Reserved	R	0	Reserved for future use. Write with 0.

表 5-17. Interrupt Flag Register Description (continued)

表 5-18. Interrupts

	DESCRIPTION
INTERROPT	DESCRIPTION
CRC Calculation Completed	This IRQ occurs when a CRC calculation that is triggered by writing into the CRC registers is completed and the result can be read from the CRC result register (see $\ddagger 5.11.4$).
BIP-8 Error Detected	This IRQ occurs when a BIP-8 error is detected (only if the BIP-8 communication mode is enabled).
General Type 4 Request	This IRQ occurs if a NFC Type 4 command has been received (Select, Read Binary, Update Binary) and requires the service of the host controller.
RF Field Removed	This IRQ occurs when at least NDEF Tag Application Select command has been received and after that the RF field is removed.
Generic Error	This IRQ occurs for any error that makes the device unreliable or nonoperational.
Read Prefetch	This IRQ occurs immediately after Read Binary request has been serviced (automatically or manually) and the RF transmission has been started. This allows RF transmission and I ² C communication to happen at the same time.





5.11.4 CRC Registers

Writing the CRC address and the CRC length registers initiates a 16-bit CRC calculation of the specified address range. The length is always assumed to be even (16-bit aligned). Writing the length register starts the CRC calculation.

During the CRC calculation, the CRC active bit is set (= 1). When the calculation is complete, the CRC completion interrupt flag is set and the result of the CRC calculation can be read from the CRC result register. TI recommends performing a CRC calculation only when the RF interface is disabled (RF Enable = 0).

表 5-19 CRC Result Register

			- L (U		an nogiotoi				
ADDRESS	15	14	13	12	11	10	9	8	
0xFFF7	CRC CCITT Result (high byte)								
	•								
ADDRESS	7	6	5	4	3	2	1	0	
0xFFF6	CRC CCITT Result (low byte)								

CRC CCITI Result (low byte)	
表 5-20 CRC Result Register Descri	intion
C O LOI OILO ILOGUILI ILOGIOLOI DOCOI	ipuo ii

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-0	CRC-CCITT Result	R	0	CRC-CCITT Result

	表 5-21. CRC Length Register									
ADDRESS	15	14	13	12	11	10	9	8		
0xFFF5	CRC Length (high byte)									
ADDRESS	7	6	5	4	3	2	1	0		
0xFFF4		CRC Length (low byte)								

表 5-22. CRC Length Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-0	CRC Length	RW	0	CRC Length. Always assumed to be even (Bit $0 = 0$). Writing into high byte starts CRC calculation.

			表 5-23.(CRC Start A	ddress Regi	ster		
ADDRESS	15	14	13	12	11	10	9	8
0xFFF3	CRC Start Address (high byte)							
ADDRESS	7	6	5	4	3	2	1	0
0xFFF2		CRC Start Address (low byte)						

表 5-24. CRC Start Address Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-0	CRC Start Address	RW	0	CRC Start Address. Defines start address within NDEF memory. This address is always assumed to be even (bit $0 = 0$).

The CRC is calculated based on the CCITT polynomial initialized with 0xFFFF.

CCITT polynomial: $x^{16} + x^{12} + x^5 + 1$

5.11.5 Communication Watchdog Register

When the communication watchdog is enabled, it expects a write or read access within a specified period; otherwise, the watchdog resets the device. If the BIP-8 communication mode is enabled, the transfer must be valid to be accepted as a watchdog reset.

表 5-25. Communication Watchdog Register										
ADDRESS	15	14	13	12	11	10	9	8		
0xFFF1		Reserved								
ADDRESS	7	6	5	4	3	2	1	0		
0xFFF0		Rese	erved		Time	Enable				

表 5-26. Communication Watchdog Register Description

BIT	FIELD	TYPE	RESE T	DESCRIPTION
15-4	Reserved	R	0	Reserved for future use. Write with 0.
3-1	Time-out Period Selection	R/W	0	$000b = 2 \text{ s } \pm 30\% \ ^{(1)}$ $001b = 32 \text{ s } \pm 30\% \ ^{(1)}$ $010b = 8.5 \text{ min } \pm 30\% \ ^{(1)}$ 011b to 111b = Reserved
0	Enable	R/W	0	0b = Communication Watchdog disabled 1b = Communication Watchdog enabled

(1) This value is based on use of the integrated low-frequency oscillator with a frequency of 256 kHz ±30%.

5.11.6 Version Register

Provides version information about the implemented ROM code.

表 5-27. Version Register

ADDRESS	15	14	13	12	11	10	9	8				
0xFFEF		Major Version										
ADDRESS	7	6	5	4	3	2	1	0				
0xFFEE	Minor Version											

表 5-28. Version Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-8	Major Version	R	1	Software version
7-0	Minor Version	R	0	Software version



5.11.7 NDEF File Identifier Register

This register is used by the host controller to determine which file has been selected (or also for Read Binary and Update Binary commands as needed).

表 5-29. NDEF File Identifier	Register
------------------------------	----------

ADDRESS	15	14	13	12	11	10	9	8			
0xFFED		File Identifier Second Byte									
ADDRESS	7	6	5	4	3	2	1	0			
0xFFEC	File Identifier First Byte										

表 5-30. NDEF File Identifier Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-8	File Identifier Second Byte	R/W	0	This is the file identifier. It is references the second byte of the File ID in the Select command. (For example this byte for the Capability Container would be 03h).
7-0	File Identifier First Byte	R/W	0	This is the file identifier. It is references the first byte of the File ID in the Select command. (For example this byte for the Capability Container would be E1h).

5.11.8 Host Response Register

This register is used, after an interrupt is asserted by the RF430CL331H. It communicates various responses from the host controller. The actual interrupt flag clearing must happen immediately before setting the response in this register.

			A	i neet neep	enee negiet	•.		
ADDRESS	15	14	13	12	11	10	9	8
0xFFEB	Reserved	Reserved	Reserved	Reserved	Reserved	Reserved	Reserved	Reserved
	•	•			•			
ADDRESS	7	6	5	4	3	2	1	0
0xFFEA	Reserved	Reserved	Reserved	Reserved	Extra Data Sent In	Use Custom SW Response	File Exists	Interrupt Serviced

表 5-31. Host Response Register

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-4	Reserved	R/W	0	Reserved for future use. Write with 0.
3	Extra Data Sent In	R/W	0	This may only be set if the Read Prefetch interrupt has been asserted. This is possible only after a Read Binary command. This indicates to the RF430CL331H that extra data has been written to the buffer during RF data transmission to a previous Read Binary command. To enable this feature, the Extra Data Interrupt Enable must be set. This also called Prefetch on Read.
				0b = No extra data has been written.
				1b = Extra data has been written. Update buffer size.
2 Use C				This sets whether or not a custom SW (status word) should be responded to a NFC Type 4 command (Select, Read Binary, Update Binary).
	Use Custom SW Response	R/W	0	0b = Default response to the PCD.
				1b = Custom response to the PCD. The actual SW response is taken from the Custom SW Response Register.
			0	This is the response to the interrupt of General Type 4 Request with status of file select.
1	File Exists	R/W		0b = File named in the NDEF File Identifier Register does not exist.
				1b = File named in the NDEF File Identifier Register <i>does</i> exist.
	Internet Conviced	R/W	0	Setting this bit high after an interrupt (this applies only to General Type 4 Requests IRQ) has been asserted by the RF430CL331H indicates that the interrupt has been completely serviced. The actual interrupt flag clearing must happen immediately before setting this register.
Ũ				0b = The interrupt is in the process of being serviced by the host controller
				1b = The interrupt has been serviced, RF430CL331H to start processing the response

表 5-32. Host Response Register Description



5.11.9 NDEF Block Length Register

This register indicates the block length of the Read Binary or Update Binary commands to the host controller.

表 5-33. NDEF Block Length Register										
ADDRESS	15	14	13	12	11	10	9	8		
0xFFE9		Block Length MSB								
ADDRESS	7	6	5	4	3	2	1	0		
0xFFE8	Block Length LSB									

表 5-34. NDEF Block Length Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-8	Block Length MSB	R/W	0	Block length most significant byte.
7-0	Block Length LSB	R/W	0	Block length least significant byte.

5.11.10 NDEF File Offset Register

This register indicates the offset of the Read Binary or Update Binary commands to the host controller.

表 5-35. NDEF File Offset Register										
ADDRESS	15	14	13	12	11	10	9	8		
0xFFE7		File Offset MSB								
ADDRESS	7	6	5	4	3	2	1	0		
0xFFE6		File Offset LSB								

表 5-36. NDEF File Offset Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-8	File Offset MSB	R/W	0	File offset most significant byte.
7-0	File Offset LSB	R/W	0	File offset least significant byte.

5.11.11 Buffer Start Register

This register is written after a Read Binary command by the host controller indicating the index in buffer memory where the data started to be written. On an Update Binary command, this register indicates where the RF430CL331H has started to write the packet in its buffer memory.

	表 5-37. Buffer Start Register										
ADDRESS	15	14	13	12	11	10	9	8			
0xFFE5	Buffer Start MSB										
ADDRESS	7	6	5	4	3	2	1	0			
0xFFE4	Buffer Start LSB										

表 5-38. Buffer Start Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION			
15-8	Buffer Start MSB	R/W	0	Buffer start most significant byte.			
7-0	Buffer Start LSB	R/W	0	Buffer start least significant byte.			

5.11.12 SWTX Register

When a PCD issues a command, there is a time-out that is negotiated (FWI in the SENSB_RES/ATQB command). The RF430CL331H has this amount of time to respond to the PCD command. If this time-out cannot be met by RF430CL331H, the NFC protocol allows a sending a S(WTX) request (refer to Section 13.2.2 of the NFC Digital Protocol). This allows the time-out to be restarted after the PCD S(WTX) response.

When the internal state machine determines that a wait time extension is necessary, it uses this register value to populate the INF field of the S(WTX) request (refer to Table 84 of the NFC Digital Protocol). This custom setting response allows flexibility in negotiating this wait time extension.

表 5-39. SWTX Register

					-							
ADDRESS	15	14	13	12	11	10	9	8				
0xFFDF		Reserved										
ADDRESS	7	6	5	4	3	2	1	0				
0xFFDE		SWTX Request										

表 5-40. SWTX Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-8	Reserved	R/W	0	Reserved for future use. Write with 0.
7-0	SWTX Request	R/W	1	S(WTX) request byte.

5.11.13 Custom Status Word Response Register

On a NFC Type 4 command (Select, Read Binary, Update Binary), the response contains a status word (SW). This indicates whether or not the request was successful. By default, the RF430CL331H handles the SW responses automatically with predefined values. However, if custom responses are needed, for custom error status word responses, this feature may be used.

When the Use Custom SW Response is set in the Host Response register, the RF430CL331H firmware uses the SW set here to respond to the command.

ADDRESS	15	14	13	12	11	10	9	8				
0xFFDB		Custom Status Word Response MSB										
ADDRESS	7	6	5	4	3	2	1	0				
0xFFDA	Custom Status Word Response LSB											

表 5-41. Custom Status Word Response Register

表 5-42. Custom Status Word Response Register Description

BIT	FIELD	TYPE	RESET	DESCRIPTION
15-8	Custom Status Word Response MSB	R/W	0	Custom status word 1 (SW1).
7-0	Custom Status Word Response LSB	R/W	0	Custom status word 2 (SW2).

5.12 Identification

5.12.1 Revision Identification

The device revision information is shown as part of the top-side marking on the device package. The device-specific errata sheet describes these markings (see \ddagger 7.2.1).

5.12.2 Device Identification

The device type can be identified from the top-side marking on the device package. The device-specific errata sheet describes these markings (see \ddagger 7.2.1).

5.12.3 JTAG Identification

This device does not provide JTAG-compliant boundary scan test.

5.12.4 Software Identification

The Version register (see \ddagger 5.11.6) stores the software version number.



6 Applications, Implementation, and Layout

注

Information in the following Applications section is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

6.1 Application Diagram



For recommended capacitance values, see Recommended Operating Conditions.

图 6-1. Application Diagram

6.2 References

- 1. ISO/IEC 14443-2:2010, Part 2: Radio frequency interface power and signal interface (http://www.iso.org)
- 2. ISO/IEC 14443-3:2011, Part 3: Initialization and anticollision (http://www.iso.org)
- 3. ISO/IEC 14443-4:2008, Part 4: Transmission protocols (http://www.iso.org)
- 4. NFC Data Exchange Format (NDEF) Technical Specification (http://nfc-forum.org/)
- 5. NFC Forum Type 4 Tag Operation Specification (http://nfc-forum.org/)
- NFC Digital Protocol Technical Specification, Section 13.2.2, Frame Wait Time Extension (http://nfcforum.org/)

7 器件和文档支持

- 7.1 器件支持
- 7.1.1 开发支持
- 7.1.1.1 入门和下一步

德州仪器 (TI) 提供大量的开发工具,其中包括评估处理器性能、生成代码、开发算法工具、以及完全集成和 调试软件及硬件模块的工具。工具支持文档以电子文档形式提供,包含在 Code Composer Studio™集成开 发环境 (IDE)中。

下列产品为 RF430CL331H 器件的应用开发 提供支持:

软件开发工具: Code Composer Studio 集成开发环境 (IDE): 其中包括编辑器、C/C++/汇编代码生成工 具、调试工具以及其他开发工具。

硬件开发工具:有关 RF430CL331H 平台开发支持工具的完整列表,请访问德州仪器 (TI) 网站 www.ti.com。有关定价和购买信息,请联系最近的 TI 销售办事处或授权分销商。

7.1.2 器件和开发工具命名规则

为了指明产品开发周期所处的阶段,TI为所有 RF430 MCU 器件和支持工具的产品型号分配了前缀。每个商业系列成员都具有以下三个前缀中的一个:RF、P 或 X (例如,RFRF430FRL152H)。德州仪器 (TI) 建议为其支持的工具使用三个可用前缀指示符中的两个:RF 和 X。这些前缀代表了产品开发的发展阶段:即从工程原型设计(X 表示器件和工具)直到完全合格的生产器件和工具(RF 表示器件和工具)。

器件开发进化流程:

X-试验器件不一定代表最终器件的电气技术规格

P-芯片模型符合最终器件的电气技术规格,但是未经完整的质量和可靠性验证

RF - 完全合格的生产器件

支持工具开发发展流程:

X-还未经德州仪器 (TI) 完整内部质量测试的开发支持产品。

RF – 完全合格的开发支持产品

X 和 P 器件和 X 开发支持工具在供货时附带如下免责条款:

"开发的产品用于内部评估用途。"

RF 器件和 RF 开发支持工具已进行完全特性描述,并且器件的质量和可靠性已经完全论证。TI 的标准保修 证书适用。

预测显示原型器件(X 和 P)的故障率大于标准生产器件。由于这些器件的预计最终使用故障率仍未定义, 德州仪器 (TI) 建议不要将它们用于任何生产系统。只有合格的生产器件将被使用。

TI 器件的命名规则也包括一个带有器件系列名称的后缀。这个后缀包括封装类型(例如, RGE)和温度范围 (例如, T)。图 7-1 提供了读取任一系列产品成员完整器件名称的图例。

RF 430	CL 331 H A	I RGE R -EP
Processor Family <u>430 MCU Platform</u> <u>Device Typ</u> <u>Device D</u> <u>Wirel</u>	esignator ess Technology	Optional: Additional Features Optional: Tape and Reel Packaging Optional: Temperature Range
Processor Family	RF = Embedded RF r X = Experimental silic P = Prototype device	adio con
430 MCU Platform	TI's low-power microo	controller platform
Device Type	C = Fixed function L = Low-power series	
Device Designator	Various levels of integ	gration within a series
Wireless Technology	H = High frequency	
Optional: Revision	A = Device revision	
Optional: Temperature Range	$S = 0^{\circ}C \text{ to } 50^{\circ}C \\C = 0^{\circ}C \text{ to } 70^{\circ}C \\I = -40^{\circ}C \text{ to } 85^{\circ}C \\T = -40^{\circ}C \text{ to } 105^{\circ}C$	
Packaging	http://www.ti.com/pac	kaging
Optional: Tape and Reel	T = Small reel R = Large reel	

图 7-1. 器件命名规则

-EP = Enhanced product (-40°C to 105°C) -HT = Extreme temperature parts (-55°C to 150°C)

7.2 文档支持

7.2.1 相关文档

以下文档对 RF430CL331H 应答器进行了介绍。www.ti.com.cn 网站上提供了这些文档的副本。

No markings = Tube or tray

SLAZ672 **RF430CL331H 器件勘误表。** 描述了针对此器件的所有芯片修订版本功能技术规格的已知例外 情况。

7.3 社区资源

下列链接提供到 TI 社区资源的连接。链接的内容由各个分销商"按照原样"提供。这些内容并不构成 TI 技术 规范和标准且不一定反映 TI 的观点;请见 TI 的使用条款。

TI E2E™ 社区

TI 的工程师交流 (E2E) 社区。此社区的创建目的是为了促进工程师之间协作。在 e2e.ti.com 中,您可以提问、共享知识、拓展思路,在同领域工程师的帮助下解决问题。

TI 嵌入式处理器维基网页

Optional: Additional Features

德州仪器 (TI) 嵌入式处理器维基网页。此网站的建立是为了帮助开发人员熟悉德州仪器 (TI) 的嵌入式处理器,并且也为了促进与这些器件相关的硬件和软件的一般知识的创新和增长。

7.4 商标

Code Composer Studio, E2E are trademarks of Texas Instruments. *Bluetooth* is a registered trademark of Bluetooth SIG, Inc. Wi-Fi is a registered trademark of Wi-Fi Alliance.

7.5 静电放电警告



ESD 可能会损坏该集成电路。德州仪器 (TI) 建议通过适当的预防措施处理所有集成电路。如果不遵守正确的处理措施和安装程序,可能会损坏集成电路。

ESD 的损坏小至导致微小的性能降级,大至整个器件故障。精密的集成电路可能更容易受到损坏,这是因为非常细微的参数更改都可能会导致器件与其发布的规格不相符。

7.6 出口管制提示

接收方同意:如果美国或其他适用法律限制或禁止将通过非披露义务的披露方获得的任何产品或技术数据 (其中包括软件)(见美国、欧盟和其他出口管理条例之定义)、或者其他适用国家条例限制的任何受管制 产品或此项技术的任何直接产品出口或再出口至任何目的地,那么在没有事先获得美国商务部和其他相关政 府机构授权的情况下,接收方不得在知情的情况下,以直接或间接的方式将其出口。

7.7 Glossary

SLYZ022 — TI Glossary.

This glossary lists and explains terms, acronyms and definitions.

8 机械、封装和可订购信息

以下页中包括机械、封装和可订购信息。这些信息是针对指定器件可提供的最新数据。这些数据会在无通知 且不对本文档进行修订的情况下发生改变。要获得这份数据表的浏览器版本,请查阅左侧的导航栏。



PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS	Lead finish/	MSL rating/	Op temp (°C)	Part marking
	(1)	(2)			(3)	Ball material Peak reflow			(6)
						(4)	(5)		
RF430CL331HIPWR	Active	Production	TSSOP (PW) 14	2000 LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	CL331H
RF430CL331HIPWR.A	Active	Production	TSSOP (PW) 14	2000 LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	CL331H
RF430CL331HIRGTR	Active	Production	VQFN (RGT) 16	3000 LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	CL331H
RF430CL331HIRGTR.A	Active	Production	VQFN (RGT) 16	3000 LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	CL331H

⁽¹⁾ **Status:** For more details on status, see our product life cycle.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



Texas

STRUMENTS

TAPE AND REEL INFORMATION





QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*	All dimensions are nominal												
	Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
	RF430CL331HIPWR	TSSOP	PW	14	2000	330.0	12.4	6.9	5.6	1.6	8.0	12.0	Q1
Ĩ	RF430CL331HIRGTR	VQFN	RGT	16	3000	330.0	12.4	3.3	3.3	1.1	8.0	12.0	Q2



www.ti.com

PACKAGE MATERIALS INFORMATION

5-Dec-2023



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
RF430CL331HIPWR	TSSOP	PW	14	2000	338.1	338.1	20.6
RF430CL331HIRGTR	VQFN	RGT	16	3000	350.0	350.0	43.0

GENERIC PACKAGE VIEW

VQFN - 1 mm max height PLASTIC QUAD FLATPACK - NO LEAD



Images above are just a representation of the package family, actual package may vary. Refer to the product data sheet for package details.



RGT0016C



PACKAGE OUTLINE

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M. 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.



RGT0016C

EXAMPLE BOARD LAYOUT

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).

5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.



RGT0016C

EXAMPLE STENCIL DESIGN

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.



PW0014A



PACKAGE OUTLINE

TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M. 2. This drawing is subject to change without notice. 3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not
- exceed 0.15 mm per side.
- 4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
- 5. Reference JEDEC registration MO-153.



PW0014A

EXAMPLE BOARD LAYOUT

TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.

7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



PW0014A

EXAMPLE STENCIL DESIGN

TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



NOTES: (continued)

9. Board assembly site may have different recommendations for stencil design.



^{8.} Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.

重要通知和免责声明

TI"按原样"提供技术和可靠性数据(包括数据表)、设计资源(包括参考设计)、应用或其他设计建议、网络工具、安全信息和其他资源, 不保证没有瑕疵且不做出任何明示或暗示的担保,包括但不限于对适销性、某特定用途方面的适用性或不侵犯任何第三方知识产权的暗示担 保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任:(1) 针对您的应用选择合适的 TI 产品,(2) 设计、验 证并测试您的应用,(3) 确保您的应用满足相应标准以及任何其他功能安全、信息安全、监管或其他要求。

这些资源如有变更,恕不另行通知。TI 授权您仅可将这些资源用于研发本资源所述的 TI 产品的相关应用。 严禁以其他方式对这些资源进行 复制或展示。您无权使用任何其他 TI 知识产权或任何第三方知识产权。您应全额赔偿因在这些资源的使用中对 TI 及其代表造成的任何索 赔、损害、成本、损失和债务,TI 对此概不负责。

TI 提供的产品受 TI 的销售条款或 ti.com 上其他适用条款/TI 产品随附的其他适用条款的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。

TI 反对并拒绝您可能提出的任何其他或不同的条款。

邮寄地址:Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 版权所有 © 2025,德州仪器 (TI) 公司