

www.ti.com

Ten Output High Performance Clock Synchronizer, Jitter Cleaner, and Clock Distributor Check for Samples: CDCE72010

FEATURES

- High Performance LVPECL, LVDS, LVCMOS PLL Clock Synchronizer
- Two Reference Clock Inputs (Primary and Secondary Clock) for Redundancy Support with Manual or Automatic Selection
- Accepts Two Differential Input (LVPECL or LVDS) References up to 500MHz (or Two LVCMOS Inputs up to 250MHz) as PLL Reference
- VCXO_IN Clock is Synchronized to One of Two Reference Clocks
- VCXO_IN Frequencies up to 1.5GHz (LVPECL) 800MHz for LVDS and 250MHz for LVCMOS Level Signaling
- Outputs Can be a Combination of LVPECL, LVDS, and LVCMOS (Up to 10 Differential LVPECL or LVDS Outputs or up to 20 LVCMOS Outputs), Output 9 can be Converted to an Auxiliary Input as a 2nd VC(X)O.
- Output Divider is Selectable to Divide by 1, 2, 3, 4, 5, 6, 8, 10, 12, 16, 18, 20, 24, 28, 30, 32, 36, 40, 42, 48, 50, 56, 60, 64, 70, or 80 On Each Output Individually up to Eight Dividers. (Except for Output 0 and 9, Output 0 Follows Output 1 Divider and Output 9 Follows Output 8 Divider)
- SPI Controllable Device Setting
- Individual Output Enable Control via SPI Interface
- Integrated On-Chip Non-Volatile Memory (EEPROM) to Store Settings without the Need to Apply High Voltage to the Device
- Optional Configuration Pins to Select Between Two Default Settings Stored in EEPROM
- Efficient Jitter Cleaning from Low PLL Loop
 Bandwidth
- Very Low Phase Noise PLL Core
- Programmable Phase Offset (Input Reference to Outputs)

- Wide Charge-Pump Current Range From 200µA to 3mA
- Presets Charge-Pump to V_{CC_CP}/2 for Fast Center-Frequency Setting of VC(X)O, Controlled Via the SPI Bus
- SERDES Startup Mode (Depending on VCXO Range)
- Auxiliary Input: Output 9 can Serve as 2nd VCXO Input to Drive All Outputs or to Serve as PLL Feedback Signal
- RESET or HOLD Input Pin to Serve as Reset or Hold Functions
- REFERENCE SELECT for Manual Select Between Primary and Secondary Reference Clocks
- POWER DOWN (PD) to Put Device in Standby Mode
- Analog and Digital PLL Lock Indicator
- Internally Generated VBB Bias Voltages for Single-Ended Input Signals
- Frequency Hold-Over Mode Activated by HOLD Pin or SPI Bus to Improve Fail-Safe Operation
- Input to All Outputs Skew Control
- Individual Skew Control for Each Output with Each Output Divider
- Packaged in a QFN-64 Package
- ESD Protection Exceeds 2kV HBM
- Industrial Temperature Range of –40°C to 85°

APPLICATIONS

- Low Jitter Clock Driver for High-End Telecom and Wireless Applications
- High Precision Test Equipment



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

SCAS858C – JUNE 2008 – REVISED JANUARY 2012





These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

DESCRIPTION

The CDCE72010 is a high-performance, low phase noise, and low skew clock synchronizer that synchronizes a VCXO (Voltage Controlled Crystal Oscillator) or VCO (Voltage Controlled Oscillator) frequency to one of two reference clocks. The clock path is fully programmable providing the user with a high degree of flexibility. The following relationship applies to the dividers:

Frequency (VCXO_IN or AUX_IN) / Frequency (PRI_REF or SEC_REF) = (P*N)/(R*M)

The VC(X)O_IN clock operates up to 1.5GHz through the selection of external VC(X)O and loop filter components. The PLL loop bandwidth and damping factor can be adjusted to meet different system requirements.

The CDCE72010 can lock to one of two reference clock inputs (PRI_REF and SEC_REF) and supports frequency hold-over mode for fail-safe and system redundancy. The outputs of the CDCE72010 are user definable and can be any combination of up to 10 LVPECL/LVDS outputs or up to 20 LVCMOS outputs. The built-in synchronization latches ensure that all outputs are synchronized for very low output skew.

All device settings, including output signaling, divider value selection, input selection, and many more, are programmable with the SPI (4-wire Serial Peripheral Interface). The SPI allows individual control of the device settings.

The device operates in a 3.3V environment and is characterized for operation from -40°C to +85°C.



Figure 1. High Level Block Diagram of the CDCE72010





www.ti.com

AUX_SEL

U3P

U3N

U4N

SCAS858C – JUNE 2008 – REVISED JANUARY 2012



PACKAGE

The CDCE72010 is available in a 64-pin lead-free "green" plastic quad flatpack package with enhanced bottom thermal pad for heat dissipation. The Texas Instruments package designator is RGC (S-PQFP-N64).



PIN FUNCTIONS

	PIN		
NAME	NO.	1/0	DESCRIPTION
VCC	5, 8, 11, 14, 19 22, 25, 28, 31 34, 37, 40 and 43	Power	3.3V supply for the output buffers. $^{(2)}$
VCC_PLL	4, 63	A. Power	3.3V PLL supply voltage for the PLL circuitry.
VCC_IN	57, 60	A. Power	3.3V reference input buffers and circuitry supply voltage.
vcc_vcxo	51, 54	A. Power	3.3V VCXO input buffer and circuitry supply voltage.
GND	32	Ground	Ground connected to thermal pad internally.
GND	PAD	Ground	Ground on thermal pad. See layout recommendations.
VCCA	48, 49	A. Power	3.3V for internal analog circuitry power supply
GND_CP	2	A. Ground	Analog ground for charge pump
VCC_CP	64	A. Power	Charge pump power supply pin used to have the same supply as the external VCO/VCXO. It can be set from 2.3V to 3.6V.
SPI_MISO	15	0	3-State LVCMOS output is enabled when SPI_LE is asserted low. It is the serial data output to the SPI bus interface.
SPI_LE or CD1	45	I	LVCMOS input, control latch enable for the Serial Programmable Interface (SPI), with hysteresis in SPI mode. In configuration default mode this pin becomes CD1.
SPI_CLK or CD2	46	I	LVCMOS input, serial control clock input for the SPI bus interface, with hysteresis. <i>In configuration default mode this pin becomes CD2.</i>
SPI_MOSI or CD3	44	I	LVCMOS input, master out slave in as a serial control data input to CDCE72010 for the SPI bus interface. <i>In configuration default mode this pin becomes CD3 and it should be tied to GND.</i>

(1) It is recommended to use supply filter to each VCC supply domain independently.

(2) Pin 5 and 8, pin 28 and 31, pin 40 and 43, pin 51 and 54, pin 4 and 63 and pin 60 and 57 are internally connected.



www.ti.com

SCAS858C -JUNE 2008-REVISED JANUARY 2012

PIN FUNCTIONS (continued)

P	IN		
NAME	NO.	1/0	DESCRIPTION
MODE_SEL	16	I	SPI MODE = H ; when driven high or left unconnected, it defaults to SPI bus interface mode. CD (Configuration Default) MODE = L ; If tied low the device goes into configuration default mode which is configured by CD1, CD2, CD3, and AUX_SEL. In configuration default mode the device loads various configuration defaults from the EEPROM into memory at start-up.
AUX_SEL	18	I	This pin is used in CD mode only. If set to "1" or left unconnected, it disables output 9 and enables the AUXILIARY input to drive all outputs from output0 to output8 depending on the EEPROM configuration. If driven low in CD mode, it enables output 9 and makes all outputs driven by the VCXO Input depending on the internal EEPROM configuration.
REF_SEL	47	I	If Auto Reference Select mode is OFF, this pin acts as an External Input Reference Select Pin; The REF_SEL signal selects one of two input clocks: REF_SEL [1]: PRI_REF is selected; REF_SEL [0]: SEC_REF is selected; The input has an internal 150- $k\Omega$ pull-up resistor and if left unconnected it will default to logic level "1". If Auto Reference Select mode in ON, this pin not used.
PD	17	I	This pin is active low and can be activated externally or by the corresponding bit in the SPI register (in case of logic high, the SPI setting is valid). This pin switches the device into powerdown mode The input has an internal 150-k Ω pull-up resistor and if left unconnected it will default to logic level "1".
RESET or HOLD	33	I	This LVCMOS input can be programmed (SPI) to act as $\overline{\text{HOLD}}$ or $\overline{\text{RESET}}$. $\overline{\text{RESET}}$ is the default function. This pin is active low and can be activated external or via the corresponding bit in the SPI register. In the case of $\overline{\text{RESET}}$, the CP (Charge Pump) is switched to 3-state and all counters are reset to zero. The LVPECL outputs are static low (N) and high (P) respectively, and the LVCMOS outputs are all low or high if inverted. In the case of $\overline{\text{HOLD}}$, the CP (Charge Pump) is switched into 3-state mode only. After $\overline{\text{HOLD}}$ is released and with the next valid reference clock cycle, the charge pump is switched back into normal operation (CP stays in 3-state as long as no reference clock is valid). During $\overline{\text{HOLD}}$, all outputs are at normal operation. This mode allows external control of "frequency hold-over" mode. The input has an internal 150-k Ω pull-up resistor.
VCXO_IN+	53	I	VCXO input (+) for LVPECL+, LVDS+, and LVCMOS level inputs.
VCXO_IN-	52	I	Complementary VCXO input for LVPECL-, LVDS- inputs. In the case of a LVCMOS level input on VCXO IN+, ground this pin through 1k resistor.
PRI_REF+	59	I	Universal input buffer (LVPECL, LVDS, LVCMOS) positive input for the Primary Reference Clock.
PRI_REF-	58	I	Universal input buffer (LVPECL, LVDS) negative input for the Primary Reference Clock. In the case of LVCMOS signaling, ground this pin through 1k resistor.
SEC_REF+	62	I	Universal input buffer (LVPECL, LVDS, LVCMOS) positive input for the Secondary Reference Clock.
SEC_REF-	61	I	Universal input buffer (LVPECL, LVDS,) negative input for the Secondary Reference Clock. In the case of LVCMOS signaling, ground this pin through 1k resistor.
TESTOUTA	1	Α	Analog Test Point for TI internal testing. Connect a $1k\Omega$ pull-down resistor or leave unconnected.
STATUS	55	0	LVCMOS output for TI internal testing. Leave unconnected unless it is configured as the IREF_CP pin. In this case it should be connected to a 12 -k Ω resistor to GND.
CP_OUT	3	AO	Charge pump output
VBB	56	AO	Internal voltage bias analog output
PLL_LOCK	50	AO	LVCMOS output for PLL_LOCK information. This pin is set high if the PLL is in lock. This output can be programmed to be a digital lock detect or analog lock detect (see description of Analog Lock).
U0P:U0N U1P:U1N U2P:U2N U3P:U3N U4P:U4N U5P:U5N U6P:U6N U7P:U7N U8P:U8N	7, 6 10, 9 13, 12 21, 20 24, 23 27, 26 30, 29 36, 35 39, 38	0	The outputs of the CDCE72010 are user definable and can be any combination of up to 9 LVPECL outputs, 9 LVDS outputs, or up to 18 LVCMOS outputs. The outputs are selectable via the SPI interface. The power-up setting is EEPROM configurable.

www.ti.com

STRUMENTS

XAS

PIN FUNCTIONS (continued)

	PIN	1/0	
NAME	NO.	1/0	DESCRIPTION
U9P or AUXINP	42	I/O	Positive universal output buffer 9 can be 3-stated and used as a positive universal auxiliary input buffer (It requires external termination). The auxiliary input signal can be routed to drive the outputs or the feedback loop to the PLL.
U9N or AUXINN	41	I/O	Negative universal output buffer 9 can be 3-stated and used as a negative universal auxiliary input buffer (It requires external termination). The auxiliary input signal can be routed to drive the outputs or the feedback loop to the PLL.

PACKAGE THERMAL RESISTANCE FOR QFN (RGZ) PACKAGE⁽¹⁾ ⁽²⁾

AIRFLOW (LFM)		θ _{JP} (°C/W) ⁽³⁾	θ _{JA} (°C/W)
0	JEDEC compliant board (6×6 VIAs on PAD)	1.5	28
100	JEDEC compliant board (6×6 VIAs on PAD)	1.5	17.6
0	Recommended layout (10×10 VIAs on PAD)	1.5	22.8
100	Recommended layout (10×10 VIAs on PAD)	1.5	13.8

(1) The package thermal impedance is calculated in accordance with JESD 51 and JEDEC2S2P (high-k board).

(2) Connected to GND with 9 thermal vias (0.3 mm diameter).

(3) θ_{JP} (Junction – Pad) is used for the QFN package, because the main heat flow is from the junction to the GND-pad of the QFN.

ABSOLUTE MAXIMUM RATINGS

over operating free-air temperature range (unless otherwise noted)

			MIN	MAX	UNIT
V _{CC} , AV _{CC} , V _{CC_CP}	Supply voltage range ⁽¹⁾		-0.5	4.6	V
VI	Input voltage range ⁽²⁾		-0.5	$V_{CC} + 0.5$	V
Vo	Output voltage range ⁽²⁾		-0.5	V _{CC} + 0.5	V
	Input current	$V_{\rm I} < 0, V_{\rm I} > V_{\rm CC}$		±20	mA
	Output current for LVPECL/LVCMOS Outputs	$0 < V_O < V_{CC}$		±50	mA
TJ	Junction temperature			125	°C
T _{stg}	Storage temperature range		-65	150	°C

(1) All supply voltages have to be supplied simultaneously.

(2) The input and output negative voltage ratings may be exceeded if the input and output clamp-current ratings are observed.



www.ti.com

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

RECOMMENDED OPERATING CONDITIONS

for the CDCE72010 device for under the specified industrial temperature range of -40°C to 85°C

			MIN	NOM	MAX	UNIT
Power Suppl	у					
V _{CC}	Supply voltage		3	3.3	3.6	V
V _{CC_PLL} , V _{CC_IN} , V _{CC_VCXO} , V _{CCA}	Analog supply voltage		3	3.3	3.6	
V _{CC_CP}			2.3		V_{CC}	V
P _{LVPECL}	REF at 30.72MHz VCXO at 491.52MHz Outputs are LVPECL-HS	Divider 1 set to divide by 8 (DCR 30%) Divider 2 set to divide by 4 (DCR 30%) Divider 3 set to divide by 2 (DCR 30%) Divider 4 set to divide		2.9		W
P _{LVDS}	REF at 30.72MHz VCXO at 491.52MHz Outputs are LVDS-HS	by 2 (DCR 30%) Divider 5 set to divide by 1 (DCR 30%) Divider 6 set to divide by 1 (DCR 0%) Divider 7 set to divide by 1 (DCR 0%)		2.0		W
P LVCMOS	REF at 30.72MHz VCXO at 122.88MHz Outputs are LVCMOS	Divider 8 set to divide by 1 (DCR 0%) DCR: Divider Current Reduction Setting		2.2		W
P _{OFF}	REF at 30.72MHz VCXO at 491.52MHz	Dividers are disabled. Outputs are disabled.		775		mW
P _{PD}		Device is powered down		30		mW
Typical Opera	ating Conditions at V_{CC} = 3.3V and 25°	C unless otherwise specified.				
Differential In	nput Mode (PRI_REF, SEC_REF, VC	XO_IN and AUX_IN)	1			
V _{IN}	Differential input amplitude	(V _{INP} – V _{INN})	0.1		1.3	V
V _{ICM}	Common-mode input voltage		1.0		V _{CC} - 0.3	V
IIH	Differential input current high (No internal termination)	$V_{I} = V_{CC}, V_{CC} = 3.6 V$			20	μA
IIL	Differential input current low(No internal termination)	$V_{I} = 0 V, V_{CC} = 3.6 V$	-20		20	μA
	Input capacitance on PRI_REF, SE	C_REF and VCXO_REF		3		pF
	Input capacitance on AUX_IN			7		pF
LVCMOS Inp	ut Mode (SPI_CLK, SPI_MOSI, SPI_	LE, PD, RESET, REF_SEL, MODE_SEL)				
V _{IL}	Low-level input voltage LVCMOS		0		$0.3 \ V_{CC}$	V
V _{IH}	High-level input voltage LVCMOS		0.7 V _{CC}		V_{CC}	V
V _{IK}	LVCMOS input clamp voltage	$V_{CC} = 3 \text{ V}, \text{ II} = -18 \text{ mA}$			-1.2	V
I _{IH}	LVCMOS input current	$V_{I} = V_{CC}, V_{CC} = 3.6 V$			20	μΑ
I _{IL}	LVCMOS input	$V_{I} = 0 V, V_{CC} = 3.6 V$	-10		-40	μA
Cl	Input capacitance (LVCMOS signals)	$V_I = 0 V \text{ or } V_{CC}$		3		pF

www.ti.com

TIMING REQUIREMENTS

over recommended ranges of supply voltage, load, and operating free-air temperature $^{(1)}$ $^{(2)}$

	PARAMETER	MIN	TYP MA	X UNIT
PRI_REF/SEC_	REF			
f _{REF - Single}	For single-ended inputs (LVCMOS) on PRI_REF and SEC_REF		25	0 MHz
f _{REF} - Diff	For differential inputs (LVDS and LVPECL) on PRI_REF and SEC_REF (R divider set to DIV2)		50	0 MHz
Duty Cycle	Duty cycle of PRI_REF or SEC_REF	40%	60'	6
t _{slew}	Input signal slew rate	1		V/ns
VCXO_IN, AUX	_IN			
f _{REF} - Single	For single-ended inputs (LVCMOS)		25	0 MHz
f _{REF - Diff}	For differential inputs (LVDS and LVPECL)		150	0 MHz
Duty Cycle	Duty cycle of PRI_REF or SEC_REF	40%	60'	6
t _{slew}	Input signal slew rate	1		V/ns
PD, RESET, Ho	ld, REF_SEL			
t _r /t _f	Rise and fall time of the $\overline{\text{PD}}$, $\overline{\text{RESET}}$, $\overline{\text{Hold}}$, REF _SEL signal from 20% to 80% of the signal			4 ns

(1) From 250MHz to 500MHz is achieved by setting the divide by 2 in the R-divdier

(2) If the feedback clock (derived from the VCXO input) is less than 2MHz, the device stays in normal operation mode but the frequency detection circuitry resets the STATUS_VCXO signal and PLL_LOCK signal to low. Both status signals are no longer relevant. This affects the HOLD-Over-Function as well as the PLL_LOCK signal is no longer valid.

www.ti.com

AC/DC CHARACTERISTICS

over the specified industrial temperature range of -40°C to 85°C

	PARAMETER	TEST CC	NDITIONS	MIN	TYP ⁽¹⁾	MAX	UNIT
SPI Output	(MISO) / PLL_LOCK	1					
I _{OH}	High-level output current	V _{CC} = 3.3 V	V _O = 1.65 V		-30		mA
I _{OL}	Low-level output current	V _{CC} = 3.3 V	V _O = 1.65 V		33		mA
V _{OH}	High-level output voltage for LVCMOS outputs	$V_{CC} = 3 V$	I _{OH} = -100 μA	V _{CC} -0.5			V
V _{OL}	Low-level output voltage for LVCMOS outputs	$V_{CC} = 3 V$	I _{OL} = 100 μA			0.3	V
Co	Output capacitance on MISO	$V_{CC} = 3.3 \text{ V}; \text{ VO} = 0 \text{ V}$	/ or V _{CC}		3		pF
I _{OZH}	2 state sutput surrant	$V_{O} = V_{CC}$			5		μΑ
I _{OZL}	3-state output current	$V_0 = 0 V$			-5		μA
EEPROM							
EEcyc	Programming cycle of EEPROM			100	1000		Cycles
EEret	Data retention			10			Years
VBB							
VBB	VCXO termination voltage depends on the settings of the VCXO/AUX_IN input buffers	IBB = -0.2 mA Depending on the sett = 25 Ω	IBB = -0.2 mA Depending on the setting, Output impedance = 25 Ω			1.9	V
Input Buffe	rs Internal Termination Res	sistors (VCXO_IN,PRI_	REF and SEC_REF)				
	Termination resistance ⁽²⁾	Single ended			53		Ω
Phase Dete	ctor						
f _{CPmax}	Maximum charge pump frequency	Default PFD pulse wic	lth delay			100	MHz
Charge Pun	np						
ICP3St	Charge pump 3-state current	0.5 V < VCP < V _{CC_CF}	s – 0.5 V		15		nA
ICPA	ICP absolute accuracy	$V_{CP} = 0.5 V_{CC_CP}$; inte	ernal reference resistor		20%		
ICPA	ICP absolute accuracy	VCP = 0.5 V _{CC_CP} ; ex 12kΩ (1%)	ternal reference resistor		5%		
ICPM	Sink/source current matching	0.5 V < VCP < V _{CC_CF} settings	- 0.5 V, SPI default		%4		
IVCPM	ICP vs VCP matching	0.5 V < VCP < V _{CC_CF}	o – 0.5 V		6%		
V _{I_REF_CP}	Voltage on STATUS PIN when configured as I_REF_CP	12-kΩ resitor to GND (External current path pump current)	for accurate charge		1.24		V

(1) All typical values are at V_{CC} = 3.3 V, T_A = 25°C. (2) Termination resistor can vary by 20%.

TEXAS INSTRUMENTS

www.ti.com

AC/DC CHARACTERISTICS (CONTINUED)

over the specified industrial temperature range of -40° C to 85° C

	PARAMETER	TEST C	ONDITIONS	MIN	TYP ⁽¹⁾	MAX	UNIT
LVCMOS O	utput		· · · ·				
f _{clk}	Output frequency (see Figure 2)	Load = 5 pF to GND				250	MHz
V _{OH}	High-level output voltage for LVCMOS outputs	V _{CC} = min to max	I _{OH} = −100 μA	V _{CC} – 0.5			V
V _{OL}	Low-level output voltage for LVCMOS outputs	V _{CC} = min to max	I _{OL} =100 μA			0.3	V
I _{OH}	High-level output current	V _{CC} = 3.3 V	V _O = 1.65 V		-30		mA
I _{OL}	Low-level output current	V _{CC} = 3.3 V,	V _O = 1.65 V		33		mA
t _{pho}	Phase offset without using available delay adjustment	VCXO at 491.52MHz 16 and reference at a delays are fixed to or	z, Output 1 is divide by 30.72MHz, M and N ne value (set to 0).		13		ns
t _{pd(LH)} / tpd(HL)	Propagation delay from VCXO_IN to Outputs	Crosspoint to V _{CC} /2,	load = 5 pF		3.3		ns
		Divide by 1 for all dividers			75		
t _{ak(a)}	Skew, output-to-output LVCMOS single-ended output	Divide by 16 for all dividers			75		ps
·SK(0)		Divide by 1 for divide all other dividers	er 1 and divide by 16 for		1400		P.
Co	Output capacitance on Y0 to Y8	$V_{CC} = 3.3 \text{ V}; V_{O} = 0$	V or V _{CC}		5		pF
Co	Output capacitance on Y9	$V_{CC} = 3.3 \text{ V}; V_{O} = 0$	V or V _{CC}		5		pF
I _{OZH}	3-state LVCMOS output current	$V_{O} = V_{CC}$			5		μA
I _{OZL}	3-state LVCMOS output current	$V_{O} = 0V$			-5		μA
I _{OPDH}	Power-down output current	$V_{O} = V_{CC}$				25	μA
I _{OPDL}	Power-down output current	$V_{O} = 0V$				5	μA
Duty cycle	LVCMOS	With 50% / 50% duty clock	v cycle of the VCXO input	45%		55%	
t _{slew-rate}	Output rise/fall slew rate			3.6		5.2	V/ns

(1) All typical values are at V_{CC} = 3.3 V, T_A = 25°C.



www.ti.com

SCAS858C -JUNE 2008-REVISED JANUARY 2012

AC/DC CHARACTERISTICS (CONTINUED)

over the specified industrial temperature range of -40°C to 85°C

	PARAMETER	TEST CONDITIONS	MIN	TYP ⁽¹⁾	MAX	UNIT
LVDS Out	out		L		Ļ	
f _{clk}	Output frequency		0		800	MHz
V _{OD}	Differential output voltage	R _L = 100 Ω	160		270	mV
Δ_{VOD}	LVDS VOD magnitude change				50	mV
V _{OS}	Offset voltage	–40°C to 85°C		1.24		V
ΔV_{OS}	V _{OS} magnitude change			40		mV
	Short circuit V _{OUT+} to ground	V _{OUT} = 0			27	mA
	Short circuit V _{OUT} to ground	V _{OUT} = 0			27	mA
t _{pho} ⁽²⁾	Reference to output phase offset without using available delay adjustment	VCXO at 491.52MHz, Output 1 is divide by 16 and reference at 30.72MHz, M and N delays are fixed to one value (set to 0), PFD: 240kHz, (M and N = 128)		14		ns
t _{pd(LH)} / t _{pd(HL)}	Propagation delay time, VCXO_IN to output	Crosspoint to crosspoint, load		3.0		ns
		Divide by 1 for all dividers		45		
$tsk(0)^{(3)}$	Skew, output to output	Divide by 16 for all dividers		50		ps
	LVDS output	Divide by 1 for divider 1 Divide by 16 for all other dividers		2800		6.
Co	Output capacitance on Y0 to Y8	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		5		pF
Co	Output capacitance on Y9	$V_{CC} = 3.3 \text{ V}; V_{O} = 0 \text{ V or } V_{CC} \text{ 5}$		7		pF
I _{OPDH}	Power-down output current	$V_{O} = V_{CC}$			25	μA
I _{OPDL}	Power-down output current	V _O = 0V			5	μA
	Duty cycle		45		55	%
t _r /t _f	Rise and fall time	20% to 80% of V _{outpp}	110	140	160	ps
LVCMOS-1	ro-lvds ⁽⁴⁾					
tsk _{P_C}	Output skew between LVCMOS and LVDS outputs	Crosspoint to $V_{CC}/2$. Outputs are at the same output frequency and use the same output divider configuration.	0.9	1.4	1.9	ns

(1)

All typical values are at V_{CC} = 3.3 V, T_A = 25°C. This is valid only for same REF_IN clock and Y output clock frequency. It can be adjusted by the SPI controller (reference delay M and (2) VCXO delay N).

The tsk(o) specification is only valid for equal loading of all outputs. (3)

(4) The phase of LVCMOS is lagging in reference to the phase of LVDS.

ÈXAS NSTRUMENTS

www.ti.com

AC/DC CHARACTERISTICS (CONTINUED)

over the specified industrial temperature range of -40°C to 85°C

	PARAMETER	TEST CONDITIONS	MIN	TYP ⁽¹⁾	MAX	UNIT
LVDS Hi Sw	ving Output					
f _{clk}	Output frequency		0		800	MHz
V _{OD}	Differential output voltage	R _L =100 Ω	270		550	mV
Δ_{VOD}	LVDS VOD magnitude change				50	mV
V _{OS}	Offset voltage	–40°C to 85°C		1.24		V
ΔV_{OS}	V _{OS} magnitude change			40		mV
	Short Circuit V _{OUT+} to ground	V _{OUT} = 0			27	mA
	Short Circuit V _{OUT} to ground	V _{OUT} = 0			27	mA
t _{pho} ⁽²⁾	Reference to output phase offset without using available delay adjustment	VCXO at 491.52MHz, Output 1 is divide by 16 and reference at 30.72 MHz. M and N delays are fixed to one value. (Set to 0) PFD: 240kHz, (M and N = 128)		14		ns
t _{pd(LH)} / t _{pd(HL)}	Propagation delay time, VCXO_IN to output	Crosspoint to crosspoint		3.0		ns
	LVDS output skew	Divide by 1 for all dividers		45		
$t_{ak(a)}$ (3)		Divide by 16 for all dividers		50		DS
^{-5K(0)}		Divide by 1 for divider 1 Divide by 16 for all other dividers		2800		po
Co	Output capacitance on Y0 to Y8	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		5		pF
Co	Output capacitance on Y9	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		7		pF
IOPDH	Power-down output current	$V_{O} = V_{CC}$			25	μA
IOPDL	Power-down output current	$V_{O} = 0V$			5	μA
Duty cycle			45		55	%
t _r /t _f	Rise and fall time	20% to 80% of V _{outpp}	110	160	190	ps
LVCMOS-TO	D-LVDS ⁽⁴⁾		-			
tsk _{P_C}	Output skew between LVCMOS and LVDS outputs	Crosspoint to $V_{CC}/2$. Outputs are at the same output frequency and use the same output divider configuration with same output frequencies and divider values	0.9	1.4	1.9	ns

(1)

All typical values are at $V_{CC} = 3.3 \text{ V}$, $T_A = 25^{\circ}\text{C}$. This is valid only for same REF_IN clock and Y output clock frequency. It can be adjusted by the SPI controller (reference delay M and VCXO delay N). (2)

(3)

The tsk(o) specification is only valid for equal loading of all outputs. The phase of LVCMOS is lagging in reference to the phase of LVDS. (4)



www.ti.com

AC/DC CHARACTERISTICS (CONTINUED)

over the specified industrial temperature range of -40°C to 85°C

	PARAMETER	TEST CONDITIONS	MIN	TYP ⁽¹⁾	MAX	UNIT	
LVPECL Out	tput						
f _{clk}	Output frequency		0		1500	MHz	
V _{OH}	LVPECL high-level output voltage	Load, see Figure 5	V _{CC} – 1.06		V _{CC} – 0.88	V	
V _{OL}	LVPECL low-level output voltage	Load, see Figure 5	V _{CC} – 2.02		V _{CC} – 1.58	V	
VOD	Differential output voltage	Load, see Figure 5	610		970	mV	
t _{pho} ⁽²⁾	Reference to output phase offset without using available delay adjustment	VCXO at 491.52MHz, Output 1 is divide by 16 and reference at $30.72MHz$, M and N delays are fixed to one value (set to 0), PFD: 240kHz, (M and N = 128)		14		ns	
t _{pd(LH)} / t _{pd(HL)}	Propagation delay time, VCXO_IN to output	Crosspoint to crosspoint, load		3.4		ns	
	LVPECL output skew	Divide by 1 for all dividers		45			
tak(a) (3)		Divide by 16 for all dividers		50		ps	
SK(0)		Divide by 1 for divider 1 Divide by 16 for all other dividers		2700		F.~	
Co	Output capacitance on Y0 to Y8	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		5		pF	
Co	Output capacitance on Y9	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		7		pF	
IOPDH	Power-down output current	$V_{O} = V_{CC}$			25	μA	
IOPDL	Power-down output current	V _O = 0 V			5	μΑ	
	Duty cycle		45		55	%	
t _r /t _f	Rise and fall time	20% to 80% of V _{outpp}	55	75	135	ps	
LVDS-TO-L	/PECL				·		
tsk _{P_C}	Output skew between LVDS and LVPECL outputs	Crosspoint to Crosspoint with same output frequencies and divider values	0.9	1.1	1.3	ns	
LVCMOS-TO	D-LVPECL						
tsk _{P_C}	Output skew between LVCMOS and LVPECL outputs	V _{CC} /2 to Crosspoint; With same output frequencies and divider values	-150	260	700	ps	

(1) All typical values are at $V_{CC} = 3.3 \text{ V}$, $T_A = 25^{\circ}\text{C}$. (2) This is valid only for same REF_IN clock and Y output clock frequency. It can be adjusted by the SPI controller (reference delay M and VCXO delay N).

(3) The tsk(o) specification is only valid for equal loading of all outputs. :

EXAS STRUMENTS

www.ti.com

AC/DC CHARACTERISTICS (CONTINUED)

over the specified industrial temperature range of -40°C to 85°C

I	PARAMETER	TEST CONDITIONS	MIN	TYP ⁽¹⁾	MAX	UNIT	
LVPECL Hi S	Swing Output						
f _{clk}	Output frequency		0		1500	MHz	
V _{OH}	LVPECL high-level output voltage	Load, see Figure 5	V _{CC} – 1.11	V	_{CC} – 0.87	V	
V _{OL}	LVPECL low-level output voltage	Load, see Figure 5	V _{CC} – 2.06	V	_{CC} – 1.73	V	
IVODI	Differential output voltage	Load, see Figure 5	760		1160	mV	
t _{pho} ⁽²⁾	Reference to output phase offset without using available delay adjustment	VCXO at 491.52MHz, Output 1 is divide by 16 and reference at 30.72MHz, M and N delays are fixed to one value (set to 0), PFD: 240kHz, (M and N = 128)		14		ns	
t _{pd(LH)} / t _{pd(HL)}	Propagation delay time, VCXO_IN to output	Crosspoint to crosspoint, load		3.4		ns	
	LVPECL output skew	Divide by 1 for all dividers		45			
t-1.(-) (3)		Divide by 16 for all dividers		50		ns	
^t sk(o)		Divide by 1 for divider 1 Divide by 16 for all other dividers		2700			
Co	Output capacitance on Y0 to Y8	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		5		pF	
Co	Output capacitance on Y9	V_{CC} = 3.3 V; V_{O} = 0 V or V_{CC}		7		pF	
IOPDH	Power-down output current	$V_{O} = V_{CC}$			25	μA	
IOPDL	Power-down output current	$V_{O} = 0V$			5	μA	
	Duty cycle		45%		55%		
t _r /t _f	Rise and fall time	20% to 80% of V _{outpp}	55	75	135	ps	
LVDS-TO-LV	PECL				·		
tsk _{P_C}	Output skew between LVDS and LVPECL outputs	Crosspoint to Crosspoint; with same output frequencies and divider values	0.9	1.1	1.3	ns	
LVCMOS-TO	-LVPECL						
tsk _{P_C}	Output skew between LVCMOS and LVPECL outputs ⁽⁴⁾	$V_{\mbox{CC}}/2$ to Crosspoint; With same output frequencies and divider values	-150	260	700	ps	

All typical values are at V_{CC} = 3.3 V, T_A = 25°C.
 This is valid only for same REF_IN clock and Y output clock frequency. It can be adjusted by the SPI controller (reference delay M and VCXO delay N).

(3) The tsk(o) specification is only valid for equal loading of all outputs.
(4) The phase of LVCMOS is lagging in reference to the phase of LVDS and LVPECL.



www.ti.com

SCAS858C - JUNE 2008 - REVISED JANUARY 2012

PARAMETER MEASUREMENT INFORMATION



Figure 2. LVCMOS Output Test Setup







Figure 3. LVDS DC Test Setup



Figure 5. LVPECL DC Test Setup

www.ti.com

TYPICAL CHARACTERISTICS











www.ti.com

APPLICATION INFORMATION

PHASE NOISE ANALYSIS

Phase noise is measured in a closed loop mode of 491.52MHz VCXO and 30.72MHz reference and a 100Hz loop. Output 1 is measured for divide by one, output 6 for divide by 4, and output 9 for divide by 16.

Table 1. Phase Noise for LVPECL Hi	igh Swing
------------------------------------	-----------

Phase Noise Specifications under following configuration: VCXO = 491.52MHz, REF = 30.72MHz, Divide by = 491.52MHz, Divide by 4 = 122.88MHz, Divide by 16 = 30.72MHz, PFD Frequency = 240KHz, Charge Pump Current = 2mA, Loop BW = 100Hz, Output 1 = 491.52 MHZ, Output Buffer: LVPECL-HS

PHASE NOISE AT OFFSET	VCXO OPEN LOOP	REFERENCE 30.72MHz	LVPECL-HS DIVIDE BY 1	LVPECL-HS DIVIDE BY 4	LVPECL-HS DIVIDE BY 16	UNIT
10Hz	-64	-107	-80	-92	-105	dBc/Hz
100Hz	-99	-123	-92	-104	-116	dBc/Hz
1kHz	–113	-134	–115	-127	-139	dBc/Hz
10kHz	-135	-153	-135	-145	-158	dBc/Hz
100kHz	-148	-156	-146	-155	-162	dBc/Hz
1MHz	-148	-158	-146	-155	-162	dBc/Hz
10MHz	-149		-147	-156		dBc/Hz

Table 2. Phase Noise for LVDS High Swing

Phase Noise Specifications under following configuration: VCXO = 491.52MHz, REF = 30.72MHz, Divide by = 491.52MHz, Divide by 4 = 122.88MHz, Dlvide by 16 = 30.72MHz, PFD Frequency = 240KHz, Charge Pump Current = 2mA Loop BW = 100Hz, Output 1 = 491.52 MHZ, Output Buffer: LVDS-HS

PARAMETER	VCXO OPEN LOOP	REFERENCE	LVDS-HS DIVIDE BY 1	LVDS-HS DIVIDE BY 4	LVDS-HS DIVIDE BY 16	UNIT						
10Hz	-64	-107	-82	-94	-104	dBc/Hz						
100Hz	-99	-123	-92	-105	-117	dBc/Hz						
1kHz	-113	-134	-114	-127	-139	dBc/Hz						
10kHz	-135	-153	-135	-145	-151	dBc/Hz						
100kHz	-148	-156	-145	-152	-153	dBc/Hz						
1MHz	-148	-158	-146	-152	-153	dBc/Hz						
10MHz	-149		-146	-152		dBc/Hz						

Table 3. Phase Noise for LVCMOS

Phase Noise Specifications under following configuration: VCXO = 491.52MHz, REF = 30.72MHz, Divide by = 491.52MHz, Divide by 4 = 122.88MHz, Divide by 16 = 30.72MHz, PFD Frequency = 240KHz, Charge Pump Current = 2mA, Loop BW = 100Hz, Output 1 = 491.52 MHZ, Output Buffer: LVCMOS

PARAMETER	VCXO OPEN LOOP	REFERENCE	N/A	LVCMOS DIVIDE BY 4	LVCMOS DIVIDE BY 16	UNIT
10Hz	-64	-107		-91	-105	dBc/Hz
100Hz	-99	-123		-104	-116	dBc/Hz
1kHz	-113	-134		-127	-139	dBc/Hz
10kHz	-135	-153		-140	-151	dBc/Hz
100kHz	-148	-156		-151	-159	dBc/Hz
1MHz	-148	-158		-153	-160	dBc/Hz
10MHz	-149			-154		dBc/Hz



www.ti.com

INTERFACE AND CONTROL BLOCK

The Interface & Control Block includes a SPI interface, four control pins, a non-volatile memory array in which the device stores default configuration data, and an array of device registers implemented in Static RAM. This RAM, also called the device registers, configures all hardware within the CDCE72010.

Serial Peripheral Interface (SPI)

The serial interface of CDCE72010 is a simple bidirectional SPI interface for writing and reading to and from the device registers. It implements a low speed serial communications link in a master/slave topology in which the CDCE72010 is a slave. The SPI consists of four signals:

- SPI_CLK: Serial Clock (Output from Master) the CDCE72010 and the master host clock data in and out on the rising edge of SPI_CLK. Data transitions therefore occur on the falling edge of the clock. (LVCMOS Input Buffer)
- SPI_MOSI: Master Output Slave Input (LVCMOS Input Buffer) .
- **SPI_MISO:** Master Input Slave Output
- **SPI_LE:** Latch Enable (Output from Master). The falling edge of SPI_LE initiates a transfer. If SPI_LE is high, no data transfer can take place. (LVCMOS Input Buffer).

The CDCE72010 implements data fields that are 28-bits wide. In addition, it contains 12 registers, each comprising a 28 bit data field. Therefore, accessing the CDCE72010 requires that the host program append a 4-bit address field to the front of the data field as follows:



Figure 11. CDCE72010 SPI Communications Format

CDCE72010 SPI Command Structure

The CDCE72010 supports four commands issued by the Master via the SPI:

- Write to RAM
- Read Command
- Copy RAM to EEPROM unlock
- Copy RAM to EEPROM lock

Table 4 provides a summary of the CDCE72010 SPI command structure. The host (master) constructs a Write to RAM command by specifying the appropriate register address in the address field and appends this value to the beginning of the data field. Therefore, a valid command stream must include 32 bits, transmitted LSB first. The host must issue a Read Command to initiate a data transfer from the CDCE72010 back to the host. This command specifies the address of the register of interest in the data field.

Table 4. CDCE72010 SPI Command Structure⁽¹⁾ Data Field (28 Bits) Addr Field (4 Bits)* Register NVM 2 6 2 5 7 6 5 3 2 1 0 Operation 2 7 2 4 2 3 2 2 2 1 1 5 1 0 9 8 4 3 2 1 0 1 1 8 1 7 1 6 1 4 1 3 1 2 1 1 9 0 х Х Х Х Х Х Х Х х Х х х Х Х Х 0 0 Write to RAM Yes х Х Х Х Х Х Х Х Х Х Х Х Х 0 0 0 Х Write to RAM Х Х Х х х х х х Х Х Х Х Х х х х Х х Х Х Х х х Х Х 0 0 Х Х 0 1 1 Yes х х Х Х Х х Х х х х х Х Х Х Х х Х Write to RAM Х Х Х Х Х Х Х Х Х 0 0 0 2 Yes Х Х 1 Х Х 3 Write to RAM Yes Х 0 0 1 1 х Х х Х х 4 Write to RAM Yes х Х Х х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х 0 0 0 х х х х х Х х Х Х Х Х Х х Х х х х Х Х Х Х Х Х 1 5 Write to RAM х Х х Х Х 0 1 0 Yes Х Х Х х Х Х х х х Х х х Х Х х Х Х Write to RAM х Х Х Х Х Х Х Х Х Х Х 0 1 6 Yes 1 0 Х Х Х Х Х Х Write to RAM Yes Х 0 1 7 Write to RAM Х 8 Yes Х 0 0 0 1 Write to RAM Х 9 Yes Х Х Х Х 1 0 0 1 Х Х х Write to RAM Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х Х 0 10 Yes Х Х Х Х Х Х 1 0 1 Х 11 Write to RAM Yes Х 0 1 Х 1 1 Х х х 12 Status/Control No Х 0 0 1 No 0 А 0 Instruction Read Command 0 А А А 1 1 1 RAM → EEPROM 0 Instruction Unlock 0 0 0 1 1 1 1 1 Lock (2) 0 0 0 0 0 0 0 0 0 0 0 $\mathsf{RAM} \to \mathsf{EEPROM}$ 0 0 0 0 0 1 0 0 0 0 0 0 1 Instruction 1 0 0 1 1 1 1 1

(1) CAUTION: In a read Cycle the Address Field should be ignored when accessing the CDCE72010 device.

(2) After execution of this command, the EEPROM is permanently locked. After locking EEPROM, device configuration can only be changed via Write into RAM after power up; however EEPROM can no longer be changed.

SPI Interface Master

The Interface master can be designed using a FPGA or a micro controller. The CDCE72010 acts as a slave to the SPI master. The SPI Master should be designed to issue none consecutive read or write commands. The SPI clock should start and stop with respect to the SPI_LE signal as shown in Figure 12. SPI_MOSI, SPI_CLK, and SPI_LE are generated by the SPI Master. SPI_MISO is gnererated by the SPI slave the CDCE72010.



Figure 12. CDCE72010 SPI Read/Write Command

SPI Consecutive Read/Write Cycles to the CDCE72010

Figure 13 illustrates how two consecutive SPI cycles are performed between a SPI Master and the CDCE72010 SPI Slave.



www.ti.com

SCAS858C – JUNE 2008 – REVISED JANUARY 2012





Writing to the CDCE72010

Figure 14 illustrates a Write to RAM operation. Notice that the latching of the first data bit in the data stream (Bit 0) occurs on the first rising edge of SPI_CLK after SPI_LE transitions from a high to a low. For the CDCE72010, data transitions occur on the falling edge of SPI_CLK. A rising edge on SPI_LE signals to the CDCE72010 that the transmission of the last bit in the stream (Bit 31) has occurred.



Figure 14. CDCE72010 SPI Write Operation

Reading from the CDCE72010

Figure 15 shows how the CDCE72010 executes a Read Command. The SPI master first issues a Read Command to initiate a data transfer from the CDCE72010 back to the host (see Table 4). This command specifies the address of the register of interest (marked as AAAA in Table 1). By transitioning SPI_LE from a low to a high, the CDCE72010 resolves the address specified in the appropriate bits of the data field. The host drives SPI_LE low and the CDCE72010 presents the data present in the register specified in the Read Command on SPI_MISO.

IMPORTANT NOTE: The read instruction does not return SPI_MISO Bit 0 properly. This bit is stuck with zero. The host should ignore this bit when accessing the CDCE72010.



Figure 15. CDCE72010 SPI Read Operation

Writing to EEPROM

After the CDCE72010 detects a power-up and completes a reset cycle, the device copies the contents of the on-board EEPROM into the Device Registers. (SPI_LE signal has to be HIGH in order for the EEPROM to load correctly during the rising edge of Power_Down signal).

The host issues one of two special commands shown in Table 4 to copy the contents of Device Registers 0 through 11 (a total of 336 bits) into EERPOM. They include:

- Copy RAM to EEPROM Unlock, Execution of this command can happen many times.
- Copy RAM to EEPROM Lock: Execution of this command can happen only once; after which the EEPROM is permanently locked.

After either command is initiated, power must remain stable and the host must not access the CDCE72010 for at least 50 ms to allow the EEPROM to complete the write cycle and to avoid the possibility of EEPROM corruption.

TEXAS INSTRUMENTS

SCAS858C-JUNE 2008-REVISED JANUARY 2012

www.ti.com

SPI CONTROL INTERFACE TIMING



Figure 16. Timing Diagram for SPI Write Command



Figure 17. Timing Diagram for SPI Read Command

	PARAMETER	MIN	TYP	MAX	UNIT
f _{Clock}	Clock Frequency for the SPI_CLK			20	MHz
t ₁	SPI_LE to SPI_CLK setup time	10			ns
t ₂	SPI_MOSI to SPI_CLK setup time	10			ns
t ₃	SPI_MOSI to SPI_CLK hold time	10			ns
t ₄	SPI_CLK high duration	25			ns
t ₅	SPI_CLK low duration	25			ns
t ₆	SPI_CLK to SPI_LE Hold time	10			ns
t ₇	SPI_LE Pulse Width	20			ns
t ₈	SPI_CLK to MISO data valid			10	ns
t ₉	SPI_LE to SPI_MISO Data Valid			10	ns

Table 5. SPI Bus Timing Characteristics



www.ti.com

CDCE72010 Default Configuration

The CDCE72010 on-chip EEPROM has been factory preset to the default settings listed in Table 6

		0 0	
REGISTER	DEFAULT SETTING	REGISTER	DEFAULT SETTING
REG0000	002C0040	REG0007	EB040717
REG0001	83840051	REG0008	010C0158
REG0002	83400002	REG0009	01000049
REG0003	83400003	REG0010	0BFC07CA
REG0004	81800004	REG0011	8000058B
REG0005	81800005	REG0012	Undetermined
REG0006	EB040006		

Table 6. CDCE72010 Default Configuration Settings

The default configuration programmed in the EEPROM is: a 10MHz primary reference single ended LVCMOS, a 491.52MHz LVPECL VCXO running at 80kHz PFD with a 10Hz loop bandwidth. Reference Auto Select is off, M divider is set for 125, N divider is set to 768, charge pump current is set to 2.2mA, and feedback divider is set to divide by 8. Divider 1 is set to divide by 4, Dividers 2 and 3 are set to divide by 1, Dividers 4 and 5 are set to divide by 2, Dividers 6 and 7 are set to divide by 8, and Divider 8 is set to divide by 16.Output0:LVCMOS, Output1:Hi-LVPECL, Output2: Hi-LVPECL, Output3:Hi_LVPECL, Output4:LVPECL, Output5:LVPECL, Output6:Hi-LVDS, Output7:Hi-LVDS, Output8:LVCMOS and Output9:LVCMOS.

ÈXAS

NSTRUMENTS

www.ti.com

Register 0 Address 0x00: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION								
0	INBUFSELX	Reference Input	Primary and secondary Buffer Type Select (LVPECL,LVDS or LVCMOS)							EEDDOM	
1	INBUFSELY	Buffers	XY(10) LVPECL, (11) LVDS, (00) LVCMC)S- Inpu	it is Pos	itive pin				EEFROIVI	
2	PRISEL	Reference Input Buffer	When REFSELCNTRL is set to 1, the foll If Bits (2,3): 00 – No input buffer is select If Bits (2,3): 10 – PRI_REF is selected, SI If Bits (2,3): 01 – SEC_REF is selected, F If Bits (2,3): 11 – Auto Select (PRI then S	owing so ed/active EC_REF PRI_REF EC).	ettings a e - is pow - is pow	apply: vered dov vered dov	wn wn ⁽¹⁾			EEPROM	
4	VCXOSEL	Divider START DETERM-Block	When set to 0, PRI- or SEC-clock is select When set to 1, VCXO/AUX-clock is select	When set to 0, PRI- or SEC-clock is selected, depending on bits 2 and 3 (default) When set to 1, VCXO/AUX-clock is selected, overwrites bits 2 and 3							
5	REFSELCNTRL	Reference Selection Control	Reference Select Control to select if the c in Register 0 bits 2 and 3 or from the exter - When set to 0: the external pin REF_SE SEC. Autoselect is not available. - When set to 1: The external pin REF_SI 3>) describes which reference input clocl Autoselect). In autoselect mode, refer to t	eference Select Control to select if the control of the reference is from the internal bit Register 0 bits 2 and 3 or from the external select pin. When set to 0: the external pin REF_SEL takes over the selection between PRI and EC. Autoselect is not available. When set to 1: The external pin REF_SEL is ignored. The table in (Register 0 <2 and >) describes which reference input clock is selected and available (none, PRI, SEC or utoselect). In autoselect mode, refer to the timing diagram.							
6	DELAY_PFD0	252	PFD pulse width PFD bit 0								
7	DELAY_PFD1	PFD	PFD pulse width PFD bit 1	D pulse width PFD bit 1							
8	Reserved		Must be set 0	/lust be set 0							
9	CP_DIR	Charge Pump	Determines which direction CP current wi Feedback Clock, Positive CP output curre	Determines which direction CP current will regulate (Reference Clock leads to Feedback Clock, Positive CP output current [0], Negative CP output current [1])							
10	CP_SRC		Switches the current source in the charge	e pump o	on wher	n set to 1	(TI Tes	st-GTME)	EEPROM	
11	CP_SNK	Charge Pump	Switches the current sink in the charge pu	ump on	when s	et to 1 (1	T Test-C	GTME)		EEPROM	
12	CP_OPA	Diagnostics	Switches the charge pump op-amp off wh	nen set t	to 1 (TI	Test-GT	ME)			EEPROM	
13	CP_PRE		Preset charge pump output voltage to V _{C0}	_{C_CP} /2, c	on [1], o	ff [0]				EEPROM	
14	ICP0		CP current setting bit 0							EEPROM	
15	ICP1	Charge Pump	CP current setting bit 1								
16	ICP2		CP current setting bit 2								
17	ICP3		CP current setting bit 3								
18	RESERVED		Must be set to 0							EEPROM	
19	RESERVED		Must be set to 0							EEPROM	
20	IREFRES	Charge Pump Diagnostics	Enables the 12-k Ω pull-down resistor at I_	_REF_C	CP pin w	hen set	to 1 (TI	Test-G	TME)	EEPROM	
21	PECLOHISWING	Output 0	High output voltage swing in LVPECL/LVI	DS mod	e if set	to 1				EEPROM	
22	CMOSMODE0PX	0.1.10	LVCMOS mode select for OUTPUT 0 pos	sitive pin							
23	CMOSMODE0PY	Output 0	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	tate					EEPROM	
24	CMOSMODE0NX	0.1.10	LVCMOS mode select for OUTPUT 0 nec	ative pi	n.						
25	CMOSMODE0NY	Output 0	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	tate					EEPROM	
					l	REGIST	ER BIT	5			
26	OUTBUFSEL0X	Output 0		22	23	24	25	26	27	EEPROM	
			LVPECL	0	0	0	0	0	1		
			LVDS	0	1	0	1	1	1		
27	OUTBUFSEL0Y Output 0	LVCMOS	See Settings Above ⁽²⁾ 0 0				EEPROM				
21				All Outputs Disabled	0	1	0	1	1	0	

This setting is only available if the Register 11 Bit 3 is set to 0 (Feedback Divider clock is set to CMOS type). Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs. (1)

(2)





www.ti.com

Register 1 Address 0x01: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION								
0	ACDCSEL	Input Buffers	If set to 0 AC Termination, If set to 1 DC	terminat	ion					EEPROM	
1	HYSTEN	Input Buffers	If set to 1 Input Buffers Hysteresis enable	ed						EEPROM	
2	TERMSEL	Input Buffers	If set to 0 Input Buffer Internal Termination	n enable	ed					EEPROM	
3	PRIINVBB	Input Buffers	If set to 1 Primary Input Negative pin bias	sed with	internal	VBB vo	ltage			EEPROM	
4	SECINVBB	Input Buffers	If set to 1 Secondary Input Negative pin I	If set to 1 Secondary Input Negative pin biased with internal VBB voltage							
5	FAILSAFE	Input Buffers	If set to 1 Fail Safe is enabled for all input	If set to 1 Fail Safe is enabled for all input buffers							
6	PH1ADJC0										
7	PH1ADJC1										
8	PH1ADJC2			parse phase adjust select for Output Divider 1							
9	PH1ADJC3	Output 0 and 1	Coarse phase adjust select for Output Di								
10	PH1ADJC4										
11	PH1ADJC5										
12	PH1ADJC6										
13	OUT1DIVRSEL0										
14	OUT1DIVRSEL1										
15	OUT1DIVRSEL2									EEPROM	
16	OUT1DIVRSEL3	Output 0 and 1	Output Divider 1 ratio select								
17	OUT1DIVRSEL4										
18	OUT1DIVRSEL5										
19	OUT1DIVRSEL6										
20	EN01DIV	Output 0 and 1	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM	
21	PECL1HISWING	Output 1	High Output Voltage Swing in LVPECL/L	VDS Mo	de if set	to 1				EEPROM	
22	CMOSMODE1PX	Output 4	LVCMOS mode select for OUTPUT 1 Po	sitive Pir	n.					FEDDOM	
23	CMOSMODE1PY	Output	(X,Y) = 00: Active, 10: Inverting, 11: Low	, 01: 3-S	itate					EEPROM	
24	CMOSMODE1NX	Output 4	LVCMOS mode select for OUTPUT 1 Ne	gative P	'in.					FEDDOM	
25	CMOSMODE1NY	Output	(X,Y) = 00: Active, 10: Inverting, 11: Low	, 01: 3-S	itate					EEPROM	
						REGIST	ER BIT	5			
26	OUTBUFSEL1X	Output 1	OUTFOLTTPE	22	23	24	25	26	27	EEPROM	
			LVPECL	0	0	0	0	0	1		
			LVDS 0 1 0 1 1 1								
27	OUTBUFSEL1Y	Output 1	LVCMOS	See Settings Above ⁽¹⁾ 0			0	EEPROM			
			All Outputs Disabled	0	1	0	1	1	0		

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs.

SCAS858C-JUNE 2008-REVISED JANUARY 2012

www.ti.com

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPT	DESCRIPTION/FUNCTION							
0	DLYM0		Reference phase delay M bit0								
1	DLYM1	DELAY M	Reference phase delay M bit1							EEPROM	
2	DLYM2		Reference phase delay M bit2							•	
3	DLYN0		Feedback phase delay N bit0								
4	DLYN1	DELAY N	Feedback phase delay N bit1	Feedback phase delay N bit1							
5	DLYN2		Feedback phase delay N bit2						†		
6	PH2ADJC0										
7	PH2ADJC1										
8	PH2ADJC2										
9	PH2ADJC3	Output 2	Coarse phase adjust select for output div	Coarse phase adjust select for output divider 2							
10	PH2ADJC4										
11	PH2ADJC5										
12	PH2ADJC6										
13	OUT2DIVRSEL0										
14	OUT2DIVRSEL1										
15	OUT2DIVRSEL2										
16	OUT2DIVRSEL3	Output 2	Output Divider 2 ratio select						EEPROM		
17	OUT2DIVRSEL4										
18	OUT2DIVRSEL5										
19	OUT2DIVRSEL6										
20	EN2DIV	Output 2	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM	
21	PECL2HISWING	Output 2	High Output Voltage Swing in LVPECL/L	VDS Mo	de if set	to 1				EEPROM	
22	CMOSMODE2PX	Output 0	LVCMOS mode select for OUTPUT 2 Po	sitive Pir	n.					FEDDOM	
23	CMOSMODE2PY	Output 2	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	state					EEPROM	
24	CMOSMODE2NX	Output 0	LVCMOS mode select for OUTPUT 2 Ne	gative P	'in.					FEDDOM	
25	CMOSMODE2NY	Output 2	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	state					EEPROM	
					I	REGIST	ER BIT	S			
26	OUTBUFSEL2X Output 2	Output 2	GOIFOITIFE	22	23	24	25	26	27	EEPROM	
			LVPECL	0	0	0	0	0	1		
			LVDS	0	1	0	1	1	1		
27	OUTBUFSEL2Y	Output 2	LVCMOS See Settings Above ⁽¹⁾ 0 0						EEPROM		
				All Outputs Disabled	0	1	0	1	1	0	

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs.





www.ti.com

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

Register 3 Address 0x03: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION							POWER UP CONDITIO N	
0	DIS_FDET_REF	PLL Freq. Detect	When set to 0, the REF-clock frequency of When set to 1, it is switched OFF	detector	is ON					EEPROM	
1	DIS_FDET_FB	Diagnostics	When set to 1, the feedback path frequer (TI Test-GTME)	When set to 1, the feedback path frequency detector is switched OFF (TI Test-GTME)							
2	BIAS_DIV01<0>		When BIAS_DIV01<1:0> =								
3	BIAS_DIV01<1>	Output Divider 0 and 1	01, Current reduction for all output-divider by about 20% 10, Current reduction for all output-divider by about 20%						EEPROM		
4	BIAS_DIV23<0>		When BIAS_DIV23<1:0> =								
5	BIAS_DIV23<1>	Output Divider 2 and 3	00, No current reduction for all output-div 01, Current reduction for all output-divide 10, Current reduction for all output-divide	out 20% out 30%					EEPROM		
6	PH3ADJC0										
7	PH3ADJC1										
8	PH3ADJC2										
9	PH3ADJC3	Output 3	Coarse phase adjust select for Output Divider 3							EEPROM	
10	PH3ADJC4										
11	PH3ADJC5										
12	PH3ADJC6										
13	OUT3DIVRSEL0										
14	OUT3DIVRSEL1										
15	OUT3DIVRSEL2									EEPROM	
16	OUT3DIVRSEL3	Output 3	Output Divider 3 ratio select								
17	OUT3DIVRSEL4										
18	OUT3DIVRSEL5										
19	OUT3DIVRSEL6										
20	EN3DIV	Output 3	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM	
21	PECL3HISWING	Output 3	High Output Voltage Swing in LVPECL/LV	VDS Mo	de if se	t to 1				EEPROM	
22	CMOSMODE3PX	Output 2	LVCMOS mode select for OUTPUT 3 Pos	sitive Pi	n.					FEDDOM	
23	CMOSMODE3PY	Output 3	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3 - S	State					EEPROM	
24	CMOSMODE3NX	Output 2	LVCMOS mode select for OUTPUT 3 Ne	gative F	in.					FEDDOM	
25	CMOSMODE3NY	Output 3	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-8	State					EEPROM	
						REGIST	ER BIT	5			
26	OUTBUFSEL3X	Output 3	001P01 TYPE 22	22	23	24	25	26	27	EEPROM	
			LVPECL	0	0	0	0	0	1		
			LVDS	0	1	0	1	1	1		
27	OUTBUFSEL3Y	Output 3	LVCMOS	See S	ettings A	Above ⁽¹⁾		0	0	EEPROM	
			All Outputs Disabled	0	1	0	1	1	0		

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION							
0	RESERVED		Must be set '0'							EEPROM
1	RESERVED		Must be set '0'							EEPROM
2	RESERVED		Must be set '0'							EEPROM
3	RESERVED		Must be set '0'	ust be set '0'						
4	HOLDONLOR	HOLD_OVER	If set to 0, CP remains active and will dise	set to 0, CP remains active and will discharge loop filter if input reference clock is lost						
5	RESERVED									EEPROM
6	PH4ADJC0									
7	PH4ADJC1									
8	PH4ADJC2									
9	PH4ADJC3	Output 4	Coarse phase adjust select for Output Div	oarse phase adjust select for Output Divider 4						EEPROM
10	PH4ADJC4									
11	PH4ADJC5									
12	PH4ADJC6									
13	OUT4DIVRSEL0									
14	OUT4DIVRSEL1									
15	OUT4DIVRSEL2								EEPROM	
16	OUT4DIVRSEL3	Output 4	Output Divider 4 ratio select							
17	OUT4DIVRSEL4									
18	OUT4DIVRSEL5									
19	OUT4DIVRSEL6									
20	EN4DIV	Output 4	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM
21	PECL4HISWING	Output 4	High Output Voltage Swing in LVPECL/LV	VDS Mo	de if set	to 1				EEPROM
22	CMOSMODE4PX	Output 4	LVCMOS mode select for OUTPUT 4 Pos	sitive Pi	n.					
23	CMOSMODE4PY	Output 4	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	State					EEPROIVI
24	CMOSMODE4NX	Output 4	LVCMOS mode select for OUTPUT 4 Ne	gative P	'in.					
25	CMOSMODE4NY	Output 4	(X,Y) = 00: Active, 10: Inverting, 11: Low, 01: 3-State						EEPROIVI	
			REGISTER BITS							
26	OUTBUFSEL4X	Output 4		22	23	24	25	26	27	EEPROM
			LVPECL	0	0	0	0	0	1	
			LVDS	0	1	0	1	1	1	
27	OUTBUFSEL4Y	Output 4	LVCMOS	See Settings Above ⁽¹⁾ 0 0					EEPROM	
			All Outputs Disabled	0	1	0	1	1	0	

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs



www.ti.com



www.ti.com

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

Register 5 Address 0x05: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPT	'ION/FU	NCTION	I				POWER UP CONDITIO N
0	BIAS_DIV45<0> BIAS_DIV45<1>	Output Divider 4 and 5	When BIAS_DIV45<1:0> = 00, No current reduction for all output-divider 01, Current reduction for all output-divider 10, Current reduction for all output-divider	<pre>/hen BIAS_DIV45<1:0> = 0, No current reduction for all output-divider 1, Current reduction for all output-divider by about 20% 0, Current reduction for all output-divider by about 30%</pre>						
2	BIAS_DIV67<0>		When BIAS_DIV67<1:0> =	nen BIAS_DIV67<1:0> =						
3	BIAS_DIV67<1>	Output Divider 6 and 7	00, No current reduction for all output-divident 01, Current reduction for all output-divident 10, Current reduction for all output-divident 01, Current for all output-dividen), No current reduction for all output-divider), Current reduction for all output-divider by about 20%), Current reduction for all output-divider by about 30%						EEPROM
4	RESERVED									EEPROM
5	RESERVED									EEPROM
6	PH5ADJC0									
7	PH5ADJC1									
8	PH5ADJC2	-								
9	PH5ADJC3	Output 5	Coarse phase adjust select for Output Div	Coarse phase adjust select for Output Divider 5						EEPROM
10	PH5ADJC4	-								
11	PH5ADJC5	-								
12	PH5ADJC6	-								
13	OUT5DIVRSEL0									
14	OUT5DIVRSEL1	-	Output Divider 5 ratio select							
15	OUT5DIVRSEL2	-							EEPROM	
16	OUT5DIVRSEL3	Output 5								
17	OUT5DIVRSEL4	-								
18	OUT5DIVRSEL5	-								
19	OUT5DIVRSEL6	-								
20	EN5DIV	Output 5	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM
21	PECL5HISWING	Output 5	High Output Voltage Swing in LVPECL/LV	/DS Mo	de if set	to 1				EEPROM
22	CMOSMODE5PX		LVCMOS mode select for OUTPUT 5 Pos	sitive Pir	۱.					
23	CMOSMODE5PY	Output 5	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	tate					EEPROM
24	CMOSMODE5NX		LVCMOS mode select for OUTPUT 5 New	aative P	in.					
25	CMOSMODE5NY	Output 5	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	tate					EEPROM
			REGISTER BITS							
26	OUTBUFSEL5X	Output 5	OUTPUT TYPE	22	23	24	25	26	27	EEPROM
			LVPECL	0	0	0	0	0	1	
			LVDS	0	1	0	1	1	1	-
27	OUTBUFSEL5Y	Output 5	LVCMOS	See S	ettings A	bove ⁽¹⁾	1	0	0	EEPROM
]	All Outputs Disabled	0	1	0	1	1	0	

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs

www.ti.com

STRUMENTS

EXAS

Register 6 Address 0x06: SPI Mode											
REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION	/FUNC	TION					POWER UP CONDITION	
0	FB_FD_DESEL	LOCK-DET	0 Feedback Frequency Detector is connect 1 Feedback Frequency Detector is disconn	Peedback Frequency Detector is connected to the Lock Detector Feedback Frequency Detector is disconnected from the Lock Detector							
1	RESERVED		Set to 0	et to 0							
2	FBDETERM_DIV_SE L		0 FB-Deterministic Clock divided by 1 1 FB- Deterministic Clock divided by 2	FB-Deterministic Clock divided by 1 FB- Deterministic Clock divided by 2							
3	FBDETERM_DIV2_DI S	FB-Divider/ Deterministic Blocks	0 FB-Deterministic-DIV2-Block in normal of 1 FB-Deterministic-DIV2 reset (here REG6) FB-Deterministic-DIV2-Block in normal operation I FB-Deterministic-DIV2 reset (here REG6_RB<2> == 0)							
4	FB_START_BYPASS	Diooko) FB-Divider started with delay block (RC), normal operation 1 FB-Divider can be started with external REF_SEL-signal (pin)								
5	DET_START_BYPAS S	All Output Dividers	0 Output-Dividers started with delay block (1 Output-Dividers can be started with exter	(RC), n nal NR	ormal	operatio -signal (n pin)			EEPROM	
6	PH6ADJC0	Output 6									
7	PH6ADJC1										
8	PH6ADJC2										
9	PH6ADJC3		Coarse phase adjust select for Output Divider 6						EEPROM		
10	PH6ADJC4										
11	PH6ADJC5										
12	PH6ADJC6										
13	OUT6DIVRSEL0										
14	OUT6DIVRSEL1										
15	OUT6DIVRSEL2										
16	OUT6DIVRSEL3	Output 6	Output Divider 6 ratio select							EEPROM	
17	OUT6DIVRSEL4										
18	OUT6DIVRSEL5										
19	OUT6DIVRSEL6										
20	EN6DIV	Output 6	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM	
21	PECL6HISWING	Output 6	High Output Voltage Swing in LVPECL/LVE	DS Mo	de if se	et to 1				EEPROM	
22	CMOSMODE6PX	Output 0	LVCMOS mode select for OUTPUT 6 Posit	tive Pir	۱.					FERROM	
23	CMOSMODE6PY	Output 6	(X,Y) = 00: Active, 10: Inverting, 11: Low, 0	1: 3-S	tate					EEPROM	
24	CMOSMODE6NX	Output 0	LVCMOS mode select for OUTPUT 6 Nega	ative Pi	in.					FERROM	
25	CMOSMODE6NY	Output 6	(X,Y) = 00: Active, 10: Inverting, 11: Low, 0	1: 3-S	tate					EEPROM	
			REGISTER BITS								
26	OUTBUFSEL6X	Output 6	OUTPUT TYPE	22	23	24	25	26	27	EEPROM	
			LVPECL	0	0	0	0	0	1		
		LVDS 0 1 0 1 1					1	1			
27	OUTBUFSEL6Y	JFSEL6Y Output 6 LVCMOS See Settings Above ⁽¹⁾ 0 0					0	EEPROM			
			All Outputs Disabled	0 1 0 1 1					0	<u> </u>	

(1) Use description for bits 22, 23, 24 and 25 for setting the LVCMOS outputs



SCAS858C - JUNE 2008 - REVISED JANUARY 2012

www.ti.com

Register 7 Address 0x07: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPT	DESCRIPTION/FUNCTION								
0	LOCKW 0		Lock-detect window Bit 0 (Refer to Reg 9	Bits 6 a	nd 7)					EEPROM		
1	LOCKW 1		Lock-detect window Bit 1 (Refer to Reg 9	ck-detect window Bit 1 (Refer to Reg 9 Bits 6 and 7) t to 0								
2	RESERVED		Set to 0									
3	LOCKC0	LOCK-DET	Number of coherent lock events Bit 0	nber of coherent lock events Bit 0								
4	LOCKC1		Number of coherent lock events Bit 1	mber of coherent lock events Bit 1								
5	ADLOCK		Selects Digital PLL_LOCK 0, Selects Ana	ects Digital PLL_LOCK 0, Selects Analog PLL_LOCK 1								
6	PH7ADJC0											
7	PH7ADJC1											
8	PH7ADJC2											
9	PH7ADJC3	Output 7	Coarse phase adjust select for Output Div	/ider 7						EEPROM		
10	PH7ADJC4											
11	PH7ADJC5											
12	PH7ADJC6											
13	OUT7DIVRSEL0											
14	OUT7DIVRSEL1											
15	OUT7DIVRSEL2								1			
16	OUT7DIVRSEL3	Output 7	Output Divider 7 ratio select	Output Divider 7 ratio select								
17	OUT7DIVRSEL4											
18	OUT7DIVRSEL5											
19	OUT7DIVRSEL6											
20	EN7DIV	Output 7	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM		
21	PECL7HISWING	Output 7	High Output Voltage Swing in LVPECL/LV	/DS Mo	de if set	to 1				EEPROM		
22	CMOSMODE7PX	Outrast 7	LVCMOS mode select for OUTPUT 7 Pos	sitive Pir	า					FEDDOM		
23	CMOSMODE7PY	Output 7	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	tate					EEPROM		
24	CMOSMODE7NX	0 1 17	LVCMOS mode select for OUTPUT 7 Ne	gative P	in.					FEDDOM		
25	CMOSMODE7NY	Output 7	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-S	tate					EEPROM		
							ER BIT	6				
26	OUTBUFSEL7X	Output 7	OUTPOT TIPE	22	23	24	25	26	27	EEPROM		
			LVPECL	0	0	0	0	0	1			
			LVDS	0 1 0 1 1			1	1				
27	OUTBUFSEL7Y	Output 7	LVCMOS	See Se	ettings A	bove ⁽¹⁾		0	0	EEPROM		
			All Outputs Disabled	0	1	0	1	1	0			

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPT	DESCRIPTION/FUNCTION							
0	VCXOBUFSELX	_	VCXO and AUX Input Buffer Type Select (LVPECL,LVDS or LVCMOS)								
1	VCXOBUFSELY		XY(10) LVPECL, (11) LVDS, (00) LVCMOS- Input is Positive Pin O and AUX ut Buffers							-	
2	VCXOACDCSEL	Input Buffers								EEPROM	
3	VCXOHYSTEN		If Set to 1 Input Buffers Hysteresis enable	et to 1 Input Buffers Hysteresis enabled							
4	VCXOTERMSEL		If Set to 0 Input Buffer Internal Termination	set to 0 Input Buffer Internal Termination enabled							
5	VCXOINVBB	VCXO Input Buffer	If Set to 1 It Biases VCXO Input negative	Set to 1 It Biases VCXO Input negative pin with internal VCXOVBB Voltage						EEPROM	
6	PH8ADJC0										
7	PH8ADJC1										
8	PH8ADJC2										
9	PH8ADJC3	Output 8 and 9	Coarse phase adjust select for Output Div	Coarse phase adjust select for Output Divider 8						EEPROM	
10	PH8ADJC4										
11	PH8ADJC5										
12	PH8ADJC6										
13	OUT8DIVRSEL0										
14	OUT8DIVRSEL1		utput 8 and 9 Output Divider 8 ratio select (seeTable 8)								
15	OUT8DIVRSEL2										
16	OUT8DIVRSEL3	Output 8 and 9								EEPROM	
17	OUT8DIVRSEL4										
18	OUT8DIVRSEL5										
19	OUT8DIVRSEL6										
20	EN89DIV	Output 8 and 9	When set to 0, the divider is disabled When set to 1, the divider is enabled							EEPROM	
21	PECL8HISWING	Output 8	High Output Voltage Swing in LVPECL/LV	/DS Mod	de if set	to 1				EEPROM	
22	CMOSMODE8PX	Output 9	LVCMOS mode select for OUTPUT 8 Pos	sitive Pin							
23	CMOSMODE8PY	Output 8	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-St	ate					EEPROM	
24	CMOSMODE8NX	Output 9	LVCMOS mode select for OUTPUT 8 Neg	gative Pi	n.					EEDROM	
25	CMOSMODE8NY	Output 8	(X,Y) = 00: Active, 10: Inverting, 11: Low,	01: 3-St	ate					EEFROM	
			REGISTER BITS								
26	OUTBUFSEL8X	Output 8		22	23	24	25	26	27	EEPROM	
			LVPECL	0	0	0	0	0	1		
			LVDS	0	1	0	1	1	1		
27	OUTBUFSEL8Y	Output 8	LVCMOS	See Settings Above ⁽¹⁾ 0 0					EEPROM		
			All Outputs Disabled	0	1	0	1	1	0		

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs



www.ti.com



www.ti.com

SCAS858C - JUNE 2008 - REVISED JANUARY 2012

Register 9 Address 0x09: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION	/FUNCT	ION					POWER UP CONDITION	
0	HOLDF		Enables the Frequency Hold-Over (External Hold Over Function based on the external circuitry) on 1, off 0								
1	RESERVED										
2	HOLD		3-State Charge Pump 0 - (equal to HOLD pin function)								
3	HOLDTR	HOLD-Over	IOLD-Over HOLD function always activated 1 (recommended for test purposes, only) Triggered by analog PLL Lock detect outputs If analog PLL Lock Signal is [1] (PLL locked), HOLD is activated If analog PLL Lock Signal is [0] (PLL not lock), HOLD is deactivated							EEPROM	
4	HOLD_CNT0		HOLD Function is reactivated after X Ref Clock Cycles. Defined by								
5	HOLD_CNT1		(HOLD_CNT0,HOLD_CNT1) : X = Number of For (00) : X = 64, (01) : X = 128, (10) : X = 25	[:] Clock C 56, (11) :	Cycles. X = 51	2 Cloc	k Cycle	es			
6	LOCKW 2		Extended Lock-detect window Bit 2 (also refe	r to Reg	7 Bits () and 1)				
7	LOCKW 3	LOCK-DET	Extended Lock-detect window Bit 3 (also refe	r to Reg	7 Bits () and 1)			EEPROM	
8	NOINV_RESHOL_ INT	Chip CORE	When set to 0, SPI/HOLD_INT and SPI/RESE When set to 1, SPI/HOLD_INT and SPI/RESE	ET_INT i ET_INT r	nverted not inve	(defau	ılt)			EEPROM	
9	DIVSYNC_DIS	Diagnostic: PLL N/M Divider	When GTME = 0, this Bit has no functionality, When set to 0, START-Signal is synchronized When set to 1, START-Sync N/M Divider in P	, But who to N/M LL are b	en GTN Divider ypasse	IE = 1, Input (d	then: Clocks			EEPROM	
10	START_BYPASS	Divider START DETERM-Block	When set to 0, START-Signal is synchronized When set to 1, START-Sync Block is bypasse	to VCX	O-Cloc	k				EEPROM	
11	INDET_BP	Divider START DETERM-Block	When set to 0, Sync Logic active when VCXC When set to 1, Sync Logic is independent from	Vhen set to 0, Sync Logic active when VCXO/AUX-Clocks are available Vhen set to 1, Sync Logic is independent from VCXO- and/or AUX-Clocks						EEPROM	
12	PLL_LOCK_BP	Divider START DETERM-Block	When set to 0, Sync Logic waits for 1st PLL_LOCK state When set to 1, Sync Logic independent from 1st PLL_LOCK						EEPROM		
13	LOW_FD_FB_EN	Divider START DETERM-Block	When set to 0, Sync Logic is independent from VCXO/DIV_FB freq. (PLL-FD) When set to 1, Sync Logic is started for VCXO/DIV_FB > ~600KHz, stopped for VCXO/DIV_FB < ~600KHz					EEPROM			
14	NPRESET_MDIV	PLL M/FB-Divider	When set to 0, M-Divider uses NHOLD as NP When set to 1, M-Divider NOT preseted by N	RESET HOLD						EEPROM	
15	BIAS_DIV_FB<0>		When BIAS_DIV_FB<1:0> =								
16	BIAS_DIV_FB<1>	Feedback Divider	 00, No current reduction for FB-Divider 01, Current reduction for FB-Divider by about 10, Current reduction for FB-Divider by about 	20% 30%						EEPROM	
17	BIAS_DIV89<0>		When BIAS_DIV89<1:0> =								
18	BIAS_DIV89<1>	Output Divider 8 and 9	00, No current reduction for all output-rivider 01, Current reduction for all output-divider by 10, Current reduction for all output-divider by	about 20 about 30)%)%					EEPROM	
19	AUXINVBB		If set to 1 it biases AUX Input Negative pin wi	th intern	al VCX	OVBB	voltage).			
20	DIS_AUX_Y9	AUX Input Buffer	If set to 1 AUX in Input Mode Buffer Is disable FB_MUX_SEL and OUT_MUX_SEL bits setti	ed. If set ngs.	to 0 it f	ollows	the be	havior c	f	EEPROM	
21	PECL9HISWING	Output 9	High output voltage swing in LVPECL/LVDS I	Mode if s	set to 1					EEPROM	
22	CMOSMODE9PX		LVCMOS mode select for OUTPUT 9 Positive	e pin.							
23	CMOSMODE9PY	Output 9	(X,Y) = 00: Active, 10: Inverting, 11: Low, 01:	3-State						EEPROM	
24	CMOSMODE9NX	0	LVCMOS mode select for OUTPUT 9 Negative pin							FERROM	
25	CMOSMODE9NY	Output 9	(X,Y) = 00: Active, 10: Inverting, 11: Low, 01: 3-State						EEPROM		
			REGISTER BITS								
26	OUTBUFSEL9X	Output 9	utput 9 22 23 24 25 26 LVPECL 0				26	27	EEPROM		
							0	0	1		
			LVDS	0	1	0	1	1	1		
27	OUTBUFSEL9Y	Output 9	LVCMOS	See Se	ettings A	bove ⁽¹)	0	0	EEPROM	
			All Outputs Disabled	0	1	0	1	1	0		

(1) Use description for bits 22, 23, 24, and 25 for setting the LVCMOS outputs

REGISTER BIT

0

1

2

3 4

5

6

7

8 9

10

25

26 27

34

N11

N12

N13

SCAS858C-JUNE 2008-REVISED JANUARY 2012

BIT NAME

M0

M1

M2

M3

M4

M5

M6

M7

M8

M9

M10

RELATED BLOCK

Reference

(PRI/SEC) Divider M

11	M11		Reference Divider M Bit 11
12	M12		Reference Divider M Bit 12
13	M13		Reference Divider M Bit 13
14	N0		VCXO Divider N Bit 0
15	N1		VCXO Divider N Bit 1
16	N2		VCXO Divider N Bit 2
17	N3		VCXO Divider N Bit 3
18	N4		VCXO Divider N Bit 4
19	N5		VCXO Divider N Bit 5
20	N6	VCXO/AUX/SEC	VCXO Divider N Bit 6
21	N7	Divider N	VCXO Divider N Bit 7
22	N8		VCXO Divider N Bit 8
23	N9		VCXO Divider N Bit 9
24	N10		VCXO Divider N Bit 10

VCXO Divider N Bit 11

VCXO Divider N Bit 12

VCXO Divider N Bit 13

Product Folder Link(s): CDCE72010

Register 10 Address 0x0A: SPI Mode

Reference Divider M Bit 0

Reference Divider M Bit 1

Reference Divider M Bit 2

Reference Divider M Bit 3

Reference Divider M Bit 4

Reference Divider M Bit 5

Reference Divider M Bit 6

Reference Divider M Bit 7

Reference Divider M Bit 8

Reference Divider M Bit 9

Reference Divider M Bit 10

DESCRIPTION/FUNCTION

Texas Instrum	ENTS
	Texas Instrum

www.ti.com

POWER UP CONDITION

EEPROM

EEPROM



www.ti.com

Register 11 Address 0x0B: SPI Mode

REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION	
0	PRI_DIV2	Input Buffers	If set to 1 enables Primary Reference Divide by 2	EEPROM	
1	SEC_DIV2	Input Buffers	If set to 1 enables Secondary Reference Divide by 2	EEPROM	
2	FB_DIS	FB Path Integer Counter 32	When set to 0, FB divider is active When set to 1, FB divider is disabled	EEPROM	
3	FB_CML_SEL	FB Path Integer Counter 32	When set to 0, FB clock is CMOS type ⁽¹⁾ When set to 1, FB clock is CML type and uses CML2CMOS converter in PLL	EEPROM	
4	FB_INCLK_INV	FB-Divider/ Deterministic Blocks	When set to 0, Input clock for FB not inverted (normal mode, low speed) When set to 1, Input clock for FB inverted (higher speed mode)	EEPROM	
5	FB_COUNT32_0		Feedback Counter Bit0		
6	FB_COUNT32_1		Feedback Counter Bit1		
7	FB_COUNT32_2		Feedback Counter Bit2		
8	FB_COUNT32_3	FB Path Integer	Feedback Counter Bit3	EEPROM	
9	FB_COUNT32_4	Counter 52	Feedback Counter Bit4		
10	FB_COUNT32_5		Feedback Counter Bit5		
11	FB_COUNT32_6		Feedback Counter Bit6		
12	FB_PHASE0		Feedback Phase Adjust Bit0		
13	FB_PHASE1		Feedback Phase Adjust Bit1	EEPROM	
14	FB_PHASE2		Feedback Phase Adjust Bit2		
15	FB_PHASE3	FB Path Integer	Feedback Phase Adjust Bit3		
16	FB_PHASE4	Counter 52	Feedback Phase Adjust Bit4		
17	FB_PHASE5		Feedback Phase Adjust Bit5		
18	FB_PHASE6		Feedback Phase Adjust Bit6	-	
19	PD_PLL	PLL	If set to 0, PLL is in normal mode If set to 1, PLL is powered down	EEPROM	
20	FB_MUX_SEL See Table 7	Clock Tree and Deterministic Block	When set to 0, the VCXO Clock is selected for the Clock Tree and FB-Div and Det When set to 1, the AUX Clock is selected for the Clock Tree and FB-Div and Det	EEPROM	
21	OUT_MUX_SEL See Table 7	Clock Tree	If Set to 0 it selects the VCXO Clock and if Set to 1 it selects the AUX Clock	EEPROM	
22	FB_SEL	Diagnostics	Feed Back Path Selects FB/VCXO-Path when set to 0 (TI Test-GTME) The Secondary Reference clock input is selected when set to 1 (TI Test-GTME)	EEPROM	
23	NRESHAPE1	5.4	Reshapes the Reference Clock Signal 0, Disable Reshape 1	EEPROM	
24	SEL_DEL1	Selection Control	If set to 0 it enables short delay for fast operation If Set to 1 Long Delay recommended for Input References below 150Mhz	EEPROM	
25	RESET_HOLD_MO DE	Reset Circuitry	If set to 1 the RESET or HOLD pin acts as HOLD, set to 0 it acts as RESET	EEPROM	
26	EPLOCK	Status	Read only. If EPLOCK reads a 0, the EEPROM is unlocked. If EPLOCK reads a 1, then the EEPROM is locked.	EEPROM	
27	Reserved	read only	Read only; always reads '1'	EEPROM	

(1) When Feedback Divider clock is set to CMOS type, only feedback divider values greater than 5 are available.

Table 7. Output Buffers Source Feed, PLL Source Feed, and AUX IN/OUTPUT 9 Selection

FB_MUX_SEL	OUT_MUX_SEL	PLL FEED AND OUTPUTS FEED	AUX INPUT OR OUTPUT 9
0	0	VCXO::PLL, VCXO::Y0Y9 and Deterministic Block	OUTPUT 9 is enabled
1	0	AUXIN::PLL, VCXO::Y0Y8 and Deterministic Block	AUX IN is enabled
0	1	VCXO::PLL, AUXIN::Y0Y8 and Deterministic Block	AUX IN is enabled
1	1	AUXIN::PLL, AUXIN::Y0Y8 and Deterministic Block	AUX IN is enabled

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

.....

_

www.ti.com

NSTRUMENTS

ÈXAS

Register 12 Address 0x0C: SPI Mode (RAM only Register)					
REGISTER BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POR DEFAULT	
0	RESERVED		Must be set '0'		RAM
1	RESERVED		Must be set '0'		RAM
2	RESERVED		Must be set '0'		RAM
3	RESERVED		Must be set '0'		RAM
4	INDET_AUX	Status (Read Only)	It indicates that a clock is present at AUX-input (Y9) , when set to 1		RAM
5	INDET_VCXO	Status (Read Only)	It indicates that a clock is present at VCXO-input , when set to 1		RAM
6	PLL_LOCK	Status (Read Only)	It indicates that the PLL is locked when set to 1		RAM
7	SLEEP	Power Down	Power-down mode on when set to 0, Off when set to 1	1	RAM
8	RESET_HOLD	Reset	If set to 0 this bit forces "RESET or HOLD" depending on the setting of RESET_HOLD_MODE bit in Register 11. If set to 0 RESET or HOLD are asserted. Set for 1 for normal operation.	1	RAM
9	GTME	Diagnostics	General Test Mode Enable, Test Mode is only enabled, if this bit is set to 1 This bit controls many test modes on the device.	0	RAM
10	REVISION0	Status	Read only: Revision Control Bit 0		RAM
11	REVISION1	Status	Read only: Revision Control Bit 1		RAM
12	REVISION2	Status	Read only: Revision Control Bit 2		RAM
13	PD_10	Diagnostics	When set to 0, all blocks are on. (TI Test-GTME) When set to 1, the VCXO Input, AUX Input and all output buffers and divider blocks are disabled. This test is done to measure the effect of the I/O circuitry on the Charge Pump. (TI Test-GTME)	0	RAM
14	SXOIREF	Diagnostics	If set to 0 that Status pin is used as CMOS output to enable TI test modes. Set to 1 when IREFRES is set to 1 and 12-K Ω resistor is connected. (TI Test-GTME)	0	RAM
15	SHOLD	Diagnostics	Routes the HOLD signal to the PLL_LOCK pin when set to 1 (TI Test-GTME)	0	RAM
16	RESERVED		Must be set '0'	0	RAM
17	STATUS0	Diagnostics	TI test registers. For TI use only Route internal signals to external STATUS pin. STATUS3, STATUS2, STATUS1, STATUS0 (S3, S2, S1, S0) will select that internal status signal that will be routed to the external STATUS pin.	1	RAM
18	STATUS1				
19	STATUS2				
20	STATUS3				
21	TITSTCFG0	Diagnostics	TI test registers. For TI use only	0	RAM
22	TITSTCFG1	Diagnostics	TI test registers. For TI use only	0	RAM
23	TITSTCFG2	Diagnostics	TI test registers. For TI use only	0	RAM
24	TITSTCFG3	Diagnostics	TI test registers. For TI use only	0	RAM
25	PRIACTIVITY	Status	It indicates activity on the Primary when set to - (read only bit)		RAM
26	SECACTIVITY	Status	It indicates activity on the Secondary when set to - (read only bit)		RAM
27	RESERVED				RAM

. . .

- -

•

NOTE

If TI test bits (Register 12< bits 17,18,19, 20> are set to 1000, Reference Select from the Smart Mux will show on the STATUS pin (High = Primary REF is selected and Low = Secondary REF is selected).

When TI test bits are set to 0000 the Reference Clock Frequency Detector shows up on the STATUS pin. In this mode the STATUS pin goes high if a clock is detected and low if a clock is not detected. In this configuration Register 3 Bit 0 should be set to 0.


www.ti.com

OUTPUT DIVIDERS SETTINGS

The CDCE72010 has a complex multi stage output divider. The table below describes the setting of Bits 13:19 of Register 1 to 8 and the setting for the feedback divider bits 5:11 of register 11. The table below describes divider settings and the phase relation of the outputs with respect to divide by one clock. To calculate the phase relation between 2 different dividers see Output Divider and Phase Adjust Section in this document.

	FOR REGISTER 1 TO 8 BITS {19[BIT6] TO 13[BIT0]} FOR REGISTER 11 BITS {11[BIT6] TO 5[BIT0]}							
[Bit 6]	[Bit 5]	[Bit 4]	[Bit 3]	[Bit 2]	[Bit 1]	[Bit 0]		
0	1	0	0	0	0	0	1	
1	0	0	0	0	0	0	2	
1	0	0	0	0	0	1	3	
1	0	0	0	0	1	0	4	
1	0	0	0	0	1	1	5	
0	0	0	0	0	0	0	4'	
0	0	0	0	0	0	1	6	
0	0	0	0	0	1	0	8	
0	0	0	0	0	1	1	10	
0	0	0	0	1	0	0	8'	
0	0	0	0	1	0	1	12	
0	0	0	0	1	1	0	16	
0	0	0	0	1	1	1	20	
0	0	0	1	0	0	0	12'	
0	0	0	1	0	0	1	18	
0	0	0	1	0	1	0	24	
0	0	0	1	0	1	1	30	
0	0	0	1	1	0	0	16'	
0	0	0	1	1	0	1	24'	
0	0	0	1	1	1	0	32	
0	0	0	1	1	1	1	40	
0	0	1	0	0	0	0	20'	
0	0	1	0	0	0	1	30'	
0	0	1	0	0	1	0	40'	
0	0	1	0	0	1	1	50	
0	0	1	0	1	0	0	24'	
0	0	1	0	1	0	1	36	
0	0	1	0	1	1	0	48	
0	0	1	0	1	1	1	60	
0	0	1	1	0	0	0	28	
0	0	1	1	0	0	1	42	
0	0	1	1	0	1	0	56	
0	0	1	1	0	1	1	70	
0	0	1	1	1	0	0	32'	
0	0	1	1	1	0	1	48'	
0	0	1	1	1	1	0	64	
0	0	1	1	1	1	1	80	

Table 8. Output Dividers and Feedback Divide Settings and Phase Output

SCAS858C-JUNE 2008-REVISED JANUARY 2012

CONFIGURATION DEFAULT MODE (CD MODE)

The CDCE72010 has two modes of operation, SPI Interface and Configuration Default Mode. The Configuration Default mode is selected when MODE_SEL Pin is driven low and it is used where SPI interface is not available. In the CD Mode configuration, the SPI interface Pins become static control pins CD1, CD2, CD3 and AUX_SEL as shown in the Pin description. The CD Mode signals are sampled only at power up or after Power Down are asserted.

In CD Mode, CD1 and CD2 are used to switch between EEPROM saved configurations.

- CD1 allows swapping Divider and Phase Adjust value between output couples
- · CD2 allows changing the output type for each output.
- AUX_SEL Controls the Output Mux between VCXO and AUX Input.
- CD3 must be grounded in CD Mode.

Without any interface a single device with a single program can have multiple configurations that can be implemented on more than one socket.



Figure 18. Writing to EEPROM via SPI Bus



Figure 19. Using CD1, CD2 to Control What is Copied From EEPROM Into Registers at Power Up

INSTRUMENTS

Texas



www.ti.com

SCAS858C - JUNE 2008 - REVISED JANUARY 2012

Register 0 Address 0x00: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	INBUFSELX	Reference Input	Primary and Secondary Buffer Type Select (LVPECL.LVDS or LVCMOS)	FEDDOM
1	INBUFSELY	Buffers	XY(10) LVPECL, (11) LVDS, (00) LVCMOS- Input is Positive Pin	EEPROM
2 3	PRISEL	Reference Input Buffer	When REFSELCNTRL is set to 1 the following settings apply: If Bit (2,3): 00 – no Input Buffer is selected/active If Bit (2,3): 10 – PRI_REF is selected, SEC_BUF is powered down If Bit (2,3): 11 – Auto Select (PRI then SEC).	EEPROM
4	VCXOSEL	Divider START DETERM-Block	When set to 0, PRI- or SEC-Clocks are selected, depending on Bits 2 and 3 (default) When set to 1, VCXO/AUX-clock selected, overwrites Bits 2 and 3	EEPROM
5	REFSELCNTRL	Reference Selection Control	Reference Select Control to select if the control of the reference is from the internal bit in Register 0 bits 2 and 3 or from the external select pin. – When set to 0: The external pin REF_SEL takes over the selection between PRI and SEC. Autoselect is not available. – When set to 1 R0.2 and R0.3 bits must be set '1': The external pin REF_SEL is ignored. The Table in (Register 0 <2 and 3>) describes, which reference input clock is selected and available at (none, PRI, SEC or Autoselect). In autoselect mode, refer to the timing diagram	EEPROM
6	DELAY_PFD0	PFD	PFD Pulse Width PFD Bit 0	EEPROM
7	DELAY_PFD1	PFD	PFD Pulse Width PFD Bit 1	EEPROM
8	RESERVED		Must be set '0'	EEPROM
9	CP_DIR	Charge Pump	Determines in which direction CP current will regulate (Reference Clock leads to Feedback Clock; Positive CP output current [0]; Negative CP output current [1]	EEPROM
10	CP_SRC		Switches the current source in the Charge Pump on when set to 1 (TI Test-GTME)	EEPROM
11	CP_SNK	Diagnostics	Switches the current sink in the Charge Pump on when set to 1 (TI Test-GTME)	EEPROM
12	CP_OPA		Switches the Charge Pump op-amp off when set to 1 (TI Test-GTME)	EEPROM
13	CP_PRE		Preset Charge Pump output voltage to V _{CC_CP} /2, on [1], off [0]	EEPROM
14	ICP0		CP Current Setting Bit 0	EEPROM
15	ICP1	Charge Pump	CP Current Setting Bit 1	EEPROM
16	ICP2		CP Current Setting Bit 2	EEPROM
17	ICP3		CP Current Setting Bit 3	EEPROM
18	RESERVED		Must be set '0'	EEPROM
19	RESERVED		Must be set '0'	EEPROM
20	IREFRES	Diagnostics	Enables the 12k pull-down resistor at I_REF_CP Pin when set to 1 (TI Test-GTME)	EEPROM
21	PECLOHISWING	Output 0	High output voltage swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	RESERVED			EEPROM
23	RESERVED			EEPROM
24	OUTBUF0CD2LX		Output Buffer 0 Signaling Selection when CD2 In low	EEPROM
25	OUTBUF0CD2LY	CD2 Low	(X,Y) = 01: LVPEČL, 11: LVDS, 00: LVCMOS, 10: Output Disable	
26	OUTBUF0CD2HX		Output Buffer 0 Signaling Selection when CD2 in high	
27	OUTBUF0CD2HY	CD2 High	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: output disable	EEPKOM

(1) This setting is only avaiable if the Register 11 Bit 3 is set to 0 (Feedback Divider clock is set to CMOS type).

SCAS858C-JUNE 2008-REVISED JANUARY 2012

www.ti.com	

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	ACDCSEL	Input Buffers	If Set to 0 AC Termination, If set to 1 DC termination	EEPROM
1	HYSTEN	Input Buffers	If Set to 1 Input Buffers Hysteresis enabled	EEPROM
2	TERMSEL	Input Buffers	If Set to 0 Input Buffer Internal Termination enabled	EEPROM
3	PRIINVBB	Input Buffers	If Set to 1 Primary Input Negative Pin biased with internal VBB voltage.	EEPROM
4	SECINVBB	Input Buffers	If Set to 1 Secondary Input Negative Pin biased with internal VBB voltage	EEPROM
5	FAILSAFE	Input Buffers	If Set to 1 Fail Safe is enabled for all input buffers.	EEPROM
6	PH1ADJC0			
7	PH1ADJC1			
8	PH1ADJC2			
9	PH1ADJC3	Output 0 and 1	Coarse phase adjust select for output divider 1	EEPROM
10	PH1ADJC4			
11	PH1ADJC5			
12	PH1ADJC6			
13	OUT1DIVRSEL0		OUTPUT DIVIDER 1 Ratio Select (See Table 8)	EEPROM
14	OUT1DIVRSEL1			
15	OUT1DIVRSEL2			
16	OUT1DIVRSEL3	Output 0 and 1		
17	OUT1DIVRSEL4			
18	OUT1DIVRSEL5			
19	OUT1DIVRSEL6			
20	EN01DIV	Output 0 and 1	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL1HISWING	Output 1	High output voltage swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA1CD1H	CD1 High	CD1 PIN is high and DIVPHA1CD1H is set to low Loads Output Divider 1 and Phase Adjust 1 into OUTPUT 1 CD1 PIN is high and DIVPHA1CD1H is set to high Loads Output Divider 2 and Phase Adjust 2 into OUTPUT 1	EEPROM
23	DIVPHA1CD1L	CD1 Low	CD1 PIN is low and DIVPHA1CD1L is set to low Loads Output Divider 1 and Phase Adjust 1 into OUTPUT 1 CD1 PIN is low and DIVPHA1CD1L is set to high Loads Output Divider 2 and Phase Adjust 2 into OUTPUT 1	EEPROM
24	OUTBUF1CD2LX	CD2 Low	Output Buffer 1 Signaling Selection when CD2 in low	EEPROM
25	OUTBUF1CD2LY	CD2 LOW	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	
26	OUTBUF1CD2HX		Output Buffer 1 Signaling Selection when CD2 in high	EEPROM
27	OUTBUF1CD2HY		(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	





SCAS858C - JUNE 2008 - REVISED JANUARY 2012

www.ti.com

Register 1 Address 0x01: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	DLYM0		Reference Phase Delay M Bit0	
1	DLYM1	DELAY M	Reference Phase Delay M Bit1	EEPROM
2	DLYM2		Reference Phase Delay M Bit2	-
3	DLYN0		Feedback Phase Delay N Bit0	
4	DLYN1	DELAY N	Feedback Phase Delay N Bit1	EEPROM
5	DLYN2		Feedback Phase Delay N Bit2	-
6	PH2ADJC0			
7	PH2ADJC1			
8	PH2ADJC2			
9	PH2ADJC3	Output 2	Coarse phase adjust select for output divider 2	EEPROM
10	PH2ADJC4			
11	PH2ADJC5			
12	PH2ADJC6			
13	OUT2DIVRSEL0		OUTPUT DIVIDER 2 Ratio Select (See Table 8)	EEPROM
14	OUT2DIVRSEL1			
15	OUT2DIVRSEL2			
16	OUT2DIVRSEL3	Output 2		
17	OUT2DIVRSEL4			
18	OUT2DIVRSEL5			
19	OUT2DIVRSEL6			
20	EN2DIV	Output 2	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL2HISWING	Output 2	High output voltage swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA2CD1H	CD1 High	CD1 PIN is high and DIVPHA2CD1H is set to low Loads Output Divider 2 and Phase Adjust 2 into OUTPUT 2 CD1 PIN is high and DIVPHA2CD1H is set to high Loads Output Divider 1 and Phase Adjust 1 into OUTPUT 2	EEPROM
23	DIVPHA2CD1L	CD1 Low	CD1 PIN is low and DIVPHA2CD1L is set to low Loads Output Divider 2 and Phase Adjust 2 into OUTPUT 2 CD1 PIN is low and DIVPHA2CD1L is set to high Loads Output Divider 1 and Phase Adjust 1 into OUTPUT 2	EEPROM
24	OUTBUF2CD2LX		Output Buffer 2 Signaling Selection when CD2 in low	EEPROM
25	OUTBUF2CD2LY	CD2 LOW	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	
26	OUTBUF2CD2HX	OD0 Lites	Output Buffer 2 Signaling Selection when CD2 in high	
27	OUTBUF2CD2HY	CD2 High	(X,Y) = 01: LVPEČL, 11: LVDS, 00: LVCMOS, 10: Ŏutput Disable	EEPROM

42

Submit Documentation Feedback

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

IVI

Product Folder Link(s): CDCE7201	0

Copyright © 2008–2012, Texas Instruments Incorporated

Register 3 Address 0x03: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	DIS_FDET_REF	PLL Freq. Detect	When set to 0, the REF-clock frequency detector is ON When set to 1, it is switched OFF	EEPROM
1	DIS_FDET_FB	Diagnostics	When set to 1, the feedback path frequency detector is switched OFF (TI Test-GTME)	EEPROM
2	BIAS_DIV01<0>		When BIAS_DIV01<1:0> =	EEPROM
3	BIAS_DIV01<1>	Output Divider 0 and 1	00, No current reduction for all output-divider01, Current reduction for all output-divider by about 20%10, Current reduction for all output-divider by about 30%	EEPROM
4	BIAS_DIV23<0>		When BIAS_DIV23<1:0> =	EEPROM
5	BIAS_DIV23<1>	Output Divider 2 and 3	00, No current reduction for all output-divider01, Current reduction for all output-divider by about 20%10, Current reduction for all output-divider by about 30%	EEPROM
6	PH3ADJC0			
7	PH3ADJC1			EEPROM
8	PH3ADJC2			
9	PH3ADJC3	Output 3	Coarse phase adjust select for output divider 3	
10	PH3ADJC4			
11	PH3ADJC5			
12	PH3ADJC6			
13	OUT3DIVRSEL0		OUTPUT DIVIDER 3 Ratio Select (See Table 8)	
14	OUT3DIVRSEL1			
15	OUT3DIVRSEL2			EEPROM
16	OUT3DIVRSEL3	Output 3		
17	OUT3DIVRSEL4			
18	OUT3DIVRSEL5			
19	OUT3DIVRSEL6			
20	EN3DIV	Output 3	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL3HISWING	Output 3	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA3CD1H	CD1 High	CD1 PIN is high and DIVPHA3CD1H is set to low Loads Output Divider 3 and Phase Adjust 3 into OUTPUT 3 CD1 PIN is high and DIVPHA3CD1H is set to high Loads Output Divider 4 and Phase Adjust 4 into OUTPUT 3	EEPROM
23	DIVPHA3CD1L	CD1 Low	CD1 PIN is Low and DIVPHA3CD1L is set to low Loads Output Divider 3 and Phase Adjust 3 into OUTPUT 3 CD1 PIN is Low and DIVPHA3CD1L is set to high Loads Output Divider 4 and Phase Adjust 4 into OUTPUT 3	EEPROM
24	OUTBUF3CD2LX	CD2 Low	Output Buffer 3 Signaling Selection when CD2 in low	FERROM
25	OUTBUF3CD2LY	CD2 LOW	(X,Y) = 01:LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPKOW
26	OUTBUF3CD2HX		Output Buffer 3 Signaling Selection when CD2 in high	FEDDON
27	OUTBUF3CD2HY		(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPRON



www.ti.com



www.ti.com

SCAS858C -JUNE 2008-REVISED JANUARY 2012

Register 4 Address 0x04: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	RESERVED		Must be set '0'	EEPROM
1	RESERVED		Must be set '0'	EEPROM
2	RESERVED		Must be set '0'	EEPROM
3	RESERVED		Must be set '0'	EEPROM
4	HOLDONLOR	HOLD_OVER	If set to 0, CP remains active and will discharge loop filter if input reference clock is lost. If set to 1 it will 3-state the charge pump to act as a HOLD on Loss of Reference Clocks (Primary and Secondary)	EEPROM
5	RESERVED			EEPROM
6	PH4ADJC0			
7	PH4ADJC1			
8	PH4ADJC2			
9	PH4ADJC3	Output 4	Coarse phase adjust select for output divider 4	EEPROM
10	PH4ADJC4			
11	PH4ADJC5			
12	PH4ADJC6			
13	OUT4DIVRSEL0		OUTPUT DIVIDER 4 Ratio Select (See Table 8)	EEPROM
14	OUT4DIVRSEL1			
15	OUT4DIVRSEL2			
16	OUT4DIVRSEL3	Output 4		
17	OUT4DIVRSEL4			
18	OUT4DIVRSEL5			
19	OUT4DIVRSEL6			
20	EN4DIV	Output 4	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL4HISWING	Output 4	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA4CD1H	CD1 High	CD1 PIN is high and DIVPHA4CD1H is set to low Loads Output Divider 4 and Phase Adjust 4 into OUTPUT 4 CD1 PIN is high and DIVPHA4CD1H is set to high Loads Output Divider 3 and Phase Adjust 3 into OUTPUT 4	EEPROM
23	DIVPHA4CD1L	CD1 Low	CD1 PIN is low and DIVPHA4CD1L is set to low Loads Output Divider 4 and Phase Adjust 4 into OUTPUT 4 CD1 PIN is low and DIVPHA4CD1L is set to high Loads Output Divider 3 and Phase Adjust 3 into OUTPUT 4	EEPROM
24	OUTBUF4CD2LX		Output Buffer 4 Signaling Selection when CD2 in low (X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPROM
25	OUTBUF4CD2LY			
26	OUTBUF4CD2HX		Output Buffer 4 Signaling Selection when CD2 in high	FEDDOM
27	OUTBUF4CD2HY	CD2 High	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	

SCAS858C-JUNE 2008-REVISED JANUARY 2012

www.ti.com

Register 5 Address 0x05: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	BIAS_DIV45<0>		When BIAS_DIV45<1:0> =	
1	BIAS_DIV45<1>	Output Divider 4 and 5	00, No current reduction for all output-divider01, Current reduction for all output-divider by about 20%10, Current reduction for all output-divider by about 30%	EEPROM
2	BIAS_DIV67<0>		When BIAS_DIV67<1:0> =	
3	BIAS_DIV67<1>	Output Divider 6 and 7	00, No current reduction for all output-divider 01, Current reduction for all output-divider by about 20% 10, Current reduction for all output-divider by about 30%	EEPROM
4	RESERVED			EEPROM
5	RESERVED			EEPROM
6	PH5ADJC0			
7	PH5ADJC1			
8	PH5ADJC2			
9	PH5ADJC3	Output 5	Coarse phase adjust select for output divider 5	EEPROM
10	PH5ADJC4			
11	PH5ADJC5			
12	PH5ADJC6			
13	OUT5DIVRSEL0		OUTPUT DIVIDER 5 Ratio Select (See Table 8)	EEPROM
14	OUT5DIVRSEL1			
15	OUT5DIVRSEL2			
16	OUT5DIVRSEL3	Output 5		
17	OUT5DIVRSEL4			
18	OUT5DIVRSEL5			
19	OUT5DIVRSEL6			
20	EN5DIV	Output 5	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL5HISWING	Output 5	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA5CD1H	CD1 High	CD1 PIN is high and DIVPHA5CD1H is set to low Loads Output Divider 5 and Phase Adjust 5 into OUTPUT 5 CD1 PIN is high and DIVPHA5CD1H is set to high Loads Output Divider 6 and Phase Adjust 6 into OUTPUT 5	EEPROM
23	DIVPHA5CD1L	CD1 Low	CD1 PIN is low and DIVPHA5CD1L is set to low Loads Output Divider 5 and Phase Adjust 5 into OUTPUT 5 CD1 PIN is low and DIVPHA5CD1L is set to high Loads Output Divider 6 and Phase Adjust 6 into OUTPUT 5	EEPROM
24	OUTBUF5CD2LX	CD2 Low	Output Buffer 5 Signaling Selection when CD2 in low	FEDDOM
25	OUTBUF5CD2LY	CD2 LOW	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	
26	OUTBUF5CD2HX		Output Buffer 5 Signaling Selection when CD2 in high	EEPROM
27	OUTBUF5CD2HY	CD2 High	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	





SCAS858C - JUNE 2008 - REVISED JANUARY 2012

www.ti.com

Register6 Address 0x06: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	FB_FD_DESEL	LOCK-DET	0 Feedback Frequency Detector is connected to the Lock Detector 1 Feedback Frequency Detector is disconnected from the Lock Detector	EEPROM
1	RESERVED		Set to "0"	
2	FBDETERM_DIV_SEL		0 FB-Deterministic Clock divided by 1 1 FB- Deterministic Clock divided by 2	
3	FBDETERM_DIV2_DIS	FB-Divider / Deterministic Blocks	0 FB-Deterministic-DIV2-Block in normal operation 1 FB-Deterministic-DIV2 reset (here REG6_RB<2> == "0")	EEPROM
4	FB_START_BYPASS		0 FB-Divider started with delay block (RC), normal operation 1 FB-Divider can be started with external REF_SEL-signal (pin)	
5	DET_START_BYPASS	All Output Dividers	0 Output-Dividers started with delay block (RC), normal operation 1 Output-Dividers can be started with external NRESET-signal (pin)	EEPROM
6	PH6ADJC0			
7	PH6ADJC1			
8	PH6ADJC2			EEPROM
9	PH6ADJC3	Output 6	Coarse phase adjust select for output divider 6	
10	PH6ADJC4			
11	PH6ADJC5			
12	PH6ADJC6			
13	OUT6DIVRSEL0		OUTPUT DIVIDER 6 Ratio Select (See Table 8)	
14	OUT6DIVRSEL1			
15	OUT6DIVRSEL2			EEPROM
16	OUT6DIVRSEL3	Output 6		
17	OUT6DIVRSEL4			
18	OUT6DIVRSEL5			
19	OUT6DIVRSEL6			
20	EN6DIV	Output 6	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL6HISWING	Output 6	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA6CD1H	CD1 High	CD1 PIN is high and DIVPHA6CD1H is set to low Loads Output Divider 6 and Phase Adjust 6 into OUTPUT 6 CD1 PIN is high and DIVPHA6CD1H is set to high Loads Output Divider 5 and Phase Adjust 5 into OUTPUT 6	EEPROM
23	DIVPHA6CD1L	CD1 Low	CD1 PIN is low and DIVPHA6CD1L is set to low Loads Output Divider 6 and Phase Adjust 6 into OUTPUT 6 CD1 PIN is low and DIVPHA6CD1L is set to high Loads Output Divider 5 and Phase Adjust 5 into OUTPUT 6	EEPROM
24	OUTBUF6CD2LX	CD2 Low	Output Buffer 6 Signaling Selection when CD2 in low	EEDROM
25	OUTBUF6CD2LY	CD2 LOW	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPKOM
26	OUTBUF6CD2HX		Output Buffer 6 Signaling Selection when CD2 in high	FEDDOM
27	OUTBUF6CD2HY		(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	LOCKW 0		Lock-detect window bit 0 (Refer to Reg 9 Bits 6 and 7)	
1	LOCKW 1		Lock-detect window bit 1 (Refer to Reg 9 Bits 6 and 7)	
2	RESERVED		Set to 0	550004
3	LOCKC0	LOCK-DET	Number of coherent lock events bit 0	EEPROM
4	LOCKC1		Number of coherent lock events bit 1	
5	ADLOCK		Selects Digital PLL_LOCK 0 ,Selects Analog PLL_LOCK 1	
6	PH7ADJC0			
7	PH7ADJC1			
8	PH7ADJC2			
9	PH7ADJC3	Output 7	Coarse phase adjust select for output divider 7	EEPROM
10	PH7ADJC4			
11	PH7ADJC5			
12	PH7ADJC6			
13	OUT7DIVRSEL0		OUTPUT DIVIDER 7 Ratio Select (See Table 8)	
14	OUT7DIVRSEL1			
15	OUT7DIVRSEL2			
16	OUT7DIVRSEL3	Output 7		EEPROM
17	OUT7DIVRSEL4			
18	OUT7DIVRSEL5			
19	OUT7DIVRSEL6			
20	EN7DIV	Output 7	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL7HISWING	Output 7	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA7CD1H	CD1 High	CD1 PIN is high and DIVPHA7CD1H is set to low Loads Output Divider 7 and Phase Adjust 7 into OUTPUT 7 CD1 PIN is high and DIVPHA7CD1H is set to high Loads Output Divider 8 and Phase Adjust 8 into OUTPUT 7	EEPROM
23	DIVPHA7CD1L	CD1 Low	CD1 PIN is low and DIVPHA7CD1L is set to low Loads Output Divider 7 and Phase Adjust 7 into OUTPUT 7 CD1 PIN is low and DIVPHA7CD1L is set to high Loads Output Divider 8 and Phase Adjust 8 into OUTPUT 7	EEPROM
24	OUTBUF7CD2LX	CD2 Low	Output Buffer 7 Signaling Selection when CD2 in low	EEDDOM
25	OUTBUF7CD2LY	CD2 LOW	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPROM
26	OUTBUF7CD2HX		Output Buffer 7 Signaling Selection when CD2 in high	EEDBOM
27	OUTBUF7CD2HY	CD2 High	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPROM

Table 9. Register 7 Address 0x07: CD Mode



www.ti.com

46



www.ti.com

SCAS858C-JUNE 2008-REVISED JANUARY 2012

Register	8	Address	0x08:	CD	Mode
register	•	Aug. 633	0,00.	00	mouc

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	VCXOBUFSELX		VCXO and AUX Input Buffer Type Select (LVPECL,LVDS or LVCMOS)	
1	VCXOBUFSELY		XY(10) LVPECL, (11) LVDS, (00) LVCMOS- Input is Positive Pin	
2	VCXOACDCSEL	Input Buffers	If Set to 0 AC Termination, If set to 1 DC Termination	EEPROM
3	VCXOHYSTEN	VCXO Input Buffer	If Set to 1 Input Buffers Hysteresis enabled	
4	VCXOTERMSEL		If Set to 0 Input Buffer Internal Termination enabled	
5	VCXOINVBB	VCXO Input Buffer	If Set to 1 It biases VCXO Input negative pin with internal VCXOVBB voltage	EEPROM
6	PH8ADJC0			
7	PH8ADJC1			
8	PH8ADJC2			
9	PH8ADJC3	Output 8 and 9	Coarse phase adjust select for output divider 8 and 9	EEPROM
10	PH8ADJC4			
11	PH8ADJC5			
12	PH8ADJC6			
13	OUT8DIVRSEL0			
14	OUT8DIVRSEL1			EEPROM
15	OUT8DIVRSEL2			
16	OUT8DIVRSEL3	Output 8 and 9	OUTPUT DIVIDER 8 and 9 Ratio Select (See Table 8)	
17	OUT8DIVRSEL4			
18	OUT8DIVRSEL5			
19	OUT8DIVRSEL6			
20	EN89DIV	Output 8 and 9	When set to 0, the divider is disabled When set to 1, the divider is enabled	EEPROM
21	PECL8HISWING	Output 8	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	DIVPHA8CD1H	CD1 High	CD1 PIN is high and DIVPHA8CD1H is set to low Loads Output Divider 8 and Phase Adjust 8 into OUTPUT 8 CD1 PIN is high and DIVPHA8CD1H is set to high Loads Output Divider 7 and Phase Adjust 7 into OUTPUT 8	EEPROM
23	DIVPHA8CD1L	CD1 Low	CD1 PIN is low and DIVPHA8CD1L is set to low Loads Output Divider 8 and Phase Adjust 8 into OUTPUT 8 CD1 PIN is low and DIVPHA8CD1L is set to high Loads Output Divider 7 and Phase Adjust 7 into OUTPUT 8	EEPROM
24	OUTBUF8CD2LX		Output Buffer 8 Signaling Selection when CD2 in low	FEDDOM
25	OUTBUF8CD2LY	CD2 LOW	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	CEPROM
26	OUTBUF8CD2HX		Output Buffer 8 Signaling Selection when CD2 in high	
27	OUTBUF8CD2HY	CD2 High	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPROM

www.ti.com

Register 9 Address 0x09: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	HOLDF1		Enables the Frequency Hold-Over Function 1 on 1, off 0	
1	HOLDF2		Enables the Frequency Hold-Over Function 2 on 1, off 0	_
2	HOLD		3-State Charge Pump 0 - (equal to HOLD-Pin function)	_
3	HOLDTR	HOLD- Over	HOLD function always activated "1" (recommended for test purposes, only) HOLD- Over Triggered by analog PLL Lock detect outputs If analog PLL Lock Signal is [1] (PLL locked), HOLD is activated If analog PLL Lock Signal is [0] (PLL not lock), HOLD is deactivated	
4	HOLD_CNT0		HOLD1 Function is reactivated after X Ref Clock Cycles. Defined by	
5	HOLD_CNT1		(HOLD_CNT0,HOLD_CNT1)::X= Number of Clock Cycles. For (00)::X=64, (01) ::X=128, (10)::X=256, (11)::X=512 Clock Cycles.	
6	LOCKW 2		Extended Lock-detect window Bit 2 (Also refer to Reg 7 Bits 0 and 1)	FEDROM
7	LOCKW 3	LOCK-DET	Extended Lock-detect window Bit 3 (Also refer to Reg 7 Bits 0 and 1)	LEFROM
8	NOINV_RESHOL_INT	Chip CORE	When set to 0, SPI/HOLD_INT and SPI/RESET_INT inverted (default) When set to 1, SPI/HOLD_INT and SPI/RESET_INT not inverted	EEPROM
9	DIVSYNC_DIS	Diagnostic: PLL N/M Divider	When $GTME = 0$, this bit has no functionality, But when $GTME = 1$, then: When set to 0, START-Signal is synchronized to N/M Divider Input Clocks When set to 1, START-Sync N/M Divider in PLL are bypassed	EEPROM
10	START_BYPASS	Divider START DETERM-Block	When set to 0, START-Signal is synchronized to VCXO-Clock When set to 1, START-Sync Block is bypassed	EEPROM
11	INDET_BP	Divider START DETERM-Block	When set to 0, Sync Logic active when VCXO/AUX-Clocks are available When set to 1, Sync Logic is independent from VCXO- and/or AUX-Clocks	EEPROM
12	PLL_LOCK_BP	Divider START DETERM-Block	When set to 0, Sync Logic waits for 1st PLL_LOCK state When set to 1, Sync Logic independent from 1st PLL_LOCK	EEPROM
13	LOW_FD_FB_EN	Divider START DETERM-Block	When set to 0, Sync Logic is independent from VCXO/DIV_FB freq. (PLL-FD) When set to 1, Sync Logic is started for VCXO/DIV_FB > ~600KHz, stopped for VCXO/DIV_FB < ~600KHz	EEPROM
14	NPRESET_MDIV	PLL M/FB-Divider	When set to 0, M-Divider uses NHOLD1 as NPRESET When set to 1, M-Divider NOT preseted by NHOLD1	EEPROM
15	BIAS_DIV_FB<0>		When BIAS_DIV_FB<1:0> =	
16	BIAS_DIV_FB<1>	Feedback Divider	00, No current reduction for FB-Divider 01, Current reduction for FB-Divider by about 20% 10, Current reduction for FB-Divider by about 30%	EEPROM
17	BIAS_DIV89<0>		When BIAS_DIV89<1:0> =	
18	BIAS_DIV89<1>	Output Divider 8 and 9	00, No current reduction for all output-divider 01, Current reduction for all output-divider by about 20% 10, Current reduction for all output-divider by about 30%	EEPROM
19	AUXINVBB		If Set to 1 it Biases AUX Input Negative Pin with internal VCXOVBB voltage.	
20	DIS_AUX_Y9	AUX Buffer	If Set to 1 AUX in input Mode Buffer is disabled. If Set to 0 it follows the behavior of FB_MUX_SEL and OUT_MUX_SEL bits settings.	EEPROM
21	PECL9HISWING	Output 9	High Output Voltage Swing in LVPECL/LVDS Mode if set to 1	EEPROM
22	RESERVED			EEPROM
23	RESERVED			EEPROM
24	OUTBUF9CD2LX		Output Buffer 9 Signaling Selection when CD2 in low	
25	OUTBUF9CD2LY	CD2 Low	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPROM
26	OUTBUF9CD2HX		Output Buffer 9 Signaling Selection when CD2 in high	
27	OUTBUF9CD2HY	CD2 High	(X,Y) = 01: LVPECL, 11: LVDS, 00: LVCMOS, 10: Output Disable	EEPROM





SCAS858C - JUNE 2008 - REVISED JANUARY 2012

www.ti.com

Register 10 Address 0x0A: CD Mode

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION
0	M0		Reference Divider M bit 0	
1	M1		Reference Divider M bit 1	-
2	M2		Reference Divider M bit 2	
3	M3		Reference Divider M bit 3	
4	M4		Reference Divider M bit 4	
5	M5		Reference Divider M bit 5	
6	M6	Reference	Reference Divider M bit 6	FERROM
7	M7	Divider M	Reference Divider M bit 7	EEPROIVI
8	M8		Reference Divider M bit 8	
9	M9		Reference Divider M bit 9	
10	M10		Reference Divider M bit 10	
11	M11		Reference Divider M bit 11	-
12	M12		Reference Divider M bit 12	
13	M13		Reference Divider M bit 13	
14	N0		VCXO Divider N bit 0	
15	N1		VCXO Divider N bit 1	
16	N2		VCXO Divider N bit 2	
17	N3		VCXO Divider N bit 3	
18	N4		VCXO Divider N bit 4	
19	N5		VCXO Divider N Bit 5	
20	N6	VCXO/AUX/SEC	VCXO Divider N Bit 6	FERROM
21	N7	Divider N	VCXO Divider N Bit 7	EEPROIVI
22	N8		VCXO Divider N Bit 8	
23	N9		VCXO Divider N Bit 9	
24	N10		VCXO Divider N Bit 10	
25	N11]	VCXO Divider N Bit 11	
26	N12		VCXO Divider N Bit 12	
27	N13		VCXO Divider N Bit 13	

www.ti.com

STRUMENTS

EXAS

RAM BIT	BIT NAME	RELATED BLOCK	DESCRIPTION/FUNCTION	POWER UP CONDITION				
0	PRI_DIV2	Input Buffers	If set to 1 Enables Primary Reference Divide by 2	EEPROM				
1	SEC_DIV2	Input Buffers	If set to 1 Enables Secondary Reference Divide by 2	EEPROM				
2	FB_DIS	FB Path Integer Counter 32	When set to 0, FB divider is active When set to 1, FB divider is disabled	EEPROM				
3	FB_CML_SEL	FB Path Integer Counter 32	When set to 0, FB clock is CMOS type When set to 1, FB clock is CML type and uses CML2CMOS converter in PLL	EEPROM				
4	FB_INCLK_INV	FB-Divider / Deterministic Blocks	When set to 0, Input clock for FB not inverted (normal mode, low speed) When set to 1, Input clock for FB inverted (higher speed mode)	EEPROM				
5	FB_COUNT32_0		Feedback Counter Bit0					
6	FB_COUNT32_1		Feedback Counter Bit1					
7	FB_COUNT32_2	FB Path Integer	Feedback Counter Bit2					
8	FB_COUNT32_3	Counter 32	Feedback Counter Bit3	EEPROM				
9	FB_COUNT32_4	(P divider)	Feedback Counter Bit4					
10	FB_COUNT32_5		Feedback Counter Bit5	-				
11	FB_COUNT32_6		Feedback Counter Bit6					
12	FB_PHASE0		Feedback Phase Adjust Bit0					
13	FB_PHASE1		Feedback Phase Adjust Bit1					
14	FB_PHASE2	FB Path Integer	Feedback Phase Adjust Bit2					
15	FB_PHASE3	Counter 32	Feedback Phase Adjust Bit3	EEPROM				
16	FB_PHASE4	(P Divider)	Feedback Phase Adjust Bit4					
17	FB_PHASE5		Feedback Phase Adjust Bit5					
18	FB_PHASE6		Feedback Phase Adjust Bit6					
19	PD_PLL	PLL	If set to 0, PLL is in normal mode If set to 1, PLL is powered down	EEPROM				
20	FB_MUX_SEL Table 10	Clock Tree and Deterministic Block	When set to 0, the VCXO Clock is selected for the Clock Tree and FB-Div/Det When set to 1, the AUX Clock is selected for the Clock Tree and FB-Div/Det.	EEPROM				
21	OUT_MUX_SEL Table 10		If Set to 0 it selects the VCXO Clock and if Set to 1 it selects the AUX Clock	EEPROM				
22	FB_SEL	Diagnostics	Feed Back Path Selects FB/VCXO-Path when set to 0 (TI Test-GTME) The Secondary Reference clock input is selected when set to 1 (TI Test-GTME)	EEPROM				
23	NRESHAPE1	Defenses Calestian	Reshapes the Reference Clock Signal 0, Disable Reshape 1					
24	SEL_DEL1	Control	If set to 0 it enables short delay for fast operation If Set to 1 Long Delay recommended for input references below 150Mhz.	EEPROM				
25	RESET_HOLD	Reset Circuitry	If set to 1 the RESET or HOLD pin acts as HOLD, set to 0 it acts as RESET.	EEPROM				
26	EPLOCK	Status	Read only. If EPLOCK reads a 0, the EEPROM is unlocked. If EPLOCK reads a 1, then the EEPROM is locked.	EEPROM				
27	EPSTATUS	Status	EEPROM Status	EEPROM				

Table 10. Output Buffers Source Feed, PLL Source Feed, and AUX IN/OUTPUT 9 Selection

FB_MUX_SEL	OUT_MUX_SEL	PLL FEED AND OUTPUT FEED	AUX INPUT OR OUTPUT 9
0	0	VCXO::PLL, VCXO::Y0Y9 and Deterministic Block	OUTPUT 9 is Enabled ⁽¹⁾
1	0	AUXIN::PLL, VCXO::Y0Y8 and Deterministic Block	AUX IN is Enabled
0	1	VCXO::PLL, AUXIN::Y0Y8 and Deterministic Block	AUX IN is Enabled
1	1	AUXIN::PLL, AUXIN::Y0Y8 and Deterministic Block	AUX IN is Enabled

(1) Default



SCAS858C -JUNE 2008-REVISED JANUARY 2012

www.ti.com

INTERFACE, CONFIGURATION, AND CONTROL

The CDCE72010 is designed to support various applications with SPI bus interface and without. In the case where systems lack the SPI bus or a Boot up configuration is required at start up before the management layer is up the built in EEPROM is used to provide this function.

The Interface bus takes the serialized address and data and writes to the specified Register bits. The content of the RAM bits are connected to logical functions in the device. Changing the content of the Register bits (high or low) instantly changes the logical functions inside the device.

At power up or after power down is de-asserted the contents of the EEPROM bits are copied to their corresponding Register bits. After that the content of Register can be changed via the SPI bus. When writing to EEPROM commands are detected on the SPI bus the control logic begins writing the content of the Register bits into the corresponding EEPROM bits. This process takes about 50ms. During this time the power supply should be above 3.2V.

The on-chip EEPROM can be operated in its unlocked or locked mode. An unlocked EEPROM indicates that the stored bit values can be changed on another EEPROM write sequence (available for up to a 100 EEPROM write sequences). A locked EEPROM indicates that the stored bit values cannot be changed on another EEPROM write sequence.



Figure 20. Interface Control

UNIVERSAL INPUT AND REFERENCE CLOCK BUFFERS

The CDCE72010 is designed to support what is referred to as a Universal Input Buffer structure. This type of buffer is designed to accept Differential or single ended inputs and it is sensitive enough to act as a LVPECL or LVDS in differential mode and LVCMOS in Single ended mode. With the proper external termination various types of inputs signals can be supported.

The CDCE72010 has two internal voltage biasing circuitries. One to set the termination voltage for references (PRI_REF and SEC_REF) and the second biasing circuitry is to set the termination voltage to the VCXO_IN and AUX_IN. This means that we can only have one type of differential signal on PRI_REF and SEC_REF and only one type of differential signal on VCXO_IN and AUX_IN.

	PRE_REF & SEC_REF Input Buffer Settings							M		、 、	_		PRE.	_REF	F Bu	ffer S	Settings	6			
	Settings Configuration							Register / Bits			S	Switch									
0.0	0.1	1.0	1.1	1.2	1.3/4	Hyst	Mode	Coup	Term	Vbb			_ĭ>_I ſ		0.0	0.1	1.2	1.3	P	<u>N</u>	
0	0	Х	1	Х	Х	ON	LVCMOS	DC	N/A			/ INV	Universal Input Control		X	X	1	X	0	0	0
1	0	0	1	0	0	ON	LVPECL	AC	Internal	1.9V	N t	ť P			X X	1	0	0	C	C C	C 0
1	0	1	1	0	0	ON	LVPECL	DC	Internal	1.2V	VBB	Ì			~		U	·	Ŭ	0	Ũ
1	0	Х	1	1	Х	ON	LVPECL		External			ļ	Vtb +			SE	EC_R	REF	Buffe	r Settir	ngs
1	1	0	1	0	0	ON	LVDS	AC	Internal	1.2V	↓ ₹	Į.	1		Re	gister	r / Bit	s	,	witch	
1	1	1	1	0	0	ON	LVDS	DC	Internal	1.2V		۲ (۲	÷		0.0	0.1	1.2	1.4	Р	Ν	INV
1	1	Х	1	1	Х	ON	LVDS		External			\ INV			0	0	Х	Х	0	0	0
X	х	х	0	х	х	OFF					SEC_REF/	1			X	X	1	X	0	0	0
X	X	X	1	X	X	ON					AUX_IN				X X	1	0	1	C	C C	0
															0.0	PEN	с.	CLO	SED		

Figure 21. CDCE72010 REF Voltage Biasing Circuitry

SCAS858C-JUNE 2008-REVISED JANUARY 2012

www.ti.com

	VCXO & AUX Input Buffer Settings									
Settings						Configuration				
8.0	8.1	8.2	8.3	8.4	8.5/9.19	Hyst	Mode	Coup	Term	Vbb
0	0	Х	1	Х	Х	ON	LVCMOS	DC	N/A	
1	0	0	1	0	0	ON	LVPECL	AC	Internal	1.9V
1	0	1	1	0	0	ON	LVPECL	DC	Internal	1.2V
1	0	Х	1	1	Х	ON	LVPECL		External	
1	1	0	1	0	0	ON	LVDS	AC	Internal	1.2V
1	1	1	1	0	0	ON	LVDS	DC	Internal	1.2V
1	1	Х	1	1	Х	ON	LVDS		External	
Х	Х	Х	0	Х	Х	OFF				
Х	Х	Х	1	Х	Х	ON				

AUX_IN Input Buffer Settings

R	egiste	er/Bi		Switch					
8.0	8.1	8.4	9.19	Р	N	INV			
0	0	Х	Х	0	0	0			
Х	Х	1	Х	0	0	0			
Х	1	0	0	С	С	С			
х	1	0	1	С	С	0			
VCXO Input Buffer Settings									
R	egiste	or/Bi	Inpu ts	t Bui	Switch	tings			
R 8.0	egiste 8.1	er / Bi 8.4	Inpu ts 8.5	t Bui	fer Set Switch N	tings INV			
R 8.0	egiste 8.1	er / Bi 8.4 X	Inpu ts 8.5 X	т Ви Р О	Switch N O	INV 0			
R 8.0 0 X	egiste 8.1 0 X	8.4 X	Inpu ts 8.5 X X	т Ви Р О	Switch N 0	INV 0			
R 8.0 0 X X	egiste 8.1 0 X 1	8.4 X 1 0	Inpu ts 8.5 X X 0	P 0 0 0	Switch N O C	INV 0 0 C			

O - OPEN C - CLOSED

NOTE: Using INV switch, negative input can be biased properly (either 1.2V or 1.9V) and single ended clock signal (whose common mode is already set to either 1.2V for LVDS clock or 1.9V for LVPECL clock) can be applied to positive input.



AUTOMATIC/MANUAL REFERENCE CLOCK SWITCHING (SMART MUX)

The CDCE72010 supports two reference clock inputs, the primary clock input, PRI_REF, and the secondary clock input, SEC_REF. The clocks can be selected manually or automatically. The respective mode is selected by the dedicated register. In the manual mode the external REF_SEL signal selects one of the two input clocks

In the automatic mode the primary clock is selected by default even if both clocks are available. In case the primary clock is not available or fails, then the input switches to the secondary clock until the primary clock is back. The figure below shows the automatic clock selection.



Figure 23. Automatic Clock Select Timing

In the automatic mode the frequencies of both clock signals has to be similar but may differ by up to 20%. There is no limitation placed on the phase relationship between the two inputs.

The clock input circuitry is designed to suppress glitches during switching between the primary and secondary clock in the manual and automatic mode. This insures that the clock outputs continue to clock reliably when a transition from a clock input occurs.

The phase of the output clock will slowly follow the new input phase. The speed of this transition is determined by the loop bandwidth. However, there is no phase build-out function supported (like in SONET/SDH applications).



SCAS858C -JUNE 2008-REVISED JANUARY 2012

www.ti.com

PHASE FREQUENCY DETECTOR

The main function of the CDCE72010 device is to synchronize a Voltage Control Oscillator (VCO) or a Voltage Control Crystal Oscillator (VCXO) output to a reference clock input. The phase detector compares 2 signals and outputs the difference between them. It is symbolized by an XOR. The compared signals are derived from the Reference clock and from the VCO/VCXO clocks. The Reference clock is divided by the "R" Divider (1 or 2) and "M" divider (14 Bits) and presented to the PFD. The VCO/VCXO clock is divided by the Feedback Divider "P" (1 to 80) and the "N" Divider (14 Bits) and presented to the PFD.

Frequency (VCXO_IN or AUX_IN) / Frequency (PRI_REF or SEC_REF) = (P*N)/(R*M)

The PFD is a classical style with UP and DOWN signals generating flip-flops and a common reset path. Some special functions were implemented:

- Bit CP_DIR (register 0 bit<9> can swap internally the REF- and FB-CLK inputs to the PFD flip-flops.
- The reset path can be typically delayed with the bits DELAY_PFD <1:0> (register 0 bit<7:6>) from 1.5ns to 6.0ns.

PFD Pulse Width Delay (Register 0 Bits [7:6])

The "PFD pulse width delay" gets around the dead zone of the PFD transfer function and reduces phase noise and reference spurs.

PFD1	PFD0	PFD PULSE WIDTH DELAY
0	0	1.5ns ⁽¹⁾
0	1	3.0ns
1	0	4.5ns
1	1	6.0ns

Tahle	11	PFD	Pulse	Width	Delay
Table			i uise	WWIGUI	Delay

(1) Default

The PFD receives two clocks of the similar frequencies and decides if one is lagging or leading. This Lagging/Leading signals are feed to the Charge Pump. The Charge Pump in its turn takes the Lagging/Leading signals and translate them into current pulses that are feed to the external filter. The Output of the external filter is a DC level that controls the Voltage reference of the VCO/VCXO sitting outside and feeding the CDCE72010 at the VCXO Input. The VCO/VCXO drifts its outputs frequency with respect to the voltage applied to its Voltage Control pin. This is how the loop is closed.



Figure 24. Phase Frequency Detection

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

www.ti.com

	FEED	BACK DIVIDE	R SETTINGS (I	REGISTER 11:	BITS)		DIVIDER
11	10	9	8	7	6	5	SETTING
0	1	0	0	0	0	0	1
1	0	0	0	0	0	0	2
1	0	0	0	0	0	1	3
1	0	0	0	0	1	0	4
1	0	0	0	0	1	1	5
0	0	0	0	0	0	0	4'
0	0	0	0	0	0	1	6
0	0	0	0	0	1	0	8
0	0	0	0	0	1	1	10
0	0	0	0	1	0	0	8'
0	0	0	0	1	0	1	12
0	0	0	0	1	1	0	16
0	0	0	0	1	1	1	20
0	0	0	1	0	0	0	12'
0	0	0	1	0	0	1	18
0	0	0	1	0	1	0	24
0	0	0	1	0	1	1	30
0	0	0	1	1	0	0	16'
0	0	0	1	1	0	1	24'
0	0	0	1	1	1	0	32
0	0	0	1	1	1	1	40
0	0	1	0	0	0	0	20'
0	0	1	0	0	0	1	30'
0	0	1	0	0	1	0	40'
0	0	1	0	0	1	1	50
0	0	1	0	1	0	0	24'
0	0	1	0	1	0	1	36
0	0	1	0	1	1	0	48
0	0	1	0	1	1	1	60
0	0	1	1	0	0	0	28
0	0	1	1	0	0	1	42
0	0	1	1	0	1	0	56
0	0	1	1	0	1	1	70
0	0	1	1	1	0	0	32'
0	0	1	1	1	0	1	48'
0	0	1	1	1	1	0	64
0	0	1	1	1	1	1	80

Table 12. Feedback Divider Settings



SCAS858C -JUNE 2008-REVISED JANUARY 2012

www.ti.com

PHASE DELAY FOR M AND N

Delay Block in M/N Path

Table 13. Reference Delay M (PRI_REF or SEC_REF) and Feedback Delay N (VCXO) Phase Adjustment (Register 2 Bits [5:0]) ⁽¹⁾

DLYM2/DLYN2	DLYM1/DLYN1	DLYM0/DLYN0	PHASE OFFSET
0	0	0	0ps ⁽²⁾
0	0	1	±160ps
0	1	0	±320ps
0	1	1	±480ps
1	0	0	±830ps
1	0	1	±1130ps
1	1	0	±1450ps
1	1	1	±1750ps

(1) If Progr Delay M is set, all Yx outputs are lagging to the Reference Clock according to the value set. If Progr Delay N is set, all Yx outputs are leading to the Reference Clock according to the value set. Above are typical values at $V_{CC} = 3.3$ V, $T_A = 25^{\circ}$ C, PECL-output relate to Div4 mode.

(2) Default

Table 14. Input and Feedback Divider: 14-Bit (Register 10 Bits [13:0] for M and Bits [27:14] for N)

N13	N12	N11	N10	N9	N8	N7	N6	N5	N4	N3	N2	N1	N0	DIV BY ⁽¹⁾
0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
0	0	0	0	0	0	0	0	0	0	0	0	0	1	2
0	0	0	0	0	0	0	0	0	0	0	0	1	0	3
0	0	0	0	0	0	0	0	0	0	0	0	1	1	4
								•						
0	0	0	0	0	0	0	1	1	1	1	1	0	0	125 ⁽²⁾
								•						
1	1	1	1	1	1	1	1	1	1	1	1	0	1	16382
1	1	1	1	1	1	1	1	1	1	1	1	1	0	16383
1	1	1	1	1	1	1	1	1	1	1	1	1	1	16384

(1) If the divider value is Q, then the code will be the binary value of (Q - 1).

(2) Factory EEPROM Default values M = 125 and N = 768

SCAS858C-JUNE 2008-REVISED JANUARY 2012



www.ti.com

CHARGE PUMP

The Charge Pump drives the loop filter that controls the external VCO/VCXO. The Charge pump operates at the PFD frequency since the function of the charge pump is to translate the UP DOWN signals of the PFD into current pulses that drives the external filter. The Charge pump current is set by the control vector ICP [3:0].

ICP3	ICP2	ICP1	ICP0	TYPICAL CHARGE PUMP CURRENT
0	0	0	0	0 μA (3-State)
0	0	0	1	200 µA
0	0	1	0	400 µA
0	0	1	1	600 µA
0	1	0	0	800 μA
0	1	0	1	1.0 mA
0	1	1	0	1.2 mA
0	1	1	1	1.4 mA
1	0	0	0	1.6 mA
1	0	0	1	1.8 mA
1	0	1	0	2.0 mA
1	0	1	1	2.2 mA ⁽¹⁾
1	1	0	0	2.4 mA
1	1	0	1	2.6 mA
1	1	1	0	2.8 mA
1	1	1	1	3.0 mA

Table 15. CP, Charge Pump Current (Register 0 RAM Bits [17:14])

(1) Default

The CP_PRE register bit R0.13 is a useful feature to quickly set the center frequency of the VC(X)O after Power-up or Reset. The adequate control voltage for the VC(X)O will be provided to the Charge-Pump output by an internal voltage divider of $1K\Omega/1K\Omega$ to V_{CC_CP} and GND ($V_{CC_CP}/2$). The CP_PRE register bit must be reset to "0" in order for the PLL to achieve lock.

This feature helps to get the initial frequency accuracy, i.e. required at CPRI (Common Public Radio Interface) or OBSAI (Open Base Station Architecture Initiative).

The Preset Charge-Pump to $V_{CC CP}/2$ can be set and reset by register.



SCAS858C - JUNE 2008 - REVISED JANUARY 2012

www.ti.com

Charge-Pump Current Direction

The direction of the charge-pump (CP) current pulse can be changed by the register settings. It determines in which direction CP current will regulate (Reference Clock leads to Feedback Clock). Most applications use the positive CP output current (power-up condition) because of the use of a passive loop filter. The negative CP current is useful when using an active loop filter concept with inverting operational amplifier. The Figure below shows the internal PFD signal and the corresponding CP current.



PFD pulse width delay improves spurious suppression.

Figure 25. Charge Pump

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

PLL LOCK FOR ANALOG AND DIGITAL DETECT

The CDCE72010 supports two PLL Lock indications: the digital lock signal or the analog lock signal. Both signals indicate logic high-level at PLL_LOCK if the PLL locks according the selected lock condition.

The PLL is locked (set high), if the rising edge of the Reference Clock (PRI_REF or SEC_REF clock) and Feedback Clock (VCXO_IN clock) at the PFD (Phase Frequency Detect) are inside a predefined lock detect window for a pre-defined number of successive clock cycles.

The PLL is out-of-lock (set low), if the rising edge of the Reference Clock (PRI_REF or SEC_REF clock) and Feedback Clock (VCXO_IN clock) at the PFD are outside the predefined lock detect window.

Both, the lock detect window and the number of successive clock cycles are user definable in the register settings.



Figure 26. PLL Lock

The lock detect window describes the maximum allowed time difference for lock detect between the rising edge of PRI_REF or SEC_REF and VCXO_IN. The time difference is detected at the phase frequency detector. The rising edge of PRI_REF or SEC_REF is taken as reference. The rising edge of VCXO_IN is outside the lock detect window, if there is a phase displacement of more than $+0.5*t_{(lockdetect)}$ or $-0.5*t_{(lockdetect)}$.

Table 16. Lock-Detect Window	(Register 7 Bits [1:0	0] and Register 9 Bits [7:6])
------------------------------	-----------------------	------------------------------	----------

LOCKW3 [7]	LOCKW2 [6]	LOCKW1 [1]	LOCKW0 [0]	PHASE-OFFSET AT PFD-INPUT ⁽¹⁾
0	0	0	0	1.5 ns
0	0	0	1	5.8 ns ⁽²⁾
0	0	1	0	15.1 ns
0	0	1	1	Reserved
0	1	0	0	3.4 ns
0	1	0	1	7.7 ns
0	1	1	0	17.0 ns
0	1	1	1	Reserved
1	0	0	0	5.4 ns
1	0	0	1	9.7 ns
1	0	1	0	19.0 ns
1	0	1	1	Reserved
1	1	0	0	15.0 ns
1	1	0	1	19.3 ns
1	1	1	0	28.6 ns
1	1	1	1	Reserved

(1) Typical values at V_{CC} = 3.3 V, T_A = 25° C

(2) Default

58



www.ti.com

SCAS858C -JUNE 2008-REVISED JANUARY 2012

Table 17. Number of Successive Lock Events Inside the Lock Detect Window (Register 7 Bits [4:3]) the PLL Lock Signal is Delayed for Number of FB_CLK Events

LOCKC1	LOCKC0	NO. OF SUCCESSIVE LOCK EVENTS
0	0	1
0	1	16
1	0	64 ⁽¹⁾
1	1	256

(1) Default

DIGITAL LOCK DETECT

When selecting the digital PLL lock option, PLL_LOCK will possibly jitter several times between lock and out of lock until a stable lock is detected. A single "low-to-high" step can be reached with a wide lock detect window and high number of successive clock cycles. PLL_LOCK will return to out of lock if just one cycle is outside the lock detect window.



Figure 27. Digital Lock

SCAS858C – JUNE 2008 – REVISED JANUARY 2012

ANALOG LOCK DETECT

When selecting the analog PLL Lock option, the high-pulses load the external capacitor via the internal 110 μ A current source until logic high-level is reached. Therefore, more time is needed to detect logic high level, but jittering of PLL_LOCK will be suppressed like possible in case of digital lock. The time PLL_LOCK needs to return to out of lock depends on the level of V_{OUT}, when the current source starts to unload the external capacitor.



Figure 28. Analog Lock

FREQUENCY HOLD-OVER MODE

The HOLD-Function is a CDCE72010 feature that helps to improve system reliability. The HOLD-Function holds the output frequency in case the input reference clock fails or is disrupted. During HOLD, the Charge-Pump is switched off (3-State) freezing the last valid output frequency. The Hold-Function will be released after a valid reference clock is reapplied to the clock input and detected by the CDCE72010. For proper HOLD function, the Analog PLL-Lock-Detect mode has to be active. The following settings are involved with the HOLD Function:

- Lock Detect Window: Defines the window in ns inwhich the Lock is valid. The size is 3.5ns, 8.5ns, 18.5ns. Lock is set if Reference Clock and Feedback Clock are inside this predefined Lock-Detect Window for a pre-selected number of successive cycles.
- Out-of-Lock: Defines the out-of-lock condition: If the Reference Clock and the Feedback Clock at the PFD are outside the predefined Lock Detect Window.
- Number of Clock Cycles: Defines the number of successive PFD cycles which have to occur inside the lock window to set Lock detect. This does not apply for Out-of-Lock condition.
- Hold-Function: Selects HOLD-Function (see more details below).
- Hold-Trigger: Defines whether the HOLD-Function is always activated or whether it is dependent on the state of the analog PLL Lock detect output. In the latter case, HOLD is activated if Lock is set (high) and de-activated if Lock is reset (low).
- Analog PLL Lock Detect: Analog Lock output charges or discharges an external capacitor with every valid Lock cycle. The time constant for Lock detect can be set by the value of the capacitor.

The CDCE72010 supports two types of HOLD functions, one external controllable HOLD mode and one internal mode, HOLD.

EXTERNAL/HOLD FUNCTION

The Charge Pump can directly be switched into 3-State. This function is <u>also available via register</u>. If logic low is applied to HOLD pin the Charge Pump will be switched to 3-State. After HOLD pin is released, the charge pump is switched back in to normal operation, with the next <u>valid</u> reference clock cycle at PRI_REF or SEC_REF and the next valid feedback clock cycle at the PFD. During HOLD, all divider and all outputs are at normal operation.



SCAS858C – JUNE 2008 – REVISED JANUARY 2012

www.ti.com

INTERNAL/HOLD FUNCTION

In Internal HOLD Function or HOLD-Over-Function the PLL has to be in lock to start the HOLD function. It switches the Charge Pump in to 3-State when an 'out-of-lock' event occurs. It leaves the '3-State Charge Pump' state when the Reference Clock is back. Then it starts a locking sequence of 64 cycles before it goes back to the beginning of the HOLD-Over loop.



Figure 29. Frequency Hold Over



www.ti.com

OUTPUT DIVIDERS AND PHASE ADJUST

The CDCE72010 is designed with individual Output Dividers for Outputs 1 to 8. Output Divider 1 drives Output 1 and Output 0 and Output Divider 8 drives Output 8 and Output 9. Each output divider has a bypass function or it is referred to as divide by "one". Since divide by one bypasses the divider block it can address higher operating frequencies.

The output divider is designed to address divide by 1, 2, 3, 4, 5, 6, 8, 10, 12, 16, 18, 20, 24, 28, 30, 32, 36, 40, 42, 48, 50, 56, 60, 64, 70 and 80. The output divider includes a coarse phase adjust that shifts the divided clock signal. The phase adjust resolution is a function of the divide function. The maximum number of phase steps equals to the divider setting.

If the output is divide by 2, then two phase adjustment settings (0 and 180 degrees) are available. The resolution of phase adjustment is related to the output divider setting by the following: Phase adjust resolution = (1/Output Divider settings) X 360 Degrees.

Example: For a 491.52MHz VCXO where one of the outputs of the device is set to divide by 16 for a 30.72MHz desired output, this will mean that the 30.72MHz clock will have $(1/16) \times 360 = 22.5$ Degrees of phase adjustment resolution.

Output Divide Select (OUT#DIVSEL#) and Coarse Phase Adjust Select (PH#ADJC#) registers are located in Register 1 thought 8 for Output 1 thought 8 respectively.

The Phase difference between 2 divider settings on different output can be calculated using the following formula and referring to the Phase Lag number in the Output Divider Table (see Table 8).

Integer Remainder of [(Phase Lag X - Phase Lag Y)/ Divide X] as an example if we need to calculate the phase difference between divide by 4 and divide by 8 with respect to divide by 4 clock.

The Integer Remainder [(28.5 - 0.5)/4] = 0. This means there is 0 Cycle phase delay between Divide by 4 and Divide by 8 with respect to Divide by 4 Clock.

If we need to do the same calculation with respect to Divide by 8 we will have Intger Remainder [(28.5 - 0.5)/8] = 0.5 that means that there is 0.5 Cycles between Divide by 4 and divide by 8 with respect to a divide by 8 clock.



Figure 30. Maximum Output Frequency With Phase Alighment

FREQUENCY DETECTION CIRCUIT

The Frequency detector circuit can detect the input clock signal and provide the indications at STATUS pin depending on Register 12 and 3 settings (see notes in page 33). The STATUS pin will set to HIGH if a valid input clock is detected. And LOW if valid input clock is absent or missing.

The frequency detector circuit is located in between the SMART MUX and the M divider (see Figure 31).





Figure 31. Location of the Frequency Detector Circuit

The detection circuit is RC-based analog circuit. The response time to detect a new clock signal is clock-frequency dependent (min. 3.125µs at 0.8MHz). With higher clock frequency the response time will be faster as well.

If the input clock goes away, the detector reports the event within 5.2 µs independent of clock frequency.

PARAMETER	MIN	TYP	MAX	UNIT
Frequency detection threshold ⁽¹⁾	800			kHz
Response time (clock absence) ⁽¹⁾	2.62		5.2	μs
Response time (clock resumes) at 0.8 MHz ⁽¹⁾	3.125		29	μs
Clock cycles (clock resumes) at 0.8 MHz ⁽²⁾	2.5		23	cycles

Table 18. Specifications

(1) Received values from simulation

(2) Received values from simulation

SCAS858C-JUNE 2008-REVISED JANUARY 2012



DEVICE LAYOUT

The CDCE72010 is a high performance device packaged in a QFN-64. The die has all the ground pins bounded to the thermal PAD on the bottom of the package. Therefore it is essential that the connection from the thermal PAD to the ground layers should be low impedance. In addition, the thermal path in a QFN package is via the thermal PAD on the bottom of the package. Therefore, the layout of the PAD is very important and it will affect the thermal performance as well as the overall performance of the device. The illustration shown provides optimal performance in terms of thermal issues, inductance and power supply bypassing. The 10 X 10 Filled VIA pattern recommended allows for a low inductance connection between the thermal ground pad and the ground plane of the board. This pattern forms a low thermal resistive path for the heat generated by the die to get dissipated through the ground plane and to the exposed bottom side ground pad. It is recommended that solder mask not be used on this bottom side pad to maximize its effectiveness as a thermal heat sink. The recommended layout drives the thermal conductivity to 22.8 C°/W in still air and 13.8 C°/W in a 100LFM air flow if implemented on a JEDEC compliant test thermal board.



Figure 32. Device Layout



www.ti.com

DEVICE POWER

The CDCE72010 is designed as a high performance device, therefore careful attention must be paid to device configuration with respect to power consumption. Total power consumption of the device can be estimated by adding up the total power consumed by each block in the device.

The Table below describes the blocks used and power consumed per block. The total power of the device can be calculated by multiplying the number of blocks used by the power consumption per block.

Table 19.	Device	Power
-----------	--------	-------

I	nternal Block Power at 3.3V (typ.)	Power Dissipation/ Block	Number of Blocks
PLL Core, Input and Feedback		530 mW	1
Output Dividers	Divider = 1	82 mW	8
	Divider > 1	180 mW	
LVPECL Output Buffer		75 mW ⁽¹⁾	10
LVDS Output Buffer		75 mW	10
LVCMOS Output	Static	7 mW	20
Buffer	Transient, 'CL' load, 'f _{OUT} ' MHz output frequency, 'V' output swing	$V_{DD} \times V \times f_{OUT} \times (C_L + 20 \times 10^{-12}) \times 10^3$	20

(1) Approximately 50 mW power dissipates externally at termination resistors per LVPECL output pair.



Figure 33. Die Temperature

SCAS858C – JUNE 2008 – REVISED JANUARY 2012



LOOP FILTER

The CDCE72010 is designed to control an external Voltage Controlled Oscillator (VCO) or a Voltage Controlled Crystal Oscillator (VCXO) and to synchronize the controlled oscillators to the input reference. Controlling the Oscillator happens via a DC voltage that is applied to the Voltage control pin. This DC voltage is generated by the CDCE72010 in the form of AC pulses that get filtered by the external loop filter.



Figure 34. Loop Filter



www.ti.com

UNIVERSAL OUTPUT BUFFERS

The CDCE72010 is designed to drive three types of clock signaling, LVPECL, LVDS, and LVCMOS from each of the ten outputs. This super buffer that contains all three drivers is refered to as the Universal Output Buffer. Only one driver can be enabled at one time. Each universal output buffer is made from four independent buffers in parallel. When LVPECL mode is selected, only the LVPECL Buffer is enabled and the rest of the buffers are 3-stated and in low power mode. When Selecting LVDS, only the LVDS Buffer is enabled and the rest of the buffers are 3-stated and in low power mode. When LVCMOS mode is selected, both LVCMOS drivers are enabled. One LVCMOS buffer drives the negative side and the other buffer drives the positive pin.

The LVCMOS drivers are driven from the same output divider but have separate control bits. In SPI Mode, bits 22, 23, 24, and 25 of Registers 0 to 9 are used to put the LVCMOS buffer in active, inverting, low, or 3-state. In CD Mode, those bits are used for different functions and the LVCMOS buffer can be active when selected or 3-state when their not.



Figure 35. Universal Output Buffer

SCAS858C – JUNE 2008 – REVISED JANUARY 2012



Output Dividers Synchronization

The CDCE72010 is a 10 output clock device with 8 output dividers and to insure that all the outputs are synchronous a synchronization startup circuitry is used. The synchronization circuitry generates a pulse to reset all the dividers in a way, that a predictable synchronous output is generated. The Synchronization signal can be generated from different sources and can be synchronized to a specific clock. The Block diagram below illustrates the signal path of the Output Divider Sync Signal. This function is assured up to 500 MHz.

NOTE The minimum frequency required for the output synchronization block to work properly is 1 MHz.



Figure 36. Output Divider Synchronization Block Diagram



SCAS858C - JUNE 2008 - REVISED JANUARY 2012

www.ti.com

POWER UP RESET, POWER DOWN MODE AND RESET OR HOLD

The CDCE72010 is designed to address various clock synchronization applications. Some functions can be set to be in automatic and manual mode or some functions can be controlled by software or by the internal circuitry.

Table 20 explains the various functionalities of power up reset internal circuitry functionality, power down functionality and reset functionality. The hold function shares the same block with Reset and one bit in the EEPROM will select either function.

RESET_HOLD_MODE (R11.25)	SLEEP (R12.7)	RESET_HOLD (R12.8)	RESET/HOLD (pin #33)	PD (pin #17)	MODE
Х	Х	Х	Х	0	Device in Power down. On Power down exit, register reset to EEPROM defaults.
Х	0	Х	Х	1	Device in SLEEP Mode. It's the same as power down but upon exit of this mode, the registers will retain their previous state (no EEPROM reload).
0	1		00 01 10	1	Device in RESET. Power consumption minimized outputs tri-state. Upon exit of this mode, the registers will retain their previous state (no EEPROM reload).
1	1		00 01 10	1	Device in HOLD mode. The CP output is tri-stated.
Х	1		11	1	Normal Mode.

Table 20. RESET_HOLD_STATE

Changes from Revision A (June 2008) to Revision B

•	Changed many instances in rev B of this data sheet (major changes/additions to this data sheet)	. 1
•	Deleted "Dedicated Charge-PumpVCOs" from FEATURES	. 1
•	Changed Figure 1	. 2
•	Changed Pin Functions table	. 4
•	Changed Pin Functions table	. 5
•	Changed Pin Functions table	. 6
•	Changed Recommended Operating Conditions table	. 7
•	Changed Timing Requirements table	. 8
•	Changed AC/DC Characteristics table	. 9
•	Added new section "INTERFACE AND CONTROL BLOCK" including figures/tables	19
•	Changed Table 6	23
•	Changed Table 6	23
•	Changed text/rows in all Register tables	24
•	Changed SLEEP and RESET_HOLD	36
•	Changed "Universal Input and Reference Clock Buffers" section including figures	51
•	Changed Figure 21	51
•	Changed Figure 22	52
•	Changed tables in "PHASE DELAY for M and N" section	55
•	Deleted 0 from N1 and N0	55
•	Changed text in "CHARGE PUMP" section	56
•	- Changed text in CHARGE PUMP section	56
•	Changed Table 19	65
•	Changed SLEEP in Table 20 to active low	69
	-	

CI	nanges from Revision B (August 2011) to Revision C	Pag	ge
•	Changed Pin 3 and 58 to Pin 5 and 8 in PIN FUNCTIONS note		4
•	Changed in Table 6, Reg 11 from 81E09B0C to 8000058B		23

SCAS858C-JUNE 2008-REVISED JANUARY 2012

Changes from Original (June 2008) to Revision A

REVISION HISTORY

Changed Frequency equation result from (R*M)/(P*N) to (P*N)/(R*M) 2

XAS STRUMENTS

www.ti.com

Page

Page



PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS	Lead finish/	MSL rating/	Op temp (°C)	Part marking
	(1)	(2)			(3)	Ball material	Peak reflow		(6)
						(4)	(5)		
CDCE72010RGCR	Active	Production	VQFN (RGC) 64	2000 LARGE T&R	Yes	NIPDAUAG	Level-3-260C-168 HR	-40 to 85	CDCE72010
CDCE72010RGCR.B	Active	Production	VQFN (RGC) 64	2000 LARGE T&R	Yes	NIPDAUAG	Level-3-260C-168 HR	-40 to 85	CDCE72010
CDCE72010RGCT	Active	Production	VQFN (RGC) 64	250 SMALL T&R	Yes	NIPDAUAG	Level-3-260C-168 HR	-40 to 85	CDCE72010
CDCE72010RGCT.B	Active	Production	VQFN (RGC) 64	250 SMALL T&R	Yes	NIPDAUAG	Level-3-260C-168 HR	-40 to 85	CDCE72010
CDCE72010RGCTG4	Active	Production	VQFN (RGC) 64	250 SMALL T&R	Yes	NIPDAUAG	Level-3-260C-168 HR	-40 to 85	CDCE72010

⁽¹⁾ **Status:** For more details on status, see our product life cycle.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

PACKAGE MATERIALS INFORMATION

www.ti.com

Texas Instruments

TAPE AND REEL INFORMATION





QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal												
Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
CDCE72010RGCR	VQFN	RGC	64	2000	330.0	16.4	9.3	9.3	1.5	12.0	16.0	Q2
CDCE72010RGCT	VQFN	RGC	64	250	330.0	16.4	9.3	9.3	1.5	12.0	16.0	Q2
TEXAS INSTRUMENTS

www.ti.com

PACKAGE MATERIALS INFORMATION

9-Aug-2017



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
CDCE72010RGCR	VQFN	RGC	64	2000	367.0	367.0	38.0
CDCE72010RGCT	VQFN	RGC	64	250	367.0	367.0	38.0

RGC 64

9 x 9, 0.5 mm pitch

GENERIC PACKAGE VIEW

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



Images above are just a representation of the package family, actual package may vary. Refer to the product data sheet for package details.



RGC0064H



PACKAGE OUTLINE

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M. 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.



RGC0064H

EXAMPLE BOARD LAYOUT

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES: (continued)

 This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).

5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.



RGC0064H

EXAMPLE STENCIL DESIGN

VQFN - 1 mm max height

PLASTIC QUAD FLATPACK - NO LEAD



NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2025, Texas Instruments Incorporated