

# Power for C5504/05

# C5504/05 Power Spec Table

	Pin Name	Voltage (V)	Max Current <sup>4</sup> (mA)	Tolerance	Sequencing Order	Comments
	LDO1 <sup>3</sup>	1.8 - 3.6	5		12	Supplying <b>ANA LDO</b> (supplies VDDA_ANA and VDDA_PLL).
Core	CVDD <sup>1</sup> , CVDDRTC <sup>1</sup>	1.05 / 1.30	500	-5%, +10%		Typical Core Power Consumption: - 0.22mW/MHz for 75% DMAC + 25% NOP (CVDD = 1.3V @ 100MHz, Room Temp) - 0.14mW/MHz for 75% DMAC + 25% NOP (CVDD = 1.05V @ 100MHz, Room Temp)
	USB_VDD1P3, USB_VDDA1P3	1.3V	70	-5%, +10%		For best performance, these voltages should be powered by a LDO in order to minimize noise.
	DVDDIO, DVDDRTC	1.8 / 2.5 / 2.8 / 3.3	300	-10%, +10%		
	DVDDMIF	1.8 / 2.5 / 2.8 / 3.3	245	-10%, +10%		
	USB_VDDOSC, USB_VDDA3P3, USB_VDDPLL	3.3V	55	-5%, +5%		


## NOTES:

- 1) CVDD & CVDDRTC can be 1.05V or 1.30V for ≤60MHz operation and 1.30V for operating higher than 60MHz
- 2) **Power Supply Sequencing:** No sequencing is required (for further details, see section 5.3.1 of the data sheet)
- 3) If GPAIN pins are used as general purpose outputs, the internal ANA\_LDO must not be used as the max current capability of ANA\_LDO can be exceeded. In this case use an external regulator to supply VDDA\_ANA..
- 4) This column shows the maximum design current of each power domain. See the C5505/04 data sheet for actual current consumptions of some usage cases. See the data in the "Comments" column above.

# Power Options for C5504/05


\*Please visit [ti.com/processorpower](http://ti.com/processorpower) for COMPLETE power solutions

## Highest Efficiency, Low Cost Integrated PMIC




- 2 DCDC + 4 LDO's in 4x4mm QFN
- 2.25MHz for Small Inductors
- 180° Out-of-Phase Operation

## High-Efficiency, Dual DCDC + PMIC




- Up to 95% Efficiency
- 2.25MHz for Small Inductors
- Integrated SVS

## Lowest Cost, Dual DCDC @ 3.3V & 1.3V




- 3.6 - 6V input voltage
- Efficiency up to 95%
- 2.25MHz for Small Inductors

## High Input Voltage, DCDC Converters




- Input voltage capable up to 17V
- PFM mode for high efficiency during light loads
- Low-Noise LDO (32uVrms)

# Highest Efficiency, Single PMIC (TPS65054)




# High Efficiency, Low part count (TPS62400 + TPS65001)




# High Efficiency, Lowest cost

## Reduce rails to 1.3V and 3.3V



# High Input Voltage



## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

<b>Products</b>		<b>Applications</b>	
Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>	Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>	Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
DLP® Products	<a href="http://www.dlp.com">www.dlp.com</a>	Communications and Telecom	<a href="http://www.ti.com/communications">www.ti.com/communications</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>	Computers and Peripherals	<a href="http://www.ti.com/computers">www.ti.com/computers</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>	Consumer Electronics	<a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>	Energy	<a href="http://www.ti.com/energy">www.ti.com/energy</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>	Industrial	<a href="http://www.ti.com/industrial">www.ti.com/industrial</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>	Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>	Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>	Space, Avionics & Defense	<a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a>
RF/IF and ZigBee® Solutions	<a href="http://www.ti.com/lprf">www.ti.com/lprf</a>	Video and Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
		Wireless	<a href="http://www.ti.com/wireless-apps">www.ti.com/wireless-apps</a>

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2010, Texas Instruments Incorporated