SN54298, SN54LS298, SN74298, SN74LS298 QUADRUPLE 2-INPUT MULTIPLEXERS WITH STORAGE

SN5429

SDLS098 MARCH 1974 - REVISED MARCH 1988

- Selects One of Two 4-Bit Data Sources and Stores Data Synchronously with System Clock
- Applications:

Dual Source for Operands and Constants in Arithmetic Processor; Can Release Processor Register Files for Acquiring New Data

Implement Separate Registers Capable of Parallel Exchange of Contents Yet Retain External Load Capability

Universal Type Register for Implementing Various Shift Patterns; Even Has Compound Left-Right Capabilities

description


These monolithic quadruple two-input multiplexers with storage provide essentially the equivalent functional capabilities of two separate MSI functions (SN54157/SN74157 or SN54LS157/SN74LS157 and SN54175/SN74175 or SN54LS175/SN74LS175) in a single 16-pin package.

When the word-select input is low, word 1 (A1, B1, C1, D1) is applies to the flip-flops. A high input to word select will cause the selection of word 2 (A2, B2, C2, D2). The selected word is clocked to the output terminals on the negative-going edge of the clock pulse.

Typical power dissipation is 195 milliwatts for the '298 and 65 milliwatts for the 'LS298. SN54298 and SN54LS298 are characterized for operation over the full military temperature range of -55° C to 125°C; SN74298 and SN74LS298 are characterized for operation from 0°C to 70°C.

SN74298 . SN74LS298 .	98JOR W PACKAGE N PACKAGE .DOR N PACKAGE P VIEW)
B2 []	16 VCC
A2 []2	15 QA
A1 []3	14 QB
B1 []4	13 QC
C2 []5	12 QD
D2 []6	11 CLK
D1 []7	10 WS
GND []8	9 C1

SN54LS298 . . . FK PACKAGE (TOP VIEW)



NC - No internal connection

FUNCTION TABLE

INP	UTS	OUTPUTS					
WORD SELECT			a _B	٥ _C	٥D		
L	;	a1	b1	c1	d1		
н	1	a2	b2	c2	d2		
x	н	QAO	Ω_{BO}	\mathbf{o}_{CD}	Q_{D0}		

H = high level (steady state)

L = low level (steady state)

X = irrelevant (any input, including transitions)

} = transition from high to low level

a1, a2, etc. – the level of steady state input at A1, A2, etc. $Q_{A0}, Q_{B0},$ etc. = the level of $Q_A, Q_B,$ etc. entered on the


most recent + transition of the clock input.

PRODUCTION DATA documents centain information current as of publication data. Products conform to specifications par the torms of Taxas instruments standard warranty. Production processing does not necessarily include testing of all parameters.




SN54298, SN54LS298, SN74298, SN74LS298 QUADRUPLE 2-INPUT MULTIPLEXERS WITH STORAGE

logic symbol[†]




[†]This symbol is in accordance with ANSI/IEEE Std. 91-1984 and IEC Publication 617-12.

Pin numbers shown are for D, J, N, and W packages.



schematics of inputs and outputs



TEXAS INSTRUMENTS

SN54298, SN74298 QUADRUPLE 2-INPUT MULTIPLEXERS WITH STORAGE

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, VCC (see Note 1)	•
nput voltage	1
Derating free-air temperature range: SN54298	;
SN74298	
Storage temperature	:

NOTE 1: Voltage values are with respect to network ground terminal.

recommended operating conditions

		SN54298				8	UNIT		
		MIN	NOM	MAX	MIN	NOM	MAX		
Supply voltage, V _{CC}		4.5	5	5.5	4.75	5	5.25	V	
High-level output current, IOH				-800			-800	μA	
Low-level output current, 10L				16			16	mA	
Width of clock pulse, high or low level, tw		20			20			ns	
	Data	15			15				
Setup time, t _{su}	Word select	25			25			ns	
	Data				5				
Hold time, t _h	Word select	0			0			ns	
Operating free-air temperature, TA		-55		125	0		70	°C	

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

	PARAMETER	TEST CONDITIONS [†]	MIN	TYP‡	MAX	UNIT
⊻ін	High-level input voltage		2			V
VIL	Low-level input voltage				0.8	V
VIK	Input clamp voltage	V _{CC} = MIN, i ₁ = -12 mA			-1.5	V
∨он	High-level output voltage	V _{CC} ≈ MIN, V _{1H} = 2 V, V _{1L} = 0.8 V, I _{OH} =800 µ	A 2.4	3.2		v
VOL	Low-level output voltage	V _{CC} = MIN, V _{IH} = 2 V, V _{IL} = 0.8 V, I _{OL} = 16 mA			0.4	v
<u>ц</u>	Input current at maximum input voltage	V _{CC} = MAX, V _I = 5.5 V			1	mA
Чн	High-level input current	V _{CC} = MAX, V _I = 2.4 V			40	μA
HL.	Low-level input current	V _{CC} = MAX, V _I = 0.4 V			-1.6	mA
		SN54298	-20		-57	-
os	Short-circuit output current \$	V _{CC} = MAX SN7429B	-18		-57	mA
'cc	Supply current	V _{CC} = MAX, See Note 2		39	65	mA

For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

[‡]All typical values are at V_{CC} = 5 V, T_A = 25°C. [§]Not more than one output should be shorted at a time.

NOTE 2: With all outputs open and all inputs except clock low, ICC is measured after applying a momentary 4.5 V, followed by ground, to the clock input.

switching characteristics, VCC = 5 V, TA = 25°C

PARAMETER	TEST CONDITIONS	MIN T	YP MAX	UNIT
tPLH Propegation delay time, low-to-high-level output	$C_{L} = 15 pF$, $R_{L} = 400 \Omega$,		18 27	ns
TPHE Propagation delay time, high-to-low-level output	See Note 3		21 32	_ ''°

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.



SN54LS298, SN74LS298 QUADRUPLE 2-INPUT MULTIPLEXERS WITH STORAGE

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, VCC (see Note 1)			7 V
Operating free-air temperature range	SN54LS298		25°C
	SN74LS298		70°C
Storage temperature range		$-65^{\circ}C$ to 1	50°C

NOTE 1: Voltage values are with respect to network ground terminal.

recommended operating conditions

		SN54LS298			SP	98			
		MIN	NOM	MAX	MIN	NOM	MAX	UNIT	
Supply voltage, V _{CC}		4.5	5	5.5	4.75	5	5.25	v	
High-level output current, IOH				-400			-400	μA	
Low-level output current, IOL		T		4			8	mA	
Width of clock pulse, high or low level, tw		20			20			пs	
	Data	15			15				
Setup time, t _{su}	Word select	25			25			пs	
	Data	5			5				
Hold time, t _h	Word select	0			0	•		ns	
Operating free-air temperature, TA		-55		125	0		70	°C	

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

			TCONDITION	et.	SM	V54LS2	98	SN74LS298			
	PARAMETER	163	I CONDITION:	5'	MIN	TYP‡	MAX	MIN	TYP‡	MAX	UNIT
ViH	High-level input voltage				2			2			V
VIL	Low-level input voltage						0.7			0.8	V
Vik	Input clamp voltage	V _{CC} = MIN,	l∣ ≂ –18 mA				- 1.5			-1.5	V
∨он	High-level output voltage	V _{CC} ≈ MIN, V _{IL} = V _{IL} max,	V _{IH} = 2 V, I _{OH} = -400 µ.	A	2.5	3.4		2.7	3.4		v
VOL	Low-level output voltage	V _{CC} = MIN, V _{1L} = V _{IL} max	V _{IH} = 2 V,	I _{OL} = 4 mA I _{OL} = 8 mA		0.25	0.4		0.25 0.35	0.4 0.5	v
1	Input current at maximum input voltage	V _{CC} = MAX,	V ₁ = 7 V	-			0.1			0.1	mA
ін	High-level input current	V _{CC} = MAX	V1 = 2.7 V				20			20	μA
ΠL	Low-level input current	V _{CC} ≃ MAX,	V _I = 0.4 V		1		~0.4			-0.4	mΑ
los	Short-circuit output current§	V _{CC} = MAX			-20		-100	-20		-100	mA
¹ cc	Supply current	V _{CC} = MAX,	See Note 2			13	21		13	21	mА

 $^{+}$ For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

 $\frac{1}{2}$ All typical values are at V_{CC} = 5 V, T_A = 25°C.

⁸Not more than one output should be shorted at a time, and duration of the short-circuit should not exceed one second. NOTE 2: With all outputs open and all inputs except clock low, 1_{CC} is measured after applying a momentary 4.5 V, followed by ground, to the clock input.

switching characteristics, V_{CC} = 5 V, T_A = 25° C

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
tpLH Propagation delay time, low-to-high-level output	$C_{L} = 15 pF, R_{L} = 2 k\Omega,$		18	27	
TPHL Propagation delay time, high-to-low-level output	See Note 3	[21	32	ns

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.




SN54298, SN54LS298, SN74298, SN74LS298 QUADRUPLE 2-INPUT MULTIPLEXERS WITH STORAGE

TYPICAL APPLICATION DATA


This versatile multiplexer/register can be connected to operate as a shift register that can shift N-places in a single clock pulse.

The following figure illustrates a BCD shift register that will shift an entire 4-bit BCD digit in one clock pulse.



When the word-select input is high and the registers are clocked, the contents of register 1 is transferred (shifted) to register 2 and etc. In effect, the BCD digits are shifted one position. In addition, this application retains a parallel-load capability which means that new BCD data can be entered in the entire register with one clock pulse. This arrangement can be modified to perform the shifting of binary data for any number of bit locations.

Another function that can be implemented with the '298 or 'LS298 is a register that can be designed specifically for supporting multiplier or division operations. The example below is a one place/two-place shift register.



When word select is low and the register is clocked, the outputs of the arithmetic/logic units (ALU's) are shifted one place. When word select is high and the registers are clocked, the data is shifted two places.





PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS (3)	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking (6)
						(4)	(5)		
SN74LS298N	Active	Production	PDIP (N) 16	25 TUBE	Yes	NIPDAU	N/A for Pkg Type	0 to 70	SN74LS298N
SN74LS298N.A	Active	Production	PDIP (N) 16	25 TUBE	Yes	NIPDAU	N/A for Pkg Type	0 to 70	SN74LS298N

⁽¹⁾ **Status:** For more details on status, see our product life cycle.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TEXAS INSTRUMENTS

www.ti.com

23-May-2025

TUBE



- B - Alignment groove width

*All dimensions are nominal

Device	Package Name	Package Type	Pins	SPQ	L (mm)	W (mm)	T (µm)	B (mm)
SN74LS298N	N	PDIP	16	25	506	13.97	11230	4.32
SN74LS298N	N	PDIP	16	25	506	13.97	11230	4.32
SN74LS298N.A	N	PDIP	16	25	506	13.97	11230	4.32
SN74LS298N.A	N	PDIP	16	25	506	13.97	11230	4.32

N (R-PDIP-T**)

PLASTIC DUAL-IN-LINE PACKAGE

16 PINS SHOWN



NOTES:

- A. All linear dimensions are in inches (millimeters).B. This drawing is subject to change without notice.
- Falls within JEDEC MS-001, except 18 and 20 pin minimum body length (Dim A).
- \triangle The 20 pin end lead shoulder width is a vendor option, either half or full width.



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2025, Texas Instruments Incorporated