<ul> <li>Qualified for Automotive Applications</li> <li>Operating Range 2-V to 5.5-V V<sub>CC</sub></li> </ul>	_	PW PACKAGE OP VIEW)
Unbuffered Outputs	1A 1	U <sub>14</sub> V <sub>CC</sub>
<ul> <li>Latch-Up Performance Exceeds 250 mA Per</li> </ul>	1Y 🛮 2	13 6A
JESD 17	2A 🛛 3	12 🛮 6Y
<ul> <li>ESD Protection Exceeds JESD 22</li> </ul>	2Y 🛮 4	11 🛮 5A
<ul><li>2000-V Human-Body Model (A114-A)</li></ul>	3A 🛮 5	10 🛮 5Y
<ul><li>200-V Machine Model (A115-A)</li></ul>	3Y 🛮 6	9 🛮 4A
<ul> <li>1000-V Charged-Device Model (C101)</li> </ul>	GND 🛮 7	8 🛮 4Y

## description/ordering information

The SN74AHCU04 device contains six independent inverters. This device performs the Boolean function  $Y = \overline{A}$ . Internal circuitry consists of single-stage inverters that can be used in analog applications such as crystal oscillators.

#### ORDERING INFORMATION<sup>†</sup>


TA	PACKA	GE <sup>‡</sup>	ORDERABLE PART NUMBER	TOP-SIDE MARKING
SOIC - D		Tape and reel	SN74AHCU04QDRQ1	AHCU04Q
-40°C to 125°C	TSSOP - PW	Tape and reel	SN74AHCU04QPWRQ1	AHCU04Q

<sup>†</sup> For the most current package and ordering information, see the Package Option Addendum at the end of this document, or see the TI web site at http://www.ti.com.

# FUNCTION TABLE (each inverter)

INPUT A	OUTPUT Y
Н	L
L	Н

## logic diagram (positive logic)





Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.



<sup>‡</sup> Package drawings, thermal data, and symbolization are available at http://www.ti.com/packaging.

## absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage range, V <sub>CC</sub>	–0.5 V to 7 V
Input voltage range, V <sub>I</sub> (see Note 1)	
Output voltage range, V <sub>O</sub> (see Note 1)	$\dots$ -0.5 V to V <sub>CC</sub> + 0.5 V
Input clamp current, $I_{IK}$ ( $V_I < 0$ )	–20 mA
Output clamp current, $I_{OK}$ ( $V_O < 0$ or $V_O > V_{CC}$ )	±20 mA
Continuous output current, $I_O$ ( $V_O = 0$ to $V_{CC}$ )	±25 mA
Continuous current through V <sub>CC</sub> or GND	±50 mA
Package thermal impedance, θ <sub>JA</sub> (see Note 2): D package	86°C/W
PW package	113°C/W
Storage temperature range, T <sub>stg</sub>	–65°C to 150°C

<sup>†</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

## recommended operating conditions (see Note 3)

			MIN	MAX	UNIT
VCC	Supply voltage		2	5.5	V
		V <sub>CC</sub> = 2 V	1.7		
$V_{IH}$	High-level input voltage	V <sub>CC</sub> = 3 V	2.4		V
		V <sub>CC</sub> = 5.5 V	4.4		
		V <sub>CC</sub> = 2 V		0.3	
VIL	Low-level input voltage	V <sub>CC</sub> = 3 V		0.6	V
		V <sub>CC</sub> = 5.5 V		1.1	
٧ <sub>I</sub>	Input voltage	-	0	5.5	V
٧o	Output voltage		0	Vcc	V
		V <sub>CC</sub> = 2 V		-50	μΑ
lOH	High-level output current	V <sub>CC</sub> = 3.3 V ± 0.3 V		-4	
		V <sub>CC</sub> = 5 V ± 0.5 V		-8	mA
		V <sub>CC</sub> = 2 V		50	μΑ
loL	Low-level output current	V <sub>CC</sub> = 3.3 V ± 0.3 V		4	
-		$V_{CC} = 5 V \pm 0.5 V$		8	mA
TA	Operating free-air temperature	•	-40	125	°C

NOTE 3: All unused inputs of the device must be held at V<sub>CC</sub> or GND to ensure proper device operation. Refer to the TI application report, Implications of Slow or Floating CMOS Inputs, literature number SCBA004.



NOTES: 1. The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

<sup>2.</sup> The package thermal impedance is calculated in accordance with JESD 51-7.

# electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	Vcc	T <sub>A</sub> = 25°C			T <sub>A</sub> = -		T <sub>A</sub> = -40°C TO 85°C		UNIT
			MIN	TYP	MAX	MIN	MAX	MIN	MAX	
		2 V	1.8	2		1.8		1.8		
	I <sub>OH</sub> = -50 μA	3 V	2.7	3		2.7		2.7		
VOH		4.5 V	4	4.5		4		4		V
	$I_{OH} = -4 \text{ mA}$	3 V	2.58			2.3		2.4		
	I <sub>OH</sub> = -8 mA	4.5 V	3.94			3.5		3.65		
		2 V			0.2		0.2		0.2	
	I <sub>OL</sub> = 50 μA	3 V			0.3		0.3		0.3	
VOL		4.5 V			0.5		0.5		0.5	V
	I <sub>OL</sub> = 4 mA	3 V			0.36		0.5		0.44	
	I <sub>OL</sub> = 8 mA	4.5 V			0.36		0.5		0.44	
II	V <sub>I</sub> = 5.5 V or GND	0 V to 5.5 V			±0.1		±1		±1	μΑ
Icc	$V_I = V_{CC}$ or GND, $I_O = 0$	5.5 V			2		20	·	20	μΑ
Ci	$V_I = V_{CC}$ or GND	5 V		2	10	·		·	10	pF

# switching characteristics over recommended operating free-air temperature range, $V_{CC}$ = 3.3 V $\pm$ 0.3 V (unless otherwise noted) (see Figure 1)

PARAMETER	FROM	TO (OUTPUT)	LOAD	T	λ = 25°C	;	T <sub>A</sub> = -		T <sub>A</sub> = -		UNIT
	(INPUT)	(OUTPUT) CAPACITANCE		MIN	TYP	MAX	MIN	MAX	MIN	MAX	
tPLH .	^	V	0. 45 = 5		5	7.1	1	10.5	1	8.5	
<sup>t</sup> PHL	А	Y	C <sub>L</sub> = 15 pF		5	7.1	1	10.5	1	8.5	ns
<sup>t</sup> PLH	۸		C <sub>I</sub> = 50 pF		7.5	10.6	1	14	1	12	20
t <sub>PHL</sub>	А	ī	CL = 50 pr		7.5	10.6	1	14	1	12	ns

# switching characteristics over recommended operating free-air temperature range, $V_{CC}$ = 5 V $\pm$ 0.5 V (unless otherwise noted) (see Figure 1)

PARAMETER	FROM	TO (OUTPUT)	LOAD	T	λ = 25°C	:	T <sub>A</sub> = - TO 12		T <sub>A</sub> = -		UNIT
	(INPUT)	(OUTPUT)	CAPACITANCE	MIN	TYP	MAX	MIN	MAX	MIN	MAX	
tPLH		V	0 45 = 5		3.5	5.5	1	8.5	1	6.5	
<sup>t</sup> PHL	А	Y	$C_L = 15 pF$		3.5	5.5	1	8.5	1	6.5	ns
t <sub>PLH</sub>	۸	V	C <sub>I</sub> = 50 pF		5	7	1	11	1	9	nc
t <sub>PHL</sub>	А	ī	CL = 50 pr		5	7	1	11	1	9	ns

SCLS596A - NOVEMBER 2004 - REVISED APRIL 2008

# noise characteristics, $V_{CC}$ = 5 V, $C_L$ = 50 pF, $T_A$ = 25°C (see Note 4)

	PARAMETER	MIN	TYP	MAX	UNIT
V <sub>OL(P)</sub>	Quiet output, maximum dynamic V <sub>OL</sub>		0.5		V
V <sub>OL(V)</sub>	Quiet output, minimum dynamic V <sub>OL</sub>		-0.5		V
V <sub>OH(V)</sub>	Quiet output, minimum dynamic V <sub>OH</sub>		4.3		V
V <sub>IH(D)</sub>	High-level dynamic input voltage	4			V
V <sub>IL(D)</sub>	Low-level dynamic input voltage			1	V


NOTE 4: Characteristics are for surface-mount packages only.

# operating characteristics, $V_{CC} = 5 \text{ V}, T_A = 25^{\circ}\text{C}$

	PARAMETER	TEST CO	ONDITIONS	TYP	UNIT
C <sub>pd</sub>	Power dissipation capacitance	No load,	f = 1 MHz	7.3	pF



#### PARAMETER MEASUREMENT INFORMATION



NOTES: A.  $C_L$  includes probe and jig capacitance.

- B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.
- C. All input pulses are supplied by generators having the following characteristics: PRR  $\leq$  1 MHz,  $Z_Q = 50 \Omega$ ,  $t_f \leq 3$  ns,  $t_f \leq 3$  ns.
- D. The outputs are measured one at a time, with one input transition per measurement.
- E. All parameters and waveforms are not applicable to all devices.

Figure 1. Load Circuit and Voltage Waveforms

www.ti.com 23-May-2025

#### PACKAGING INFORMATION

Orderable part number	Status (1)	Material type	Package   Pins	Package qty   Carrier	RoHS	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking (6)
SN74AHCU04QPWRG4Q1	Active	Production	TSSOP (PW)   14	2000   LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 125	AHCU04Q
SN74AHCU04QPWRG4Q1.A	Active	Production	TSSOP (PW)   14	2000   LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 125	AHCU04Q

<sup>(1)</sup> Status: For more details on status, see our product life cycle.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

#### OTHER QUALIFIED VERSIONS OF SN74AHCU04-Q1:

Catalog: SN74AHCU04

<sup>(2)</sup> Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

<sup>(3)</sup> RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

<sup>(4)</sup> Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

<sup>(5)</sup> MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

<sup>(6)</sup> Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

# PACKAGE OPTION ADDENDUM

www.ti.com 23-May-2025

• Enhanced Product : SN74AHCU04-EP

Military: SN54AHCU04

NOTE: Qualified Version Definitions:


- Catalog TI's standard catalog product
- Enhanced Product Supports Defense, Aerospace and Medical Applications
- Military QML certified for Military and Defense Applications

# **PACKAGE MATERIALS INFORMATION**

www.ti.com 24-Jul-2025

## TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

#### QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



#### \*All dimensions are nominal

Device	_	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74AHCU04QPWRG4Q1	TSSOP	PW	14	2000	330.0	12.4	6.9	5.6	1.6	8.0	12.0	Q1

# **PACKAGE MATERIALS INFORMATION**

www.ti.com 24-Jul-2025



## \*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN74AHCU04QPWRG4Q1	TSSOP	PW	14	2000	353.0	353.0	32.0



SMALL OUTLINE PACKAGE



#### NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.

  2. This drawing is subject to change without notice.

  3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not
- exceed 0.15 mm per side.
- 4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
- 5. Reference JEDEC registration MO-153.



SMALL OUTLINE PACKAGE



NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.

7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SMALL OUTLINE PACKAGE



NOTES: (continued)

- 8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
- 9. Board assembly site may have different recommendations for stencil design.



#### IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2025. Texas Instruments Incorporated