SDAS020B - JUNE 1984 - REVISED AUGUST 1995

- Functionally Equivalent to AMD's AM29825
- Improved I<sub>OH</sub> Specifications
- Multiple Output Enables Allow Multiuser Control of the Interface
- Outputs Have Undershoot-Protection Circuitry
- Power-Up High-Impedance State
- Buffered Control Inputs Reduce do Loading Effects
- Package Options Include Plastic Small-Outline (DW) Packages, Ceramic Chip Carriers (FK), and Standard Plastic (NT) and Ceramic (JT) 300-mil DIPs


#### description

These 8-bit flip-flops feature 3-state outputs designed specifically for driving highly capacitive or relatively low-impedance loads. These devices are particularly suitable for implementing multiuser registers, I/O ports, bidirectional bus drivers, and working registers.


With the clock-enable (CLKEN) input low, the eight D-type edge-triggered flip-flops enter data on the low-to-high transitions of the clock (CLK) input. Taking CLKEN high disables the clock buffer, latching the outputs. These devices have noninverting data (D) inputs. Taking the clear (CLR) input low causes the eight Q outputs to go low independently of the clock.

 $\label{eq:multiuser} \begin{array}{l} \underline{\text{Multiuser}} \ \text{buffered} \ \text{output-enable} \ (\text{OE1}, \text{OE2}, \text{and} \\ \overline{\text{OE3}}) \ \text{inputs} \ \text{can} \ \text{be} \ \text{used} \ \text{to} \ \text{place} \ \text{the} \ \text{eight} \ \text{outputs} \\ \text{in either a normal logic state} \ \text{(high or low logic level)} \ \text{or} \ \text{a} \ \text{high-impedance} \ \text{state}. \ \text{In} \ \text{the} \\ \text{high-impedance} \ \text{state}, \ \text{the} \ \text{outputs} \ \text{neither} \ \text{load} \\ \text{nor} \ \text{drive} \ \text{the} \ \text{bus} \ \text{lines} \ \text{significantly}. \ \text{The} \ \text{high-impedance} \ \text{state} \ \text{and} \ \text{increased} \ \text{drive} \ \text{provide} \ \text{the} \\ \text{capability} \ \text{to} \ \text{drive} \ \text{bus} \ \text{lines} \ \text{without} \ \text{interface} \ \text{or} \\ \text{pullup components}. \end{array}$ 

SN54AS825A ... JT PACKAGE SN74AS825A ... DW OR NT PACKAGE (TOP VIEW)



SN54AS825A . . . FK PACKAGE (TOP VIEW)



NC - No internal connection

The output enables do not affect the internal operation of the flip-flops. Old data can be retained or new data can be entered while the outputs are in the high-impedance state.


The SN54AS825A is characterized for operation over the full military temperature range of  $-55^{\circ}$ C to 125°C. The SN74AS825A is characterized for operation from 0°C to 70°C.

SDAS020B - JUNE 1984 - REVISED AUGUST 1995

## FUNCTION TABLE (each flip-flop)

	OUTPUT				
OE†	CLR	CLKEN	CLK	D	Q
L	L	Х	Χ	Х	L
L	Н	L	$\uparrow$	Н	Н
L	Н	L	$\uparrow$	L	L
L	Н	Н	Χ	Χ	$Q_0$
Н	Χ	X	Χ	X	Z


### logic symbol‡



<sup>‡</sup>This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12. Pin numbers shown are for the DW, JT, and NT packages.

SDAS020B - JUNE 1984 - REVISED AUGUST 1995

#### logic diagram (positive logic)



To Seven Other Channels

Pin numbers shown are for the DW, JT, and NT packages.

#### absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage, V <sub>CC</sub>	7 V
Input voltage, V <sub>I</sub>	7 V
Voltage applied to a disabled 3-state output	5.5 V
Operating free-air temperature range, T <sub>A</sub> : SN54AS825A	. −55°C to 125°C
SN74AS825A	0°C to 70°C
Storage temperature range	. −65°C to 150°C

<sup>†</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

### SN54AS825A, SN74AS825A 8-BIT BUS-INTERFACE FLIP-FLOPS WITH 3-STATE OUTPUTS

SDAS020B - JUNE 1984 - REVISED AUGUST 1995

#### recommended operating conditions

			SN	SN54AS825A		SN74AS825A			
			MIN	NOM	MAX	MIN	NOM	MAX	UNIT
VCC	Supply voltage		4.5	5	5.5	4.5	5	5.5	V
VIH	High-level input voltage		2			2			V
V <sub>IL</sub>	Low-level input voltage				0.7			0.8	V
ІОН	High-level output current				-24			-24	mA
lOL	Low-level output current				32			48	mA
	Podes donettes	CLR low	7			4			
t <sub>W</sub> *	Pulse duration	CLK high or low	9.5			8			ns
		CLR inactive	8			8			
t <sub>su</sub> *	Setup time before CLK↑	Data	7			6			ns
		CLKEN high or low	10			6			
th*	Hold time after CLK↑	CLKEN low or data	0			0			ns
TA	Operating free-air temperature	_	-55		125	0		70	°C

<sup>\*</sup> On products compliant to MIL-STD-883, Class B, this parameter is based on characterization data but is not production tested.

# electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

DADAMETED	TEST SOMPLESMS			SN54AS825A			SN74AS825A		
PARAMETER	TEST CO	TEST CONDITIONS			MAX	MIN	TYP <sup>†</sup>	MAX	UNIT
VIK	$V_{CC} = 4.5 \text{ V},$	$I_{I} = -18 \text{ mA}$			-1.2			-1.2	V
	$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V},$	I <sub>OH</sub> = −2 mA	V <sub>CC</sub> -2	2		V <sub>CC</sub> -2	)		
VOH	V 45V	$I_{OH} = -15 \text{ mA}$	2.4	3.2		2.4	3.2		V
	V <sub>CC</sub> = 4.5 V	$I_{OH} = -24 \text{ mA}$	2			2			
V	V 45V	I <sub>OL</sub> = 32 mA		0.3	0.5				.,
VOL	$V_{CC} = 4.5 \text{ V}$	I <sub>OL</sub> = 48 mA					0.35	0.5	V
lozh	V <sub>CC</sub> = 5.5 V,	V <sub>O</sub> = 2.7 V			50			50	μΑ
lozL	V <sub>CC</sub> = 5.5 V,	V <sub>I</sub> = 0.4 V			-50			-50	μΑ
l <sub>l</sub>	$V_{CC} = 5.5 V,$	V <sub>I</sub> = 7 V			0.1			0.1	mA
lН	$V_{CC} = 5.5 V,$	V <sub>I</sub> = 2.7 V			20			20	μΑ
I <sub>IL</sub>	V <sub>CC</sub> = 5.5 V,	V <sub>I</sub> = 0.4 V			-0.5			-0.5	mA
IO <sup>‡</sup>	V <sub>CC</sub> = 5.5 V,	V <sub>O</sub> = 2.25 V	-30		-112	-30		-112	mA
		Outputs high		45	73		45	73	
Icc	V <sub>CC</sub> = 5.5 V	Outputs low		56	90		56	90	mA
		Outputs disabled		59	95		59	95	

<sup>†</sup> All typical values are at  $V_{CC} = 5 \text{ V}$ ,  $T_A = 25^{\circ}\text{C}$ .


<sup>&</sup>lt;sup>‡</sup>The output conditions have been chosen to produce a current that closely approximates one half of the true short-circuit output current, los.

### switching characteristics (see Figure 1)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	V <sub>C</sub> C <sub>L</sub> R1 R2 T <sub>A</sub>	UNIT			
		SN54AS825A SN74AS825A					1 1
			MIN	MAX	MIN	MAX	
<sup>t</sup> PLH	CLK	A O	3.5	9	3.5	7.5	
t <sub>PHL</sub>	CLK	Any Q	3.5	13.5	3.5	13	ns
<sup>t</sup> PHL	CLR	Any Q	3.5	16.5	3.5	15.5	ns
<sup>t</sup> PZH	ŌĒ	Any Q	4	12	4	11	20
<sup>t</sup> PZL	ÜE		4	13	4	12	ns
<sup>t</sup> PHZ	ŌĒ	Any Q	1	10	1.5	8	ne
t <sub>PLZ</sub>	JE JE	Ally Q	1	10	1.5	8	ns

<sup>†</sup> For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

# PARAMETER MEASUREMENT INFORMATION SERIES 54ALS/74ALS AND 54AS/74AS DEVICES



- NOTES: A. C<sub>L</sub> includes probe and jig capacitance.
  - B. Waveform 1 is for an output with internal conditions such that the output is low except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high except when disabled by the output control.
  - C. When measuring propagation delay items of 3-state outputs, switch S1 is open.
  - D. All input pulses have the following characteristics: PRR  $\leq$  1 MHz,  $t_f = t_f = 2$  ns, duty cycle = 50%.
  - E. The outputs are measured one at a time with one transition per measurement.

Figure 1. Load Circuits and Voltage Waveforms



www.ti.com 29-May-2025

#### PACKAGING INFORMATION

Orderable part number	Status (1)	Material type	Package   Pins	Package qty   Carrier	RoHS	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking (6)
5962-9078003M3A	Active	Production	LCCC (FK)   28	42   TUBE	No	SNPB	N/A for Pkg Type	-55 to 125	5962- 9078003M3A SNJ54AS 825AFK
SNJ54AS825AFK	Active	Production	LCCC (FK)   28	42   TUBE	No	SNPB	N/A for Pkg Type	-55 to 125	5962- 9078003M3A SNJ54AS 825AFK
SNJ54AS825AFK.A	Active	Production	LCCC (FK)   28	42   TUBE	No	SNPB	N/A for Pkg Type	-55 to 125	5962- 9078003M3A SNJ54AS 825AFK

<sup>(1)</sup> Status: For more details on status, see our product life cycle.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative

<sup>(2)</sup> Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

<sup>(3)</sup> RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

<sup>(4)</sup> Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

<sup>(5)</sup> MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

<sup>(6)</sup> Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.



#### PACKAGE OPTION ADDENDUM

www.ti.com 29-May-2025

and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

## FK (S-CQCC-N\*\*)

### LEADLESS CERAMIC CHIP CARRIER

28 TERMINAL SHOWN



NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a metal lid.
- D. Falls within JEDEC MS-004



#### IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2025. Texas Instruments Incorporated